

# JURASSIC PARK

## SERVICE AND OPERATION MANUAL



### **WARNING**

**IMPORTANT HEALTH WARNING: PHOTOSENSITIVE SEIZURES** - A very small percentage of people may experience a seizure when exposed to certain visual images, including flashing lights or patterns. Even people with no history of seizures or epilepsy may have an undiagnosed condition that can cause "photosensitive epileptic seizures" due to certain visual images, flashing lights or patterns. Symptoms can include lightheadedness, altered vision, eye or face twitching, jerking or shaking of arms or legs, disorientation, confusion, momentary loss of awareness, and loss of consciousness or convulsions that can lead to injury from falling down or striking nearby objects.

IMMEDIATELY STOP PLAYING AND CONSULT A DOCTOR IF YOU EXPERIENCE ANY OF THESE SYMPTOMS.

### **ATTENTION! IMPORTANT WARRANTY INFORMATION**

The electronics system, node network architecture, mechanical devices and associated software control systems in this pinball machine are designed to work with genuine Stern Pinball accessories and devices.

Installation of non-authorized accessories, lamps, LED's, motors or other devices or modification of electro-mechanical devices may damage the system and will void your warranty.

Stern Pinball machines are assembled in Elk Grove Village, Illinois, USA. Stern Pinball has inspected each game element to ensure it meets our quality standards.

Each pinball machine has unique characteristics that make it a one-of-a-kind American made product. Each will have variations in appearance resulting from differences in the machine's particular wood parts, individual printed art and mechanical assemblies. No playfield is perfectly flat and varies depending on the season. Game play will result in playfield dimpling as the harder steel ball contacts the wood and coating; over time multiple dimples will blend to make them less noticeable. Normal plastic insert crazing (tiny stress cracks) and ghosting (small cloudy areas around insert edges) are often seen in pinball machines, due to a combination of plastic mold stress, pushing of inserts into purposely undersized holes, and heating and breaking of inserts' plastic "skin" when the playfield is sanded.

© Universal City Studios LLC and Amblin Entertainment, Inc. All Rights Reserved.

Games configured for North America operate on 60 cycle electricity only. These games will not operate in countries with 50 cycle electricity (Europe, UK, Australia).



MANUAL #780-50M2-00  
JURASSIC PARK LE #500-55M2-01  
JURASSIC PARK PREMIUM #500-55M3-01

1-800-KICKERS - [parts.service@sternpinball.com](mailto:parts.service@sternpinball.com)  
[www.sternpinball.com](http://www.sternpinball.com) - [facebook.com/sternpinball](https://facebook.com/sternpinball)

# TABLE OF CONTENTS

|                                                        |          |
|--------------------------------------------------------|----------|
| <b>1. Setup and Moving .....</b>                       | <b>3</b> |
| 1.1 First-Time Setup Instructions.....                 | 3        |
| 1.2 Adjustments Menu .....                             | 6        |
| 1.3 Transporting the Game .....                        | 7        |
| 1.4 Maintenance .....                                  | 8        |
| 1.5 Maintenance Kits .....                             | 8        |
| 1.6 Common Parts.....                                  | 8        |
| <b>2. SPIKE System and Node Guide .....</b>            | <b>9</b> |
| 2.1 SPIKE System Overview .....                        | 9        |
| 2.2 Node Bus Cabling .....                             | 9        |
| 2.3 System Power .....                                 | 9        |
| 2.4 SPIKE Node Addresses .....                         | 9        |
| 2.5 SPIKE Node Programming.....                        | 10       |
| 2.6 SPIKE System Terminology .....                     | 10       |
| 2.7 Common SPIKE Node Boards.....                      | 10       |
| <b>3. Light, Switch, and Driver Reference... 11</b>    |          |
| 3.1 SPIKE Node Boards.....                             | 11       |
| 3.2 Driver Reference .....                             | 12       |
| 3.3 Switch Reference.....                              | 14       |
| 3.4 Light Reference.....                               | 18       |
| 3.5 Motor Reference .....                              | 23       |
| <b>4. Electronic Pinouts and Schematics.... 24</b>     |          |
| 4.1 SPIKE-2 CPU Node 0 .....                           | 24       |
| 4.2 Cabinet Node 1 .....                               | 28       |
| 4.3 Lower Playfield 48V Driver Pinout Node 8 .....     | 29       |
| 4.4 Mid Upper Playfield 48V Driver Pinout Node 9 ..... | 30       |
| 4.5 Lower Mid LED Board 8b.....                        | 31       |
| 4.6 Lower Left LED Board 8b1.....                      | 32       |
| 4.7 Upper Mid LED Board 8b2.....                       | 32       |
| 4.8 Lower Right LED Board 8b4 .....                    | 32       |
| 4.9 Upper Right LED Board 8b3 .....                    | 33       |
| 4.10 Upper Left LED Board 9a.....                      | 33       |
| 4.11 Serial Motor Driver Board 9b .....                | 34       |
| 4.12 Stepper Motor Driver Board.....                   | 34       |
| 4.13 Trough Serial Opto Receiver Extension 8a .....    | 35       |
| 4.14 Trough Serial Opto Transmitter .....              | 35       |
| 4.15 Dual Interrupter Opto .....                       | 35       |
| 4.16 Main Power Supply.....                            | 35       |
| 4.17 Power Distribution Board.....                     | 36       |
| 4.18 Power Plug Wiring.....                            | 36       |
| <b>5. Parts Reference..... 37</b>                      |          |
| 5.1 Playfield Rubber Parts .....                       | 37       |
| 5.2 Rubber Size Chart.....                             | 37       |
| 5.3 Playfield Assemblies, Top .....                    | 38       |
| 5.4 Playfield Assemblies, Bottom .....                 | 39       |
| 5.5 Backbox Parts.....                                 | 40       |
| 5.6 Speaker Panel Parts .....                          | 40       |
| 5.7 Cabinet Parts .....                                | 41       |
| 5.8 Ball Shooter Assembly.....                         | 42       |
| 5.9 Auto Launch Assembly .....                         | 42       |
| 5.10 Ball Trough Assembly.....                         | 43       |
| 5.11 Slingshot Assembly.....                           | 43       |

|                                             |    |
|---------------------------------------------|----|
| 5.12 Flipper Assembly, Left.....            | 44 |
| 5.13 Flipper Assembly, Right .....          | 44 |
| 5.14 Pop Bumper Assembly .....              | 45 |
| 5.15 Ball Guide Assembly .....              | 46 |
| 5.16 One Way Gate Assembly .....            | 46 |
| 5.17 Orbit Opto Assembly .....              | 46 |
| 5.18 Pop Bumper Gate Assembly .....         | 46 |
| 5.19 Right Ramp Rollunder Assembly .....    | 47 |
| 5.20 Right Wire Ramp Assembly .....         | 47 |
| 5.21 Stainless Steel Up-Post Assembly ..... | 47 |
| 5.22 Moto 2-Bank Carriage Assembly .....    | 48 |
| 5.23 Moto 2-Bank Main Assembly.....         | 48 |
| 5.24 Plastic 03 Assembly.....               | 49 |
| 5.25 Plastic 04 Assembly.....               | 49 |
| 5.26 Plastic 05 Assembly.....               | 50 |
| 5.27 Plastic 08 Assembly.....               | 50 |
| 5.28 Plastic 09 Assembly.....               | 50 |
| 5.29 Plastic 11 Assembly.....               | 51 |
| 5.30 Plastic 12 Assembly.....               | 51 |
| 5.31 Plastic 15 Assembly.....               | 51 |
| 5.32 Plastic 16 Assembly.....               | 52 |
| 5.33 Plastic 19 Assembly.....               | 52 |
| 5.34 Plastic 23 Assembly.....               | 53 |
| 5.35 Plastic 24 Assembly.....               | 53 |
| 5.36 Plastic 39 Assembly.....               | 54 |
| 5.37 Plastic 44 Assembly.....               | 54 |
| 5.38 Plastic 47 Assembly.....               | 54 |
| 5.39 Plastic 63 Assembly.....               | 55 |
| 5.40 Plastic 64 Assembly.....               | 55 |
| 5.41 Plastic 81 Assembly.....               | 55 |
| 5.42 Plastic 82 Assembly.....               | 55 |
| 5.43 Left Halfpipe Assembly .....           | 56 |
| 5.44 Left Ramp Assembly .....               | 56 |
| 5.45 Right Ramp Assembly .....              | 57 |
| 5.46 Right Halfpipe Assembly.....           | 57 |
| 5.47 Helicopter Sensor Assembly.....        | 57 |
| 5.48 T-Rex Main Assembly .....              | 58 |
| 5.49 T-Rex Up-Down Tilt Assembly .....      | 59 |
| 5.50 T-Rex Crank Assembly.....              | 59 |
| 5.51 T-Rex Motor Frame Assembly .....       | 59 |
| 5.52 T-Rex Head Assembly, Top .....         | 60 |
| 5.53 T-Rex Head Assembly, Bottom .....      | 60 |
| 5.54 T-Rex Head Assembly.....               | 61 |
| 5.55 T-Rex Jaw Assembly.....                | 61 |
| 5.56 T-Rex Jaw Slider Assembly.....         | 61 |
| 5.57 Truck Spinner Top Assembly.....        | 62 |
| 5.58 Truck Decal Assembly.....              | 62 |
| 5.59 Truck Spinner Bottom Assembly .....    | 62 |
| 5.60 Back Panel Assembly .....              | 63 |

|                                                  |           |
|--------------------------------------------------|-----------|
| <b>6. Specifications .....</b>                   | <b>64</b> |
| 6.1 Game Dimensions.....                         | 64        |
| 6.2 Warranty.....                                | 65        |
| 6.3 Warnings, Compliance, and Legal Notices..... | 65        |

# 1. SETUP AND MOVING


## 1.1 FIRST-TIME SETUP INSTRUCTIONS

Your brand new Stern Pinball Machine is carefully packed for safety and security. For your safety, exercise caution and use the correct tools and sufficient help when setting up your new game.


### TOOLS REQUIRED

- 5/8" Socket Wrench
- Utility Knife
- Snips
- An Assistant


**CAUTION: AT LEAST TWO (2) PEOPLE ARE REQUIRED TO MOVE AND MANEUVER THE GAME. USE PROPER MOVING EQUIPMENT AND EXTREME CARE WHILE HANDLING. STERN PINBALL MACHINES WEIGH OVER 250LBS BOXED.**




1. Locate the side labeled "TRUCK THIS SIDE ONLY". The bottom of the game faces this side.
2. Open the top box flaps by pulling hard in an upward motion on each flap. If the flaps are taped, cut the tape first, taking care to avoid the box staples.




3. Remove the four (4) foam pieces and two (2) narrow box tubes which contain the four (4) identical legs with levelers.
4. DO NOT CUT STRAPPING YET. Keep backbox secured in the down position.
5. With the utility knife, carefully cut down the left and right corners of the box.




6. Let the face fall forward and remove the entire side by carefully cutting the bottom.
7. With the game still in its folded position, use a 5/8" wrench to loosen and remove the 2 leg bolts on each side of the front cabinet. Ensure the leg levelers are screwed all the way into the legs.



8. Install front legs using the bolts removed from the cabinet. Secure tightly.
9. Have someone help you carefully set the game down on the front legs.



10. Set aside the open box.
11. With a 5/8" socket wrench, loosen and remove the 2 leg bolts on each side of the rear cabinet, 4 total.




12. Using supports or two people, prop the rear of the cabinet up.
13. Ensure the rear leg levelers are screwed all the way into the legs.
14. Install rear legs using the 4 bolts removed from step 11.




## FIRST-TIME SETUP CONTINUED




15. Cut nylon strapping and remove protective strap corner guards.
16. Locate the factory keys, either on the shooter rod or taped to the playfield glass.
17. Using snips, cut the tie-wrap securing the keys if required. One set of keys is for the front coin door, the other set of keys is for accessing components in the backbox.




18. Open the front coin door.
19. Reach into the game and remove the retaining clip at the rear of the cash box.
20. Remove the cash box lid by sliding it toward you.



21. Store the backbox keys, if desired, on the metal hook located in the coin door.
22. Locate and remove the pinballs, plumb bob, and backbox bolts from the cash box.
23. Replace the cash box lid and retaining clip for future use.



24. Locate the two (2) backbox bolts in the cash box.
25. Carefully raise backbox to upright position while ensuring that cables are not pinched.
26. Use the  $\frac{5}{8}$ " wrench to install the two (2) backbox bolts to secure the backbox as indicated on the back of the cabinet.



27. Reach inside the cabinet and lift the two latches located on either side of the coin door.
28. Remove the front top molding.



29. Remove the playfield glass by sliding it toward you and carefully place it in a safe location. Remove all playfield shipping tie downs, shipping blocks, and packing foam, and follow any game-specific unpacking instructions included in the playfield, if present.

**CAUTION: PLAYFIELD GLASS IS MADE FROM HIGH-STRENGTH TEMPERED GLASS. TEMPERED GLASS IS SENSITIVE TO EXTREME TEMPERATURE SHIFTS AND CORNER NICKS, WHICH CAN CAUSE THE GLASS TO FAIL CATASTROPHICALLY. TAKE CARE TO STORE THE GLASS ON A SOFT, ROOM-TEMPERATURE SURFACE AND PREVENT THE CORNERS FROM BEING DAMAGED.**



## FIRST-TIME SETUP CONTINUED

30. If pinballs were already installed into the lower ball trough, remove them before lifting the playfield.
31. Grasp the lower arch between the flippers, and firmly but gently pull directly up to raise the playfield 8 to 12 inches.
32. While holding the playfield up, pull the playfield toward you until the two playfield supports are over the front edge of the cabinet.
33. Rest the playfield on the front edge of the cabinet.
34. Raise the playfield and rest it against the backbox.
35. Visually inspect all cabinet cables and connector terminations; ensure no wires or cables are pinched and that cable harnesses are not pulled tight.
36. Locate the plumb bob in the parts bag in the cash box.
37. Slide plumb bob onto the hanger wire. Note: the vertical position of the plumb bob affects tilt sensitivity - higher makes the game more sensitive to tilting.
38. Tighten the thumb screw finger-tight.
39. Install the correct number of pinballs. Refer to the decal on the lock down assembly for the correct number of pinballs.

## LOCATING, LEVELING, AND FINAL SETUP

1. Select a location that is indoors, out of direct sunlight, and climate controlled. Excessive moisture/humidity can cause long-term damage to your game.
2. Adjust the front or rear levelers as necessary to position the playfield level bubble, located on the front right of the playfield next to the shooter lane, to float between the two (2) black lines. This will place the playfield at the recommended 6.5° pitch. Playfield angles greater than 6.5° can be achieved by turning out the rear leg leveler(s) for increased difficulty and faster gameplay.
3. Use a pinball to roll down the center of the playfield for side-to-side leveling, or use an external bubble level, digital level, or smartphone level app.
4. Plug into a grounded outlet and check for proper operation through DIAGNOSTICS.
5. Check the coin door: With the door closed, insert coins to verify proper operation.
6. Play game: Check for satisfactory operation and adjust game volume (push the Red Buttons inside the Coin Door).
7. If desired, perform any game diagnostics, game adjustments, and pricing settings at this time.



## SPIKE PINBALL SOFTWARE UPDATE INSTRUCTIONS

1. Obtain game software update file (filename ends in ".spk") from [www.sternpinball.com](http://www.sternpinball.com) or from authorized Stern distributor.
2. Place game software update file ( ".spk") in root directory of a blank FAT32-formatted USB flash drive
3. Use backbox power switch to turn off game
4. Plug in USB flash drive to CPU board USB connector (CN20 or CN21). Refer to [www.sternpinball.com](http://www.sternpinball.com)
5. Turn on game
6. The game will automatically begin software update
7. Select the correct .spk update file from list.
8. Press Enter on the service switches to start update
9. When the display indicates "Update Complete", turn off game
10. Remove USB flash drive from CPU board
11. Turn game on to complete the update and play pinball!
12. Detailed instructions and troubleshooting tips are available in the game manual, [www.sternpinball.com](http://www.sternpinball.com) and authorized Stern distributors.

## 1.2 ADJUSTMENTS MENU

### STANDARD ADJUSTMENTS

Perform the below steps to review the adjustments.

Enter the Service Menu, then enter the Standard Adjustments Menu.

Press SELECT. Press BACK to exit or escape at any time.

Press [>]. Go to the ADJ icon. Press SELECT.

Go to the S.P.I. icon. Press SELECT.

| ID | Adjustment Name       | Default Setting |
|----|-----------------------|-----------------|
| 1  | REPLAY TYPE           | AUTO            |
| 2  | REPLAY PERCENTAGE     | 10%             |
| 3  | REPLAY AWARD          | CREDIT          |
| 4  | REPLAY LEVELS         | 1               |
| 5  | AUTO REPLAY START     | 20,000,000      |
| 6  | DYNAMIC REPLAY START  | 60,000,000      |
| 7  | REPLAY LEVEL #1       | 15,000,000      |
| 8  | REPLAY LEVEL #2       | 30,000,000      |
| 9  | REPLAY LEVEL #3       | 45,000,000      |
| 10 | REPLAY LEVEL #4       | 60,000,000      |
| 11 | REPLAY BOOST          | YES             |
| 12 | SPECIAL LIMIT         | 1               |
| 13 | SPECIAL PERCENTAGE    | 10%             |
| 14 | SPECIAL AWARD         | CREDIT          |
| 15 | FREE GAME LIMIT       | 5               |
| 16 | EXTRA BALL LIMIT      | 5               |
| 17 | EXTRA BALL PERCENTAGE | 25%             |
| 18 | GAME PRICING          | USA 11          |
| 19 | MATCH PERCENTAGE      | 9%              |
| 20 | MATCH AWARD           | CREDIT          |
| 21 | BALLS PER GAME        | 3               |
| 22 | TILT WARNINGS         | 2               |
| 23 | TILT DEBOUNCE         | 1000            |
| 24 | CREDIT LIMIT          | 30              |
| 25 | ALLOW HIGH SCORES     | YES             |
| 26 | HIGH SCORE AWARD      | CREDIT          |
| 27 | GRAND CHAMPION AWARDS | 1               |
| 28 | HIGH SCORE #1 AWARDS  | 1               |
| 29 | HIGH SCORE #2 AWARDS  | 0               |
| 30 | HIGH SCORE #3 AWARDS  | 0               |
| 31 | HIGH SCORE #4 AWARDS  | 0               |
| 32 | GRAND CHAMPION SCORE  | 75,000,000      |
| 33 | HIGH SCORE #1         | 55,000,000      |
| 34 | HIGH SCORE #2         | 40,000,000      |
| 35 | HIGH SCORE #3         | 30,000,000      |
| 36 | HIGH SCORE #4         | 25,000,000      |
| 37 | HSTD INITIALS         | 3 INITIALS      |

### FEATURE ADJUSTMENTS

Each table has feature adjustments specific to the characteristics of that game. To access feature adjustments enter the Service Menu and then enter the Adjustments Menu.

Press SELECT to access the Service Menu. Press BACK to exit or escape at any time.

Press [>]. Go to the ADJ icon. Press SELECT.

STANDARD ADJUSTMENT #1 appears with the adjustment name flashing. While the adjustment name is flashing press [<] [>] to move between adjustments.

To change the adjustment setting press SELECT. While the adjustment setting is flashing, press [<] [>] repeatedly until the desired setting appears. Press the SELECT button to “install” the change. The adjustment comment (bottom line) will indicate if the factory default setting is selected or will display INSTALLED if the change is not a factory default setting.

| ID | Adjustment Name                       | Default Setting       |
|----|---------------------------------------|-----------------------|
| 38 | HSTD RESET COUNT                      | 2000                  |
| 39 | FREE PLAY                             | NO                    |
| 40 | LANGUAGE                              | ENGLISH               |
| 41 | PLAYER LANGUAGE SELECT                | YES                   |
| 42 | CUSTOM MESSAGE                        | ON                    |
| 43 | KNOCKER VOLUME                        | NORMAL                |
| 44 | GAME START                            | NO                    |
| 45 | GAME RESTART                          | YES                   |
| 46 | BALL SAVE TIME                        | 0:05                  |
| 47 | TIMED PLUNGER                         | OFF                   |
| 48 | FLIPPER BALL LAUNCH                   | OFF                   |
| 49 | COINDOOR BALL SAVER                   | OFF                   |
| 50 | COMPETITION MODE                      | NO                    |
| 51 | FAST BOOT                             | YES                   |
| 52 | Q24 OPTION                            | COIN METER            |
| 53 | TICKET DISPENSER                      | NO                    |
| 54 | PLAYER COMPETITION MODE               | YES                   |
| 55 | LOCATION ID                           | 0                     |
| 56 | GAME ID                               | 0                     |
| 57 | TIME FORMAT                           | 12-HOUR               |
| 58 | COIN INPUT DELAY                      | 30                    |
| 59 | LOST BALL RECOVERY                    | YES                   |
| 60 | COINDOOR DISABLE TILT                 | NO                    |
| 61 | COINDOOR OPEN NODE BUS POWER          | NO                    |
| 62 | PLAY ATTRACT TUTORIAL VIDEOS          | YES                   |
| 63 | EXTERNAL VOLUME KNOB FUNCTION         | HEADPHONE VOLUME ONLY |
| 64 | MUTE CABINET WHEN HEADPHONES DETECTED | YES                   |
| 65 | GI LED BRIGHTNESS                     | 100%                  |
| 66 | GI LED MAX BRIGHTNESS                 | 255                   |
| 67 | INSERT LED BRIGHTNESS                 | 100%%                 |
| 68 | INSTER LED MAX BRIGHTNESS             | 255%                  |
| 69 | FLASHER LED BRIGHTNESS                | 100%                  |
| 70 | FLASHER LED MAX BRIGHTNESS            | 255                   |
| 71 | ATTRACT MODE BACKBOX BRIGHTNESS       | 100%                  |
| 72 | GAMEPLAY BACKBOX BRIGHTNESS           | 100%                  |
| 73 | COINDOOR OPEN BACKBOX BRIGHTNESS      | 2%                    |

Go to the game icon. Press SELECT.


FEATURE ADJUSTMENT #1 appears with the adjustment name flashing. With the adjustment name flashing press [<] [>] to move between adjustments. Feature adjustments are changed similarly to standard adjustments using the SELECT button to choose options and the [<] [>] buttons to cycle through available settings.

## 1.3 TRANSPORTING THE GAME

When transporting the game, such as in the back of a truck or with a hand truck, the game's backbox must be secured to prevent damage to the side rails.

### 1. SECURE THE BACKBOX

1. Ensure that the pinballs are removed from the playfield, and secure any free-moving mechanisms that may get damaged in transport



2. Remove the backbox securing bolts
3. Carefully lower the backbox onto the side rails. Use a piece of cardboard or suitable padding between the backbox and the game.

### TOOLS REQUIRED


- STRAP (500LB OR GREATER)
- AN ASSISTANT
- HAND TRUCK



### CAUTION


**NEVER TRANSPORT THE GAME IN A MOVING VEHICLE WITH THE BACKBOX RAISED! TWO PEOPLE ARE REQUIRED TO REMOVE THE LEGS!**

### 2. REMOVE THE LEGS AND STAND UP




4. Securely strap the back box to the game
5. The game may be transported with the legs on. If the legs must be removed, follow the remaining steps.


6. Remove the legs, rear legs first. Use a stool or a friend to support the rear of the game.
7. Rest the rear of the game on the ground.



8. Stand the game up on its back.



9. Remove the front two legs.



10. Secure all loose parts and transport with a hand truck in the upright position.

## 1.4 MAINTENANCE

### REGULAR MAINTENANCE - (MONTHLY/500 GAMES)

- Remove the playfield glass
- Enter the software diagnostics menu, start lamp test, then clean and wax the playfield.
- While cleaning the playfield, identify and repair malfunctioning lights, loose parts, cracked plastics and worn rubber parts.
- While in diagnostics, enter the switch test (Select the "SW" icon, then "TEST" icon).
- Use a pinball to actuate all switches and verify the correct switch registers with the switch test.
- The game will play a sound to confirm the switch.
- Lift the playfield and inspect all assemblies for loose parts, broken wires or excessive wear. Look at the bottom of the cabinet for any parts that may have worked loose, then find the source.
- Check all coin door mechanisms and bill acceptor (if installed) for proper operation
- Play the game to ensure all coils and features are working
- Check the playfield to ensure it is level and set to the proper pitch using the bubble level on the right side wood rail.
- Check game audits: Replay % and Ball Time and note abnormal values which can indicate problems.
- Ensure game volume is set appropriately for the location.
- Clean both sides of the playfield glass and reinstall.
- Check and clean pinballs and replace if excessively worn or scuffed. Dirty pinballs accelerate game wear.

### OVERHAUL MAINTENANCE - (5000 GAMES)

- Verify latest game software is installed
- Check flippers for excessive wear. Excessive flipper sloppiness (vertical or horizontal) or weakness indicates a flipper rebuild is required.
- Clean machine inside and out and check leg levelers for free operation.
- Visual check for loose or broken playfield and cabinet parts and repair as necessary.
- Electrical check: Plug into grounded outlet and check for proper operation through DIAGNOSTICS.
- Replace worn or dirty rubbers.
- Replace pinballs.
- Check all playfield switches with a pinball.
- Check all settings (refer to manual for factory settings).
- Check coin door: With door closed, insert coins to verify proper operation.
- Check for proper adjustment of the plumb bob tilt.
- Play game: Check for satisfactory operation.

### COMMON PINBALL TOOLS

- Common nut drivers (1/4", 5/16", 11/32", 3/8")
- Phillips screwdriver
- Standard Allen wrench/Hex key set
- 3/8" Socket with ratchet
- Adjustable wrench (5/8" & 9/16")
- 6" Torpedo Level (or use a pinball)
- Flashlight or headlamp
- Soldering Iron (60w with flat tip), lead-free solder
- Wire cutter
- Wire stripper
- Long nose ("needle nose") pliers

## 1.5 MAINTENANCE KITS

| Description                                            | Part Number |
|--------------------------------------------------------|-------------|
| Jurassic Park LE/Premium Maintenance Kit               | 502-6002-M2 |
| 8 oz pinball playfield wax (Novus # 2) (675-0003-01)   | 502-6002-M3 |
| Standard Pinball (260-5000-00)                         |             |
| Cleaning Cloth                                         |             |
| All Playfield Rubber Rings                             |             |
| Spare Fuses                                            |             |
| Jurassic Park LE/Premium Deluxe Maintenance Kit        | 502-6003-M2 |
| All standard kit items, plus:                          | 502-6003-M3 |
| Flipper rebuild kits, Left and Right (500-6307-10,-00) |             |
| Jurassic Park LE Playfield Plastics Kit                | 803-5000-M2 |
| Jurassic Park Premium Playfield Plastics Kit           | 803-5000-M3 |
| Jurassic Park LE Playfield Decals Kit                  | 802-5000-M2 |
| Jurassic Park Premium Playfield Decals Kit             | 802-5000-M3 |
| Jurassic Park LE Backbox Decal Left                    | 820-76M2-01 |
| Jurassic Park Premium Backbox Decal Left               | 820-76M3-01 |
| Jurassic Park LE Backbox Decal Right                   | 820-76M2-02 |
| Jurassic Park Premium Backbox Decal Right              | 820-76M3-02 |
| Jurassic Park LE Cabinet Decal Left                    | 820-76M2-03 |
| Jurassic Park Premium Cabinet Decal Left               | 820-76M3-03 |
| Jurassic Park LE Cabinet Decal Right                   | 820-76M2-04 |
| Jurassic Park Premium Cabinet Decal Right              | 820-76M3-04 |
| Jurassic Park LE Cabinet Decal Front                   | 820-76M2-05 |
| Jurassic Park Premium Cabinet Decal Front              | 820-76M3-05 |
| Jurassic Park LE Playfield, Bare                       | 830-5000-M2 |
| Jurassic Park Premium Playfield, Bare                  | 830-5000-M3 |
| Jurassic Park LE Mirror Backglass                      | 830-8426-M2 |
| Jurassic Park Premium Translite Backglass              | 830-8427-M3 |

## 1.6 COMMON PARTS

| Description                            | Part Number |
|----------------------------------------|-------------|
| 8 oz Pinball Playfield wax (Novus # 2) | 675-0003-01 |
| Standard Pinball, 1-1/16 in            | 260-5000-00 |
| Flipper Rebuild Kit Left (Standard)    | 500-6307-10 |
| Flipper Base Plate Kit Left            | 515-6617-01 |
| Flipper Rebuild Kit Right              | 500-6307-00 |
| Flipper Base Plate Kit Right           | 515-6617-00 |

## 2. SPIKE SYSTEM AND NODE GUIDE

### 2.1 SPIKE SYSTEM OVERVIEW

The SPIKE Pinball system is a rugged, distributed, and embedded platform custom-designed for the rigors of the pinball machine environment. SPIKE takes advantage of modern technologies to deliver an immersive pinball experience that supports modern features, reduces cabling, and increases serviceability and reliability.

A Stern Pinball machine based on the SPIKE system will have at least two nodes networked together with the SPIKE node bus, a custom industrial pinball control bus that is designed around industry standards and optimized for the pinball environment. The primary CPU node is networked to one or more input/output nodes over standard Category 5 UTP (unshielded twisted pair) ethernet cabling.

There are five primary types of nodes that are found in the game.

- CPU node (Node 0) - The primary node that controls other nodes in the system. Contains the primary game software for the system and provides SPIKE node bus power for other nodes.
- Cabinet 48V node (Node 1) - Specialized node with specific inputs and outputs for coin doors, tilt mechanisms, and other bottom-cabinet devices.
- 48V playfield node - Controls high power devices such as coils and flashers, and also supports a few switch and low-power outputs. Powered by the system 48V power supply.
- Light and switch node - High-density switch and low-power LED outputs, bus-powered from the node bus. These boards contain as many as 32 switch inputs and light outputs.
- Node extensions - These sub-nodes add additional low-power input and outputs to a specific Power or I/O node and are connected with simple serial bus.

### 2.2 NODE BUS CABLING

The SPIKE node bus utilizes standard Ethernet-style RJ45 8-pin modular jacks, and off-the-shelf Category 5e or better ethernet cabling. The node bus is electrically different from Ethernet and does not utilize Ethernet or TCP/IP protocols or signaling standards. SPIKE nodes are not compatible with standard computer networking equipment.

**CAUTION:** Plugging a SPIKE Node or CPU board into a standard Ethernet port may damage one or both devices and void your warranty.

### 2.3 SYSTEM POWER

The SPIKE System is powered from an 48V DC power supply bus. Each SPIKE node converts this voltage to lower voltages required by the node and its specific components. A SPIKE 48V node typically controls high-power outputs such as game coil mechanisms and high-brightness LEDs. These powered nodes are supplied directly with 48V system power. SPIKE standard I/O nodes are low-power nodes that read switch inputs and output to standard-brightness LEDs. Standard I/O nodes use the node bus power, which is supplied by the main CPU node over the node bus modular jack connectors.

### 2.4 SPIKE NODE ADDRESSES

Each SPIKE node has a unique address ranging from 0 to 15. Not all addresses are used in all games. Nodes can be of the same part number, so the address is specified on the DIP switches on each node. When replacing a node, be certain that the correct address is set. Nodes can have 3-position and 4-position DIP switches. Refer to the appropriate table to set the address for each type of Node. The correct address for a node can be found in the SPIKE node reference section of the manual or in the game diagnostic software. Address 0 is reserved for the backbox CPU node, where the game software resides. Address 1 is reserved for the cabinet node, located inside the coin door. These two nodes do not have DIP switches as their address is not configurable.

| Address | 1   | 2   | 3   |
|---------|-----|-----|-----|
| 8       | OFF | OFF | OFF |
| 9       | OFF | OFF | ON  |
| 10      | OFF | ON  | OFF |
| 11      | OFF | ON  | ON  |
| 12      | ON  | OFF | OFF |
| 13      | ON  | OFF | ON  |
| 14      | ON  | ON  | OFF |
| 15      | ON  | ON  | ON  |

SPIKE node addresses for nodes with 3-position DIP switches. Addresses 0-7 are not used by SPIKE nodes with 3-position DIP switches.

| Address | 1   | 2   | 3   | 4   |
|---------|-----|-----|-----|-----|
| 8       | OFF | OFF | OFF | OFF |
| 9       | OFF | OFF | ON  | OFF |
| 10      | OFF | ON  | OFF | OFF |
| 11      | OFF | ON  | ON  | OFF |
| 12      | ON  | OFF | OFF | OFF |
| 13      | ON  | OFF | ON  | OFF |
| 14      | ON  | ON  | OFF | OFF |
| 15      | ON  | ON  | ON  | OFF |

SPIKE node addresses for nodes with 4-position DIP switches. Addresses 0-7 are reserved for fixed-function nodes and do not require configuration.

## SPIKE SYSTEM AND NODE GUIDE CONTINUED

### 2.5 SPIKE NODE PROGRAMMING

The SPIKE nodes are smart nodes that have on-board processors and run embedded code. The nodes are programmed automatically by the CPU node whenever software updates are installed to the CPU. When replacing a node, the CPU node will detect and update the node to the latest software with no user intervention. Always replace nodes with the power to the game turned OFF.

### 2.6 SPIKE SYSTEM TERMINOLOGY

#### MULTI GENERAL ILLUMINATION LIGHTING

General Illumination Lighting is two or more lights powered by one control source. These are often a number of LEDs connected in parallel and the system controls these as one large LED. A missing LED will not affect these circuits, however a shorted LED can cause the entire string of LEDs to turn off.

#### SINGLE LIGHTS

Single lights and LEDs are direct-controlled from SPIKE node boards. A common power source is grounded by individual transistors to turn individual LEDs on and off. Groups of LEDs, usually by node connector, share a common power source, so if a group of LEDs is out, check the wiring for the power source.

#### FLASHERS

SPIKE games treat flashers the same as single LEDs that draw more power. Flashers are controlled from the same circuits that power regular lights.

#### DRIVERS

A driver is a circuit that controls a high power-device such as a coil, magnet, or motor. Each device has a common 48V power source that is then connected to ground by a dedicated control transistor. Each driver is protected against shorting, static electricity, and over-current conditions. Take caution as 48V is always present on a device even when it is not energized.

#### OPTOS

Certain types of optical switches ("optos") require external signal conditioning. For these optos, they will interface to a SPIKE node via an opto signal conditioning board. Other optical switches connect directly to the Spike node board.

#### System Protections

**CAUTION:** Unless explicitly directed by an Authorized Stern Repair technician, perform ALL work on your pinball machine with the power disabled!


### INPUT/OUTPUT PROTECTIONS

SPIKE features built-in short-circuit, static electricity, and other protections to maximize reliability. If an LED, coil or other device shorts, it will be disabled but will not shut down the entire system in most circumstances. Groups of LEDs, coils, and switches often share common power supplies or other circuits, so it is possible that a bad device will affect the group of related devices and require removal or repair to fix the group. The system diagnostics will inform the technician of shorted or otherwise malfunctioning devices whenever possible. While the system is protected against permanent damage, it is strongly recommended to repair or replace these bad components as soon as possible to minimize downtime and maximize game earnings.

### 2.7 COMMON SPIKE NODE BOARDS

| Description                           | Type      | Part Number |
|---------------------------------------|-----------|-------------|
| SPIKE CPU Node                        | Node      | 509-1003-01 |
| Cabinet Node                          | Node      | 520-6967-72 |
| Playfield 48V Core-Driver Node        | Node      | 520-7017-72 |
| Trough Serial Opto Receiver Extension | Extension | 520-7001-00 |

# 3. LIGHT, SWITCH, AND DRIVER REFERENCE



## 3.1 SPIKE NODE BOARDS

| ID     | DIP Address     | Description                           | Location        | Part Number |
|--------|-----------------|---------------------------------------|-----------------|-------------|
| Node 0 | n/a             | SPIKE 2 CPU Node                      | Backbox         | 509-1003-01 |
| Node 1 | n/a             | Cabinet Node                          | Cabinet         | 520-6967-72 |
| Node 8 | OFF-OFF-OFF-OFF | Playfield 48V Core-Driver Node        | Lower Playfield | 520-7017-72 |
| 8a     | n/a             | Trough Serial Opto Receiver Extension | Playfield       | 520-7001-00 |
| 8b     | n/a             | Lower Center LED board                | Playfield       | 520-8405-00 |
| 8b1    | n/a             | Lower Left LED board                  | Playfield       | 520-8406-00 |
| 8b2    | n/a             | Upper Center LED board                | Playfield       | 520-8414-00 |
| 8b3    | n/a             | Upper Right LED board                 | Playfield       | 520-8408-00 |
| 8b4    | n/a             | Lower Right LED board                 | Playfield       | 520-8407-00 |
| Node 9 | OFF-OFF-ON-OFF  | Playfield 48V Core-Driver Node        | Playfield       | 520-7017-72 |
| 9a     | n/a             | Upper Left LED board                  | Playfield       | 520-8415-00 |
| 9b     | n/a             | Serial Motor Driver board             | Back Panel      | 520-6996-00 |
|        | n/a             | Stepper Motor Driver board            | Back Panel      | 520-8424-00 |

## 3.2 DRIVER REFERENCE

| ID | Name                  | Node | Connector | Ret. Pin | Ret. Wire | Voltage | V+ Pin | V+ Color | Location  | Type           | Address | Part Number    |
|----|-----------------------|------|-----------|----------|-----------|---------|--------|----------|-----------|----------------|---------|----------------|
| 1  | Trough                | 8    | CN8       | 7        | ORG GRY   | 48V     | 1-4    | GRY ORG  | Playfield | Coil - 27-1500 | 8-DR-1  | 090-5004-ND    |
| 2  | Auto Plunger          | 8    | CN8       | 9        | ORG WHT   | 48V     | 1-4    | GRY ORG  | Playfield | Coil - 23-800  | 8-DR-4  | 090-5001-ND    |
| 3  | Left Flipper          | 8    | CN8       | 6        | ORG YEL   | 48V     | 1-4    | GRY ORG  | Playfield | Coil - 22-1080 | 8-DR-5  | 090-5032-ND    |
| 4  | Right Flipper         | 8    | CN8       | 5        | ORG GRN   | 48V     | 1-4    | GRY ORG  | Playfield | Coil - 22-1080 | 8-DR-0  | 090-5032-ND    |
| 5  | Left Slingshot        | 8    | CN8       | 11       | ORG BLU   | 48V     | 1-4    | GRY ORG  | Playfield | Coil - 26-1200 | 8-DR-3  | 090-5044-ND    |
| 6  | Right Slingshot       | 8    | CN8       | 10       | ORG VIO   | 48V     | 1-4    | GRY ORG  | Playfield | Coil - 26-1200 | 8-DR-2  | 090-5044-ND    |
| 7  | Shaker Motor          | 1    | CN16      | 1        | BLU       | 48V     | 5      | RED      | Cabinet   | Motor          | 1-DR-0  | 041-5029-04    |
| 8  | Up Post-L Return Lane | 8    | CN7       | 3        | YEL BLK   | 48V     | 1      | GRY ORG  | Playfield | Coil - 26-1200 | 8-DR-6  | 090-5044-ND    |
| 9  | Up Right Flipper      | 8    | CN7       | 4        | YEL BRN   | 48V     | 1      | GRY ORG  | Playfield | Coil - 23-900  | 8-DR-7  | 090-5020-30-ND |
| 10 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 11 | Left Pop Bumper       | 9    | CN8       | 10       | ORG BLK   | 48V     | 1-4    | GRY BRN  | Playfield | Coil - 26-1200 | 9-DR-2  | 090-5044-ND    |
| 12 | Right Pop Bumper      | 9    | CN8       | 11       | ORG BRN   | 48V     | 1-4    | GRY BRN  | Playfield | Coil - 26-1200 | 9-DR-3  | 090-5044-ND    |
| 13 | Top Pop Bumper        | 9    | CN8       | 9        | ORG RED   | 48V     | 1-4    | GRY BRN  | Playfield | Coil - 26-1200 | 9-DR-4  | 090-5044-ND    |
| 14 | Up Post-Top           | 9    | CN7       | 2        | YEL GRN   | 48V     | 1      | GRY BRN  | Playfield | Coil - 26-1200 | 9-DR-8  | 090-5044-ND    |
| 15 | Up Post-Control Room  | 9    | CN7       | 3        | YEL ORG   | 48V     | 1      | GRY BRN  | Playfield | Coil - 26-1200 | 9-DR-6  | 090-5044-ND    |
| 16 | Lock-Raptor Pit       | 9    | CN8       | 6        | YEL VIO   | 48V     | 1-4    | GRY BRN  | Playfield | Coil - 26-1200 | 9-DR-5  | 090-5044-ND    |
| 17 | Motor-Raptor Pit      | 9    | CN8       | 7        | BRN       | 48V     | 1-4    | GRY BRN  | Playfield | Motor          | 9-DR-1  | 041-5111-00    |
| 18 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 19 | T-Rex Magnet-Mouth    | 9    | CN7       | 4        | BRN BLK   | 48V     | 1      | GRY BRN  | Playfield | Coil - 29-1400 | 9-DR-7  | 500-6818-01-ND |
| 20 | T-Rex Jaw             | 9    | CN8       | 5        | YEL BLU   | 48V     | 1      | GRY BRN  | Playfield | Coil - 32-1800 | 9-DR-0  | 500-5092-00-ND |
| 21 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 22 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 23 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 24 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 25 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 26 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 27 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 28 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 29 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 30 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 31 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 32 |                       |      |           |          |           |         |        |          |           |                |         |                |
| 33 | Coin Meter            | 1    | CN3       | 2        | BLK       | 12V     | 1      | RED      | Cabinet   | Digital Out    | 1-DR-2  | 500-9946-00    |
| 34 | Ticket Meter          | 1    | CN4       | 2        | BLK       | 12V     | 1      | RED      | Cabinet   | Digital Out    | 1-DR-3  | 500-9946-00    |
| 35 | Ticket Dispenser      | 1    | CN11      | 3        |           | 12V     | 1      |          | Cabinet   | Digital Out    | 1-DR-4  |                |

Continued on next page...

## DRIVER REFERENCE CONTINUED




Figure 3.2.1. Playfield driver locations (top view).

### 3.3 SWITCH REFERENCE

| ID | Name                    | Node | Node Ext | Conn. | Input Pin | Input Wire | GND Pin | Ground Wire | Location  | Type         | Address | Part Number                      |
|----|-------------------------|------|----------|-------|-----------|------------|---------|-------------|-----------|--------------|---------|----------------------------------|
| 1  | Left Outlane            | 8    | -        | CN11  | 4         | LGN RED    | 11-12   | BLK ORG     | Playfield | Rollover     | 8-SW-17 | 500-9935-03                      |
| 2  | Left Return Lane        | 8    | -        | CN11  | 5         | LGN ORG    | 11-12   | BLK ORG     | Playfield | Rollover     | 8-SW-18 | 500-9935-03                      |
| 3  |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 4  |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 5  | Right Return Lane       | 8    | -        | CN11  | 6         | LGN YEL    | 11-12   | BLK ORG     | Playfield | Rollover     | 8-SW-19 | 500-9935-04                      |
| 6  | Right Outlane           | 8    | -        | CN11  | 7         | LGN BLU    | 11-12   | BLK ORG     | Playfield | Rollover     | 8-SW-20 | 500-9935-04                      |
| 7  | Left Slingshot          | 8    | -        | CN10  | 4         | GRY BLU    | 8       | BLK GRN     | Playfield | Leaf         | 8-SW-30 | 180-5231-00                      |
| 8  | Right Slingshot         | 8    | -        | CN10  | 3         | GRY VIO    | 8       | BLK GRN     | Playfield | Leaf         | 8-SW-29 | 180-5231-00                      |
| 9  | Left Flipper Button     | 8    | -        | CN9   | 4         | GRY BRN    | 7       | BLK GRN     | Cabinet   | Leaf         | 8-SW-25 | 180-5160-01                      |
| 10 | Right Flipper Button    | 8    | -        | CN9   | 3         | GRY RED    | 7       | BLK GRN     | Cabinet   | Leaf         | 8-SW-24 | 180-5164-01                      |
| 11 | Left Flipper EOS        | 8    | -        | CN10  | 6         | GRY YEL    | 9       | BLK GRN     | Playfield | Leaf         | 8-SW-16 | 180-5149-00                      |
| 12 | Right Flipper EOS       | 8    | -        | CN10  | 5         | GRY GRN    | 9       | BLK GRN     | Playfield | Leaf         | 8-SW-31 | 180-5149-00                      |
| 13 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 14 | UP Right Flipper Button | 8    | -        | CN9   | 5         | VIO WHT    | 7       | BLK GRN     | Playfield | Leaf         | 8-SW-26 | 180-5164-01                      |
| 15 | Trough 6                | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-32 | 520-5344-00 tx<br>520-7001-00 rx |
| 16 | Trough 5                | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-33 | 520-5344-00 tx<br>520-7001-00 rx |
| 17 | Trough 4                | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-34 | 520-5344-00 tx<br>520-7001-00 rx |
| 18 | Trough 3                | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-35 | 520-5344-00 tx<br>520-7001-00 rx |
| 19 | Trough 2                | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-36 | 520-5344-00 tx<br>520-7001-00 rx |
| 20 | Trough 1                | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-37 | 520-5344-00 tx<br>520-7001-00 rx |
| 21 | Trough Jam              | 8    | 8a       | CN14  | -         |            | -       |             | Playfield | Opto         | 8-SW-38 | 520-5344-00 tx<br>520-7001-00 rx |
| 22 | Shooter Lane            | 8    | -        | CN10  | 2         | GRY WHT    | 7       | BLK GRN     | Playfield | Micro        | 8-SW-28 | 180-5157-01                      |
| 23 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 24 | Up Right Flipper EOS    | 8    | -        | CN12  | 9         | PNK BRN    | 10      | BLK RED     | Playfield | Leaf         | 8-SW-15 | 180-5149-00                      |
| 25 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 26 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 27 | Target-Lite Escape      | 8    | -        | CN11  | 10        | LGN WHT    | 11/12   | BLK ORG     | Playfield | Leaf, Target | 8-SW-23 | 515-9783-00-00                   |
| 28 | Target-Bottom Right     | 8    | -        | CN11  | 9         | LGN GRY    | 11/12   | BLK ORG     | Playfield | Leaf, Target | 8-SW-22 | 515-9783-00-00                   |
| 29 | Right Half Pipe         | 8    | -        | CN11  | 8         | LGN VIO    | 11/12   | BLK ORG     | Playfield | Micro        | 8-SW-21 | 180-5010-04                      |
| 30 | Helicopter Opto         | 8    | -        | CN12  | 5         | WHT YEL    | 10      | BLK RED     | Playfield | Opto         | 8-SW-11 | 520-8442-00                      |
| 31 | Newton Ball-Left Opto   | 9    | -        | CN9   | 3         | TAN BLK    | 7/8     | BLK BLU     | Playfield | Opto         | 9-SW-24 | 520-8102-00                      |
| 32 | Newton Ball-Right Opto  | 9    | -        | CN9   | 4         | TAN RED    | 7/8     | BLK BLU     | Playfield | Opto         | 9-SW-25 | 520-8102-00                      |
| 33 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 34 | Target-Pops             | 9    | -        | CN10  | 5         | GRY-ORG    | 7/8/9   | BLK BLU     | Playfield | Leaf, Target | 9-SW-31 | 515-9783-00-00                   |
| 35 | Pops Enter              | 9    | -        | CN10  | 6         | GRY YEL    | 7/8/9   | BLK BLU     | Playfield | Rollover     | 9-SW-16 | 500-9935-03                      |
| 36 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 37 | Target Control Room     | 9    | -        | CN11  | 2         | LGN GRY    | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-26 | 515-9783-00-00                   |
| 38 | Target Raptor Pit-Top   | 9    | -        | CN11  | 3         | LGN        | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-27 | 515-9783-00-00                   |
| 39 | Target Raptor Pit-Up L  | 9    | -        | CN11  | 4         | TAN YEL    | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-17 | 515-9783-00-00                   |
| 40 | Target Raptor Pit-Low L | 9    | -        | CN11  | 5         | TAN GRN    | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-18 | 515-9783-00-00                   |
| 41 | Target Raptor Pit-Right | 9    | -        | CN11  | 6         | TAN BLU    | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-19 | 515-9783-00-00                   |
| 42 | Target Bottom Left      | 9    | -        | CN11  | 7         | TAN VIO    | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-20 | 515-9784-00-00                   |
| 43 | Target Motor Bank       | 9    | -        | CN11  | 8         | TAN WHT    | 11/12   | BLK GRY     | Playfield | Leaf, Target | 9-SW-21 | 510-7768-00                      |
| 44 | Motor 1                 | 9    | -        | CN11  | 9         | TAN        | 11/12   | BLK GRY     | Playfield | Micro        | 9-SW-22 | 180-5119-02                      |
| 45 | Motor 2                 | 9    | -        | CN11  | 10        | TAN ORG    | 11/12   | BLK GRY     | Playfield | Micro        | 9-SW-23 | 180-5119-02                      |

Continued on next page...

## SWITCH REFERENCE CONTINUED

| ID | Name                    | Node | Node Ext | Conn. | Input Pin | Input Wire | GND Pin | Ground Wire | Location  | Type         | Address | Part Number                      |
|----|-------------------------|------|----------|-------|-----------|------------|---------|-------------|-----------|--------------|---------|----------------------------------|
| 46 | Raptor Lock Opto        | 9    | -        | CN12  | 3         | PNK ORG    | 10      | BLK WHT     | Playfield | Opto         | 9-SW-9  | 515-0215-00 tx<br>511-2887-00 rx |
| 47 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 48 | Left Pop Bumper         | 9    | -        | CN10  | 2         | GRY BLK    | 7/8/9   | BLK YEL     | Playfield | Leaf         | 9-SW-28 | 180-5232-00                      |
| 49 | Right Pop Bumper        | 9    | -        | CN10  | 3         | GRY BRN    | 7/8/9   | BLK YEL     | Playfield | Leaf         | 9-SW-29 | 180-5232-00                      |
| 50 | Top Pop Bumper          | 9    | -        | CN10  | 4         | GRY RED    | 7/8/9   | BLK YEL     | Playfield | Leaf         | 9-SW-30 | 180-5232-00                      |
| 51 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 52 | Right Orbit Enter Opto  | 8    | -        | CN12  | 2         | WHT BRN    | 10      | BLK RED     | Playfield | Opto         | 8-SW-8  | 515-0215-00 tx<br>515-0215-01 rx |
| 53 | Right Orbit Exit        | 8    | -        | CN12  | 3         | WHT RED    | 10      | BLK RED     | Playfield | Rollover     | 8-SW-9  | 500-9935-03                      |
| 54 | Right Ramp Exit         | 8    | -        | CN12  | 4         | WHT ORG    | 10      | BLK RED     | Playfield | Micro        | 8-SW-10 | 180-5087-00                      |
| 55 | 4x4 Target Right        | 9    | -        | CN12  | 5         | PNK GRN    | 10      | BLK WHT     | Playfield | Leaf, Target | 9-SW-11 | 515-9785-00-00                   |
| 56 | 4x4 Target Left         | 9    | -        | CN12  | 6         | PNK BLU    | 10      | BLK WHT     | Playfield | Leaf, Target | 9-SW-12 | 515-9785-00-00                   |
| 57 | Spinner                 | 9    | -        | CN12  | 7         | PNK VIO    | 10      | BLK WHT     | Playfield | Micro        | 9-SW-13 | 180-5010-04                      |
| 58 | Left Ramp Enter Opto    | 9    | -        | CN12  | 8         | PNK GRY    | 10      | BLK WHT     | Playfield | Opto         | 9-SW-14 | 515-0215-00 tx<br>515-0215-01 rx |
| 59 | Left Ramp Exit Opto     | 9    | -        | CN12  | 9         | PNK WHT    | 10      | BLK WHT     | Playfield | Opto         | 9-SW-15 | 515-0215-00 tx<br>515-0215-01 rx |
| 60 | Left Halfpipe Opto      | 9    | -        | CN13  | 2         | WHT BRN    | 10      | BLK BRN     | Playfield | Opto         | 9-SW-0  | 515-0215-00 tx<br>515-0215-01 rx |
| 61 | Target Top Left         | 9    | -        | CN13  | 3         | WHT RED    | 10      | BLK BRN     | Playfield | Leaf, Target | 9-SW-1  | 515-9785-00-00                   |
| 62 | Left Orbit Enter        | 9    | -        | CN13  | 4         | WHT ORG    | 10      | BLK BRN     | Playfield | Rollover     | 9-SW-2  | 500-9935-03                      |
| 63 | Left Orbit Exit Opto    | 9    | -        | CN13  | 5         | WHT YEL    | 10      | BLK BRN     | Playfield | Opto         | 9-SW-3  | 515-0215-00 tx<br>515-0215-01 rx |
| 64 | T-Rex Up                | 9    | -        | CN13  | 6         | WHT-GRN    | 10      | BLK BRN     | Playfield | Micro        | 9-SW-4  | 180-5119-02                      |
| 65 | T-Rex Mid               | 9    | -        | CN13  | 7         | WHT BLU    | 10      | BLK BRN     | Playfield | Micro        | 9-SW-5  | 180-5119-02                      |
| 66 | T-Rex Down              | 9    | -        | CN13  | 8         | WHT VIO    | 10      | BLK BRN     | Playfield | Micro        | 9-SW-6  | 180-5119-02                      |
| 67 | T-Rex Mouth             | 9    | -        | CN12  | 4         | PNK YEL    | 10      | BLK WHT     | Playfield | Opto         | 9-SW-10 | 511-7976-00 tx<br>511-2783-00 rx |
| 68 | Stepper Home            | 9    | -        | CN13  | 9         | WHT GRY    | 10      | BLK BRN     | Playfield | Micro        | 9-SW-7  | 180-5119-02                      |
| 69 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 70 | Lockdown Button         | 1    | -        | CN7   | 8         | TAN WHT    | 5       | BLK WHT     | Cabinet   | Leaf         | 1-SW-2  | 180-5218-00                      |
| 71 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 72 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 73 | Start Button            | 1    | -        | CN6   | 10        | GRY        | 5       | BLK WHT     | Cabinet   | Micro        | 1-SW-11 | 500-1060-44-LED                  |
| 74 | Tournament Start Button | 1    | -        | CN6   | 9         | GRY WHT    | 5       | BLK WHT     | Cabinet   | Micro        | 1-SW-12 | 500-6587-06-TL                   |
| 75 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 76 | Left Coin               | 1    | -        | CN5   | 9         | PNK BRN    | 3       | BLK         | Cabinet   | Micro        | 1-SW-16 |                                  |
| 77 | Right Coin              | 1    | -        | CN5   | 7         | PNK ORG    | 3       | BLK         | Cabinet   | Micro        | 1-SW-18 |                                  |
| 78 | Center Coin             | 1    | -        | CN5   | 8         | PNK RED    | 3       | BLK         | Cabinet   | Micro        | 1-SW-17 |                                  |
| 79 | Fourth Coin             | 1    | -        | CN5   | 6         |            | -       |             | Cabinet   | -            | 1-SW-19 |                                  |
| 80 | Fifth Coin              | 1    | -        | CN5   | 5         |            | -       |             | Cabinet   | -            | 1-SW-20 |                                  |
| 81 | Tilt Pendulum           | 1    | -        | CN6   | 7         | WHT        | 5       | BLK WHT     | Cabinet   | Plumb Bob    | 1-SW-14 | 516-0007-00                      |
| 82 | Sixth Coin              | 1    | -        | CN9   | 5         |            | -       |             | Cabinet   | -            | 1-SW-21 |                                  |
| 83 | Ticket Notch            | 1    | -        | CN11  | 5         |            | -       |             | Cabinet   | -            | 1-SW-8  |                                  |
| 84 | Slam Tilt               | 1    | -        | CN5   | 4         | LGN RED    | 3       | BLK         | Cabinet   | -            | 1-SW-22 |                                  |
| 85 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 86 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 87 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 88 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 89 |                         |      |          |       |           |            |         |             |           |              |         |                                  |
| 90 |                         |      |          |       |           |            |         |             |           |              |         |                                  |

Continued on next page...



## SWITCH REFERENCE CONTINUED

| ID  | Name                       | Node | Node Ext | Conn. | Input Pin | Input Wire | GND Pin | Ground Wire | Location  | Type | Address | Part Number |
|-----|----------------------------|------|----------|-------|-----------|------------|---------|-------------|-----------|------|---------|-------------|
| 91  |                            |      |          |       |           |            |         |             |           |      |         |             |
| C1  | DIP 1                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-0  | -           |
| C10 | Service Plus               | 0    | -        | CN25  | 3         | LGN VIO    | 6       | BLK         | Coin Door |      | 0-SW-9  | 515-1963-00 |
| C11 | Service Minus              | 0    | -        | CN25  | 2         | LGN BLU    | 6       | BLK         | Coin Door |      | 0-SW-10 | 515-1963-00 |
| C12 | Service Back               | 0    | -        | CN25  | 1         | LGN BLK    | 6       | BLK         | Coin Door |      | 0-SW-11 | 515-1963-00 |
| C17 | Headphone Detect           | 0    | -        | -     | -         | -          | -       | -           | Coin Door |      | 0-SW-16 | -           |
| C18 | Headphone Kit Cable Detect | 0    | -        | CN3   | 5         | BLK        | 4       | BLK         | CPU Node  |      | 0-SW-17 | -           |
| C19 | Volume Encoder 1           | 0    | -        | CN3   | 6         | WHT        | 1       | DRAIN       | CPU Node  |      | 0-SW-18 | -           |
| C2  | DIP 2                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-1  | -           |
| C20 | Volume Encoder 2           | 0    | -        | CN3   | 7         | GRN        | 1       | DRAIN       | CPU Node  |      | 0-SW-19 | -           |
| C24 | DC Sense                   | 0    | -        | CN7   | 4         | GRY RED    | 1       | BLK         | -         |      | 0-SW-23 | -           |
| C25 | Coin Door Interlock        | -    | -        | CN4   | 1         | GRY        | 4       | GRY RED     | Backbox   |      | 0-SW-24 | -           |
| C3  | DIP 3                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-2  | -           |
| C4  | DIP 4                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-3  | -           |
| C5  | DIP 5                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-4  | -           |
| C6  | DIP 6                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-5  | -           |
| C7  | DIP 7                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-6  | -           |
| C8  | DIP 8                      | 0    | -        | -     | -         |            | -       |             | CPU Node  |      | 0-SW-7  | -           |
| C9  | Service Select             | 0    | -        | CN25  | 4         | LGN GRY    | 6       | BLK         | Coin Door |      | 0-SW-8  | 515-1963-00 |

Continued on next page...

## SWITCH REFERENCE CONTINUED




Figure 3.3.1. Playfield switch locations (top view).

### 3.4 LIGHT REFERENCE

| ID | Name                         | Node | Node Ext. | Conn. | Ret. Pin | Ret. Wire | Src. Pin | Src. Wire | Location  | Type        | Light Color | Address | Part Number |
|----|------------------------------|------|-----------|-------|----------|-----------|----------|-----------|-----------|-------------|-------------|---------|-------------|
| 1  | Coin Enable                  | 1    | -         | CN8   | 6        | BLK GRY   | 2        | GRY RED   | Coin Door | Digital Out |             | 1-LP-0  |             |
| 2  | Start Button                 | 1    | -         | CN6   | 3        | YEL BRN   | 1        | RED       | Cabinet   | Feature     | White       | 1-LP-2  | 113-5071-00 |
| 3  | Tournament Start             | 1    | -         | CN6   | 2        | YEL RED   | 1        | RED       | Cabinet   | Feature     | White       | 1-LP-3  | 112-5033-08 |
| 4  | Lockdown Button-R            | 1    | -         | CN7   | 2        | RED WHT   | 1        | RED       | Cabinet   | Feature     | RGB         | 1-LP-5  | 520-5333-00 |
| 5  | Lockdown Button-G            | 1    | -         | CN7   | 3        | GRN WHT   | 1        | RED       | Cabinet   | Feature     | RGB         | 1-LP-4  | 520-5333-00 |
| 6  | Lockdown Button-B            | 1    | -         | CN7   | 4        | BLU WHT   | 1        | RED       | Cabinet   | Feature     | RGB         | 1-LP-7  | 520-5333-00 |
| 7  |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 8  |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 9  |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 10 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 11 | Left Outlane                 | 8    | -         | CN14  | 2        | BRN ORG   | 7/8      | YEL       | Playfield | Feature     | White       | 8-LP-7  | 520-5307-00 |
| 12 | Left Return Lane             | 8    | -         | CN14  | 3        | BRN RED   | 7/8      | YEL       | Playfield | Feature     | White       | 8-LP-6  | 520-5307-00 |
| 13 | Shoot Again                  | 8    | -         | CN14  | 4        | BRN       | 7/8      | YEL       | Playfield | Feature     | White       | 8-LP-5  | 520-5307-00 |
| 14 | Right Return Lane            | 8    | -         | CN14  | 5        | BRN YEL   | 7/8      | YEL       | Playfield | Feature     | White       | 8-LP-4  | 520-5307-00 |
| 15 | Right Outlane                | 8    | -         | CN14  | 6        | BRN BLU   | 7/8      | YEL       | Playfield | Feature     | White       | 8-LP-3  | 520-5307-00 |
| 16 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 17 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 18 | main gate                    | 8    | 8b        | LED7  | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-14 | 520-8405-00 |
| 19 | Brachosaurus                 | 8    | 8b        | LED8  | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-15 | 520-8405-00 |
| 20 | Gallimimus                   | 8    | 8b        | LED6  | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-13 | 520-8405-00 |
| 21 | Ankylosaurus                 | 8    | 8b        | LED10 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-17 | 520-8405-00 |
| 22 | Spitter                      | 8    | 8b        | LED9  | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-16 | 520-8405-00 |
| 23 | Triceritops                  | 8    | 8b        | LED5  | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-12 | 520-8405-00 |
| 24 | T-Rex Paddock                | 8    | 8b        | LED14 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-21 | 520-8405-00 |
| 25 | Compsognathus                | 8    | 8b        | LED11 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-18 | 520-8405-00 |
| 26 | Stegosaurus                  | 8    | 8b        | LED4  | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-11 | 520-8405-00 |
| 27 | Spinosaurus                  | 8    | 8b        | LED15 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-22 | 520-8405-00 |
| 28 | Raptor                       | 8    | 8b        | LED12 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-19 | 520-8405-00 |
| 29 | Pteranodon                   | 8    | 8b        | LED16 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-23 | 520-8405-00 |
| 30 | Visitor Center               | 8    | 8b        | LED13 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-20 | 520-8405-00 |
| 31 | T-Rex                        | 8    | 8b        | LED17 | -        | -         | -        | -         | Playfield | Feature     | White       | 8-LP-24 | 520-8405-00 |
| 32 | Control Room Wizard          | 8    | 8b        | CN1   | 4        | ORG RED   | 1/2      | RED       | Playfield | Feature     | White       | 8-LP-9  | 520-5307-00 |
| 33 | Escape Nublar                | 8    | 8b        | CN1   | 3        | ORG BRN   | 1/2      | RED       | Playfield | Feature     | White       | 8-LP-8  | 520-5307-00 |
| 34 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 35 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 36 | Control Room                 | 9    | 9a        | CN4   | 9        | ORG WHT   | 1/2/3    | RED       | Playfield | Feature     | White       | 9-LP-50 | 520-5307-00 |
| 37 | (C)HAOS                      | 8    | 8b1       | CN5   | 7        | YEL BRN   | 1/2/3    | RED       | Playfield | Feature     | White       | 8-LP-34 | 520-5307-00 |
| 38 | Control Room Arrow-R         | 8    | 8b1       | CN5   | 4        | RED BRN   | 1/2/3    | RED       | Playfield | Feature     | White       | 8-LP-31 | 520-8406-00 |
| 39 | Control Room Arrow-G         | 8    | 8b1       | CN5   | 5        | GRN BRN   | 1/2/3    | RED       | Playfield | Feature     | White       | 8-LP-32 | 520-8406-00 |
| 40 | Control Room Arrow-B         | 8    | 8b1       | CN5   | 6        | BLU BRN   | 1/2/3    | RED       | Playfield | Feature     | White       | 8-LP-33 | 520-8406-00 |
| 41 | Control Room Rescue          | 8    | 8b1       | CN4   | 8        | GRN GRY   | 1/2/3    | RED       | Playfield | Feature     | White       | 8-LP-29 | 520-8406-00 |
| 42 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 43 | Lite Escape                  | 8    | 8b1       | CN5   | 8        | YEL RED   | 1/2/3    | RED       | Playfield | Feature     | White       | 8-LP-35 | 520-8406-00 |
| 44 | 2x playfield                 | 8    | 8b        | CN2   | 3        | ORG       | 1        | RED       | Playfield | Feature     | White       | 8-LP-10 | 520-5307-00 |
| 45 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 46 |                              |      |           |       |          |           |          |           |           |             |             |         |             |
| 47 | Raptor Pit Arrow-R           | 9    | 9a        | CN4   | 3        | RED GRY   | 1/2      | RED       | Playfield | Feature     | White       | 9-LP-44 | 520-5333-00 |
| 48 | Raptor Pit Arrow-G           | 9    | 9a        | CN4   | 4        | GRN GRY   | 1/2      | RED       | Playfield | Feature     | White       | 9-LP-45 | 520-5333-00 |
| 49 | Raptor Pit Arrow-B           | 9    | 9a        | CN4   | 5        | BLU GRY   | 1/2      | RED       | Playfield | Feature     | White       | 9-LP-46 | 520-5333-00 |
| 50 | Raptor Pit Upper Left Target | 9    | 9a        | CN4   | 6        | ORG GRN   | 1/2      | RED       | Playfield | Feature     | White       | 9-LP-47 | 520-5307-00 |

Continued on next page...

## LIGHT REFERENCE CONTINUED

| ID  | Name                         | Node | Node Ext. | Conn. | Ret. Pin | Ret. Wire | Src. Pin | Src. Wire | Location  | Type    | Light Color | Address | Part Number |
|-----|------------------------------|------|-----------|-------|----------|-----------|----------|-----------|-----------|---------|-------------|---------|-------------|
| 51  | Raptor Pit Lower Left Target | 9    | 9a        | CN4   | 7        | ORG BLU   | 1/2      | RED       | Playfield | Feature | White       | 9-LP-48 | 520-5307-00 |
| 52  | Raptor Pit Right Target      | 9    | 9a        | CN4   | 8        | ORG VIO   | 1/2      | RED       | Playfield | Feature | White       | 9-LP-49 | 520-5307-00 |
| 53  | Raptor Pit Electric Fence    | 8    | 8b1       | CN4   | 7        | GRN VIO   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-28 | 520-8406-00 |
| 54  | Raptor Pit Capture           | 8    | 8b1       | CN4   | 6        | GRN BLU   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-27 | 520-8406-00 |
| 55  | Raptor Pit Gate              | 8    | 8b1       | CN4   | 5        | GRN       | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-26 | 520-8406-00 |
| 56  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 57  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 58  | Supply Drop                  | 9    | 9a        | CN4   | 12       | ORG BRN   | 1/2      | RED       | Playfield | Feature | White       | 9-LP-53 | 520-5307-00 |
| 59  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 60  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 61  | Left Halfpipe Arrow-R        | 9    | 9a        | LED26 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-37 | 520-8415-00 |
| 62  | Left Halfpipe Arrow-G        | 9    | 9a        | LED26 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-38 | 520-8415-00 |
| 63  | Left Halfpipe Arrow-B        | 9    | 9a        | LED26 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-39 | 520-8415-00 |
| 64  | Left Halfpipe Rescue         | 9    | 9a        | LED28 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-43 | 520-8415-00 |
| 65  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 66  | Left Halfpipe Target         | 9    | 9a        | LED21 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-32 | 520-8415-00 |
| 67  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 68  | Left Loop Arrow-R            | 9    | 9a        | LED11 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-20 | 520-8415-00 |
| 69  | Left Loop Arrow-G            | 9    | 9a        | LED11 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-21 | 520-8415-00 |
| 70  | Left Loop Arrow-B            | 9    | 9a        | LED11 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-22 | 520-8415-00 |
| 71  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 72  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 73  | Left Ramp Arrow-R            | 9    | 9a        | LED10 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-17 | 520-8415-00 |
| 74  | Left Ramp Arrow-G            | 9    | 9a        | LED10 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-18 | 520-8415-00 |
| 75  | Left Ramp Arrow-B            | 9    | 9a        | LED10 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-19 | 520-8415-00 |
| 76  | C(H)AOS                      | 9    | 9a        | LED12 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-23 | 520-8415-00 |
| 77  | Left Ramp Rescue             | 9    | 9a        | LED9  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-16 | 520-8415-00 |
| 78  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 79  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 80  | Spinner 100k                 | 9    | 9a        | CN2   | 10       | BLU GRN   | 1/2      | RED       | Playfield | Feature | White       | 9-LP-31 | 520-5307-00 |
| 81  | Spinner 50k                  | 9    | 9a        | LED3  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-10 | 520-8415-00 |
| 82  | Spinner 30k                  | 9    | 9a        | LED4  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-11 | 520-8415-00 |
| 83  | Spinner 15k                  | 9    | 9a        | LED5  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-12 | 520-8415-00 |
| 84  | Spinner Rescue               | 9    | 9a        | LED6  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-13 | 520-8415-00 |
| 85  | Spinner Arrow-R              | 9    | 9a        | LED27 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-40 | 520-8415-00 |
| 86  | Spinner Arrow-G              | 9    | 9a        | LED27 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-41 | 520-8415-00 |
| 87  | Spinner Arrow-B              | 9    | 9a        | LED27 | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-42 | 520-8415-00 |
| 88  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 89  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 90  | 4x4 Left Target              | 9    | 9a        | LED1  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-8  | 520-8415-00 |
| 91  | 4x4 Left Target Arrow        | 9    | 9a        | LED2  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-9  | 520-8415-00 |
| 92  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 93  | 4x4 Left Direction           | 9    | 9a        | LED8  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-15 | 520-8415-00 |
| 94  | 4x4 Turn                     | 9    | 9a        | LED7  | -        | -         | -        | -         | Playfield | Feature | White       | 9-LP-14 | 520-8415-00 |
| 95  |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 96  | 4x4 Right Direction          | 8    | 8b2       | CN6   | 7        | ORG VIO   | 1/2/3/4  | RED       | Playfield | Feature | White       | 8-LP-41 | 520-8414-00 |
| 97  | Advance T-Rex                | 8    | 8b2       | CN6   | 8        | ORG GRY   | 1/2/3/4  | RED       | Playfield | Feature | White       | 8-LP-42 | 520-8414-00 |
| 98  | 4x4 Right Target             | 8    | 8b2       | CN6   | 5        | ORG GRN   | 1/2/3/4  | RED       | Playfield | Feature | White       | 8-LP-39 | 520-8414-00 |
| 99  | 4x4 Right Target Arrow       | 8    | 8b2       | CN6   | 6        | ORG BLU   | 1/2/3/4  | RED       | Playfield | Feature | White       | 8-LP-40 | 520-8414-00 |
| 100 |                              |      |           |       |          |           |          |           |           |         |             |         |             |
| 101 |                              |      |           |       |          |           |          |           |           |         |             |         |             |

Continued on next page...



## LIGHT REFERENCE CONTINUED

| ID  | Name                   | Node | Node Ext. | Conn. | Ret. Pin | Ret. Wire | Src. Pin | Src. Wire | Location  | Type    | Light Color | Address | Part Number |
|-----|------------------------|------|-----------|-------|----------|-----------|----------|-----------|-----------|---------|-------------|---------|-------------|
| 102 | Amber Bonus            | 8    | 8b2       | CN5   | 9        | YEL ORG   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-36 | 520-8414-00 |
| 103 | Smart Missile          | 8    | 8b2       | CN5   | 10       | YEL GRN   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-37 | 520-8414-00 |
| 104 | Chaos                  | 8    | 8b2       | CN5   | 11       | YEL BLU   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-38 | 520-8414-00 |
| 105 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 106 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 107 | Right Ramp Arrow-R     | 8    | 8b3       | CN7   | 5        | RED ORG   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-45 | 520-8408-00 |
| 108 | Right Ramp Arrow-G     | 8    | 8b3       | CN7   | 6        | GRN ORG   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-46 | 520-8408-00 |
| 109 | Right Ramp Arrow-B     | 8    | 8b3       | CN7   | 7        | BLU ORG   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-47 | 520-8408-00 |
| 110 | CH(A)OS                | 8    | 8b3       | CN7   | 4        | BLU RED   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-44 | 520-8408-00 |
| 111 | Right Ramp Rescue      | 8    | 8b3       | CN7   | 3        | BLU BRN   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-43 | 520-8408-00 |
| 112 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 113 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 114 | Right Loop Arrow-R     | 8    | 8b3       | CN7   | 12       | RED YEL   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-52 | 520-8408-00 |
| 115 | Right Loop Arrow-G     | 8    | 8b3       | CN7   | 13       | GRN YEL   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-53 | 520-8408-00 |
| 116 | Right Loop Arrow-B     | 8    | 8b3       | CN7   | 14       | BLU YEL   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-54 | 520-8408-00 |
| 117 | CHA(O)S                | 8    | 8b3       | CN7   | 10       | BLU BLK   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-50 | 520-8408-00 |
| 118 | Right Orbit Rescue     | 8    | 8b3       | CN7   | 8        | BLU GRN   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-48 | 520-8408-00 |
| 119 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 120 | Right Halfpipe Arrow-R | 8    | 8b4       | CN8   | 4        | RED VIO   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-57 | 520-8407-00 |
| 121 | Right Halfpipe Arrow-G | 8    | 8b4       | CN8   | 5        | GRN VIO   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-58 | 520-8407-00 |
| 122 | Right Halfpipe Arrow-B | 8    | 8b4       | CN8   | 6        | BLU VIO   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-59 | 520-8407-00 |
| 123 | CHAO(S)                | 8    | 8b4       | CN8   | 7        | YEL VIO   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-60 | 520-8407-00 |
| 124 | Right Halfpipe Rescue  | 8    | 8b4       | CN8   | 8        | YEL GRY   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-61 | 520-8407-00 |
| 125 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 126 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 127 | Lite 2X                | 8    | 8b        | CN8   | 9        | YEL WHT   | 1/2/3    | RED       | Playfield | Feature | White       | 8-LP-62 | 520-5307-00 |
| 128 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 129 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 130 | Left Ramp Sign 1       | 9    | -         | CN14  | 5        | BRN BLU   | 7/8      | YEL       | Playfield | Feature | White       | 9-LP-4  | 520-5307-00 |
| 131 | Left Ramp Sign 2       | 9    | -         | CN14  | 6        | BRN GRN   | 7/8      | YEL       | Playfield | Feature | White       | 9-LP-3  | 520-5307-00 |
| 132 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 133 | Right Ramp Sign 1      | 8    | 8b        | CN7   | 15       | BLU       | 1/2      | RED       | Playfield | Feature | White       | 8-LP-55 | 520-5307-00 |
| 134 | Right Ramp Sign 2      | 8    | 8b        | CN7   | 16       | BLU VIO   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-56 | 520-5307-00 |
| 135 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 136 | Right Halfpipe Sign    | 8    | 8b        | CN7   | 11       | BLU GRY   | 1/2      | RED       | Playfield | Feature | White       | 8-LP-51 | 520-5307-00 |
| 137 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 138 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 139 | (M)AP                  | 9    | 9a        | CN4   | 13       | YEL BRN   | 1/2      | RED       | Backpanel | Feature | White       | 9-LP-54 | 520-5307-00 |
| 140 | M(A)P                  | 9    | 9a        | CN4   | 14       | YEL RED   | 1/2      | RED       | Backpanel | Feature | White       | 9-LP-55 | 520-5307-00 |
| 141 | MA(P)                  | 9    | 9a        | CN2   | 7        | YEL ORG   | 1/2      | RED       | Backpanel | Feature | White       | 9-LP-28 | 520-5307-00 |
| 142 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 143 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 144 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 145 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 146 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 147 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 148 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 149 |                        |      |           |       |          |           |          |           |           |         |             |         |             |
| 150 | Coin Door Gl           | 1    | -         | CN5   | 2        | YEL       | 1        | YEL-WHT   | Coin Door | G.I.    | White       | 1-LP-1  | 112-5033-08 |
| 151 | Bottom Gl-Right        | 8    | -         | CN15  | 5        | RED BLK   | 1        | YEL RED   | Playfield | G.I.    | White       | 8-LP-0  | 112-5034-WW |
| 152 | Bottom Gl-Left         | 8    | -         | CN15  | 6        | WHT BLK   | 2        | YEL BLK   | Playfield | G.I.    | White       | 8-LP-1  | 112-5034-WW |

Continued on next page...

## LIGHT REFERENCE CONTINUED

| ID  | Name                              | Node | Node Ext. | Conn. | Ret. Pin | Ret. Wire | Src. Pin | Src. Wire | Location  | Type    | Light Color | Address | Part Number |
|-----|-----------------------------------|------|-----------|-------|----------|-----------|----------|-----------|-----------|---------|-------------|---------|-------------|
| 153 | Top GI-Right                      | 9    | -         | CN15  | 5        | RED BLK   | 1        | YEL RED   | Playfield | G.I.    | White       | 9-LP-0  | 112-5034-WW |
| 154 | Top GI-Left                       | 9    | -         | CN15  | 6        | WHT BLK   | 2        | YEL BLK   | Playfield | G.I.    | White       | 9-LP-1  | 112-5034-WW |
| 155 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 156 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 157 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 158 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 159 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 160 | Escape Flash                      | 8    | 8b        | CN4   | 9        | GRN WHT   | 1/2/3    | RED       | Playfield | Flash   | White       | 8-LP-30 | 520-7000-00 |
| 161 | Raptor Pit Enter Flash x2         | 8    | 8b        | CN4   | 4        | GRN RED   | 1/2/3    | RED       | Playfield | Flash   | White       | 8-LP-25 | 520-8406-00 |
| 162 | Lite 2X Target Flash              | 8    | 8b        | CN8   | 10       | ORG YEL   | 1/2/3    | RED       | Playfield | Flash   | White       | 8-LP-63 | 520-7000-00 |
| 163 | Raptor Pit Flash                  | 9    | 9a        | CN4   | 10       | ORG BLK   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-51 | 113-5045-08 |
| 164 | Left Halfpipe Spotlight           | 9    | 9a        | CN4   | 11       | ORG RED   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-52 | 113-5045-08 |
| 165 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 166 | Right Halfpipe Spotlight          | 8    | 8b        | CN7   | 9        | BLU WHT   | 1/2      | RED       | Playfield | Flash   | White       | 8-LP-49 | 113-5045-08 |
| 167 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 168 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 169 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 170 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 171 | Spinner Jackpot Flash             | 9    | 9a        | CN2   | 9        | BLU WHT   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-30 | 520-7000-00 |
| 172 | Left Ramp Flash                   | 9    | 9a        | CN2   | 8        | YEL VIO   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-29 | 520-7000-00 |
| 173 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 174 | Top Pop Bumper                    | 9    | 9a        | CN2   | 5        | BRN RED   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-26 | 520-8059-00 |
| 175 | Left Pop Bumper                   | 9    | 9a        | CN2   | 3        | BRN BLK   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-24 | 520-8059-00 |
| 176 | Right Pop Bumper                  | 9    | 9a        | CN2   | 4        | BRN       | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-25 | 520-8059-00 |
| 177 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 178 | Backpanel Flash 1 (L)             | 9    | 9a        | CN3   | 3        | BRN GRN   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-33 | 113-5045-08 |
| 179 | Backpanel Flash 2                 | 9    | 9a        | CN3   | 4        | BRN VIO   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-34 | 113-5045-08 |
| 180 | Backpanel Flash 3                 | 9    | 9a        | CN3   | 5        | BRN GRY   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-35 | 113-5045-08 |
| 181 | Backpanel Flash 4 (R)             | 9    | 9a        | CN3   | 6        | BRN WHT   | 1/2      | RED       | Playfield | Flash   | White       | 9-LP-36 | 113-5045-08 |
| 182 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 183 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 184 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 185 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 186 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 187 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 188 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 189 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 190 | Shooter Illumination 1 (Optional) | 1    | -         | CN15  | 3        | ORG BLK   | 1        | RED       | Cabinet   | Feature | White       | 1-LP-9  | 515-2169-00 |
| 191 | Shooter Illumination 2 (Optional) | 1    | -         | CN15  | 4        | ORG BRN   | 1        | RED       | Cabinet   | Feature | White       | 1-LP-10 | 515-2169-00 |
| 192 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 193 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 194 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 195 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 196 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 197 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 198 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |
| 199 |                                   |      |           |       |          |           |          |           |           |         |             |         |             |

Continued on next page...



## LIGHT REFERENCE CONTINUED




Figure 3.4.1. Playfield light locations (top view).

## 3.5 MOTOR REFERENCE

| ID | Name               | Node | Node Ext. | Conn. | Ret. Pin | Ret. Wire | Src. Pin | Src. Wire | Location  | Type  | Light Color | Address | Part Number |
|----|--------------------|------|-----------|-------|----------|-----------|----------|-----------|-----------|-------|-------------|---------|-------------|
| 1  | Stepper PH0        | 9    | -         | CN14  | 4        | BRN RED   | -        | -         | Playfield | Motor | -           | 9-LP-5  | 520-8424-00 |
| 2  | Stepper PH1        | 9    | -         | CN14  | 3        | BRN ORG   | -        | -         | Playfield | Motor | -           | 9-LP-6  | 520-8424-00 |
| 3  | Stepper Enable     | 9    | -         | CN14  | 2        | BRN YEL   | -        | -         | Playfield | Motor | -           | 9-LP-7  | 520-8424-00 |
| 4  | Motor A Enable     | 9    | 9a        | CN5   | -        | -         | -        | -         | Playfield | Motor | -           | 9-LP-56 | 520-6996-00 |
| 5  | Motor A Control 1A | 9    | 9a        | CN5   | -        | -         | -        | -         | Playfield | Motor | -           | 9-LP-57 | 520-6996-00 |
| 6  | Motor A Control 2A | 9    | 9a        | CN5   | -        | -         | -        | -         | Playfield | Motor | -           | 9-LP-58 | 520-6996-00 |
| 7  |                    |      |           |       |          |           |          |           |           |       |             |         |             |
| 8  |                    |      |           |       |          |           |          |           |           |       |             |         |             |
| 9  |                    |      |           |       |          |           |          |           |           |       |             |         |             |
| 10 |                    |      |           |       |          |           |          |           |           |       |             |         |             |

## 4. ELECTRONIC PINOUTS AND SCHEMATICS

### 4.1 SPIKE-2 CPU NODE 0

509-1003-01

#### DIRECT SWITCH MAPPING (CN25)

The coin-door diagnostic switches are connected directly to the CPU node via the Cabinet Node. Note that both the CPU and Cabinet nodes are required for diagnostic switch operation.

| ID  | Name           | Conn. | Input Pin | Input Wire | GND Pin | Ground Wire | Location  | Type | Address | Part Number |
|-----|----------------|-------|-----------|------------|---------|-------------|-----------|------|---------|-------------|
| C1  | DIP 1          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-0  | -           |
| C2  | DIP 2          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-1  | -           |
| C3  | DIP 3          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-2  | -           |
| C4  | DIP 4          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-3  | -           |
| C5  | DIP 5          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-4  | -           |
| C6  | DIP 6          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-5  | -           |
| C7  | DIP 7          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-6  | -           |
| C8  | DIP 8          | -     | -         | -          | -       | -           | CPU Node  |      | 0-SW-7  | -           |
| C9  | Service Select | CN25  | 1         | LGN-GRY    | 11      | BLK-WHT     | Coin Door |      | 0-SW-9  | 180-5192-04 |
| C10 | Service Plus   | CN25  | 2         | LGN-VIO    | 11      | BLK-WHT     | Coin Door |      | 0-SW-10 | 180-5192-02 |
| C11 | Service Minus  | CN25  | 3         | LGN-BLU    | 11      | BLK-WHT     | Coin Door |      | 0-SW-11 | 180-5192-02 |
| C12 | Service Back   | CN25  | 4         | LGN-BLK    | 11      | BLK-WHT     | Coin Door |      | 0-SW-12 | 180-5192-00 |

#### CONNECTORS

| ID   | Connector Type       | Description                                                              |
|------|----------------------|--------------------------------------------------------------------------|
| CN1  | 5-Pin .156" Header   | Backbox 2-channel amplified speaker out                                  |
| CN2  | 3-Pin .100" Header   | Console Port                                                             |
| CN3  | 7-Pin .100" Header   | Headphone connector                                                      |
| CN4  | 2-Pin .156"          | Cabinet 1-channel amplified speaker out                                  |
| CN5  | 7-Pin .100" Header   | Line In/Out                                                              |
| CN6  | 34 Pin 2.00mm Header | LCD display connector                                                    |
| CN7  | 5-Pin .156" Header   | 48V supply from main power supply                                        |
| CN8  | 6-Pin .100" Header   | SPI Serial                                                               |
| CN9  | USB                  | USB connector - for software updates, audit dumps, and expansion modules |
| CN9  | USB                  | USB connector - for software updates, audit dumps, and expansion modules |
| CN10 | HDMI                 | HDMI Out                                                                 |
| CN11 | RJ45                 | SPIKE node bus - to cabinet node N1                                      |
| CN12 | RJ45                 | SPIKE node bus - To Topper accessory Kit                                 |
| CN13 | SD CARD              | SD Card connector                                                        |
| CN14 | 5-Pin .100" Header   | LCD Backlight                                                            |
| CN15 | 3-Pin .100" Header   | Backbox Light                                                            |
| CN16 | 4-Pin .100" Header   | 3.3v / 5v / 12v                                                          |
| CN17 | ETHERNET             | ETHERNET connector                                                       |
| CN21 | SATA Header          | SATA connector                                                           |
| CN22 | RJ45                 | SPIKE node bus - to playfield node                                       |
| CN25 | 12-Pin .100" Header  | Dedicated switch inputs - service, volume switches                       |

#### COMPONENTS

| ID             | Name                                                                            |
|----------------|---------------------------------------------------------------------------------|
| S1             | DIP Switches                                                                    |
| S2             | Reset Switch                                                                    |
| SD CARD (CN13) | For system SD card. Note: only to be removed if instructed to by Stern Service. |
| BT1            | BR1225 3V Lithium battery for game clock between power cycles                   |

#### STATUS LEDS

| LED ID   | Name                                 | Color | Description                                                                                                      |
|----------|--------------------------------------|-------|------------------------------------------------------------------------------------------------------------------|
| 48V      | +48V Supply In                       | Red   | ON: Main system power is connected. OFF: No 48V system power. Check power supply connections, cables, and fuses. |
| 3.3V     | +3.3V Logic                          | Red   | ON: Logic power supply is good. OFF: Logic power supply bad, call tech support.                                  |
| 5V       | +5V Logic                            | Red   | ON: Logic power supply is good. OFF: Logic power supply bad, call tech support.                                  |
| 12V      | +12V Backbox Illumination            | Red   | ON: Back box LED power good. OFF: Backbox LED power bad, call tech support.                                      |
| VA       | +30V Audio                           | Red   | ON: Audio power supply is good. OFF: Audio power supply off, call tech support.                                  |
| VNB      | +9V Node Bus                         | Red   | Power for the Node bus. ON: Power for node bus good. OFF: Power to node bus not detected, call tech support.     |
| 5V (CPU) | +5V Logic                            | Red   | ON: Logic power supply is good. OFF: Logic power supply bad, call tech support.                                  |
| SDIO ACT | Not Used                             | Red   | Should remain unlit as it is not currently used.                                                                 |
| STATUS   | CPU Heartbeat, System Status         | Red   | Double blink ~1/2 second: Good, Processor running. OFF: Processor not running, call tech support.                |
| μSD ACT  | Activity indicator for micro SD Card | Red   | Should blink rapidly when reading or writing to micro SD card.                                                   |
| D23      | Netbridge Status                     | Red   | Should blink once every ~1/2 second.                                                                             |

# SPIKE-2 CPU NODE 0 CONTINUED

## AUDIO PINOUTS

| ID  | Type               | Pin | Description              | Minimum Impedance | Max Power (RMS) |
|-----|--------------------|-----|--------------------------|-------------------|-----------------|
| CN1 | .156" 5-pin Header | 1   | Speaker Right Ground (-) | 4 Ohms            | -               |
|     |                    | 2   | Speaker Right (+)        | 4 Ohms            | 20W             |
|     |                    | 3   | n/c                      | -                 | -               |
|     |                    | 4   | Speaker Left Ground (-)  | 4 Ohms            | -               |
|     |                    | 5   | Speaker Left (+)         | 4 Ohms            | 20W             |
| CN3 | .100" 7-pin Header | 1   | GND                      | -                 | -               |
|     |                    | 2   | L-HP                     | 16 Ohms           | 15 mW           |
|     |                    | 3   | R-HP                     | 16 Ohms           | 15 mW           |
|     |                    | 4   | GND                      | -                 | -               |
|     |                    | 5   | Headphone Detect         | -                 | -               |
|     |                    | 6   | Headphone vol +          | -                 | -               |
|     |                    | 7   | Headphone vol -          | -                 | -               |
| CN4 | .156" 2-pin Header | 1   | Woofer Ground (-)        | 8 Ohms            | -               |
|     |                    | 2   | Woofer Out (+)           | 8 Ohms            | 40W             |
| CN5 | .100" 7-pin Header | 1   | GND                      | -                 | -               |
|     |                    | 2   | L-IN                     | 30K Ohms          | 0.6VRMS         |
|     |                    | 3   | R-IN                     | 30K Ohms          | 0.6VRMS         |
|     |                    | 4   | GND                      | -                 | -               |
|     |                    | 5   | L-OUT                    | 10K Ohms          | 1.5V            |
|     |                    | 6   | R-OUT                    | 10K Ohms          | 1.5V            |
|     |                    | 7   | Woofer Line Out          | 10K Ohms          | 1.5V            |

## COUNTRY CODES (DIP S2)

| Country        | DIP S2 |     |     |     |     |     |     |     |
|----------------|--------|-----|-----|-----|-----|-----|-----|-----|
|                | 1      | 2   | 3   | 4   | 5   | 6   | 7   | 8   |
| USA            | OFF    | OFF | OFF | OFF | OFF | OFF | OFF | OFF |
| Austria        | ON     | OFF | OFF | OFF | OFF | OFF | OFF | OFF |
| Australia      | ON     | OFF | ON  | ON  | OFF | OFF | OFF | OFF |
| Belgium        | OFF    | ON  | OFF | OFF | OFF | OFF | OFF | OFF |
| Canada 1       | ON     | ON  | OFF | OFF | OFF | OFF | OFF | OFF |
| Canada 2       | OFF    | ON  | OFF | ON  | ON  | OFF | OFF | OFF |
| China          | OFF    | OFF | ON  | ON  | ON  | OFF | OFF | OFF |
| Croatia        | OFF    | ON  | ON  | OFF | ON  | OFF | OFF | OFF |
| Denmark        | ON     | OFF | OFF | ON  | OFF | OFF | OFF | OFF |
| Finland        | ON     | OFF | ON  | OFF | OFF | OFF | OFF | OFF |
| France         | OFF    | ON  | ON  | OFF | OFF | OFF | OFF | OFF |
| Germany        | ON     | ON  | ON  | OFF | OFF | OFF | OFF | OFF |
| Greece         | ON     | ON  | ON  | ON  | OFF | OFF | OFF | OFF |
| Italy          | OFF    | OFF | OFF | ON  | OFF | OFF | OFF | OFF |
| Japan          | ON     | OFF | ON  | OFF | ON  | OFF | OFF | OFF |
| Middle East    | ON     | ON  | ON  | OFF | ON  | OFF | OFF | OFF |
| Netherlands    | OFF    | OFF | ON  | OFF | OFF | OFF | OFF | OFF |
| New Zealand    | OFF    | OFF | OFF | OFF | ON  | OFF | OFF | OFF |
| Norway         | OFF    | ON  | OFF | ON  | OFF | OFF | OFF | OFF |
| Portugal       | ON     | OFF | OFF | OFF | OFF | ON  | OFF | OFF |
| Russia         | ON     | OFF | OFF | ON  | ON  | OFF | OFF | OFF |
| S. Africa      | OFF    | OFF | ON  | OFF | ON  | OFF | OFF | OFF |
| Spain          | OFF    | ON  | OFF | OFF | ON  | OFF | OFF | OFF |
| Sweden         | ON     | ON  | OFF | ON  | OFF | OFF | OFF | OFF |
| Switzerland    | OFF    | OFF | ON  | ON  | OFF | OFF | OFF | OFF |
| Taiwan         | OFF    | OFF | OFF | ON  | ON  | OFF | OFF | OFF |
| United Kingdom | OFF    | ON  | ON  | ON  | OFF | OFF | OFF | OFF |




Figure 4.1.1. SPIKE 2 CPU Node connector detail.

## COIN DOOR SERVICE SWITCH WIRING




Figure 4.1.2. Service switch wiring. Note that the Cabinet Node must be present and CN10 and CN12 connected for the Coin Door Service Switches to function correctly.

**HIGHLIGHTED** = Factory Default      **HIGHLIGHTED** = Not Shown on Coin Card

# EURO SUMMARY & INTERNATIONAL (EURO) STANDARD PRICING SELECT TABLE

| CPU/SOUND PCB<br>DIP SWITCH SW1<br>SETTING |                 | COUNTRY<br>SETTING<br>OPTION(S) | COIN MECHANISMS (SWITCHES)<br>COINS THRU ... SLOT: |        |       |               | PRICING SCHEME<br>Number of Plays (Credits) for Price Amount Shown<br>See "Appendix J" for Coin Cards Examples & Info! | Requires SPI<br>Coin Card(s)<br>Part Number |
|--------------------------------------------|-----------------|---------------------------------|----------------------------------------------------|--------|-------|---------------|------------------------------------------------------------------------------------------------------------------------|---------------------------------------------|
| Pos.                                       | 1 2 3 4 5 6 7 8 | Default Highlighted             | LEFT                                               | CENTER | RIGHT | 4TH           |                                                                                                                        |                                             |
| ON                                         | SEE BELOW       | Euro 1                          |                                                    |        |       |               | EUR // EUROPEAN UNION EUROS // [ € ]                                                                                   |                                             |
| OFF                                        | SETTINGS        | Euro 2                          |                                                    |        |       |               | 1/0.50                                                                                                                 | 755-5401-01-Y                               |
|                                            |                 | Euro 3                          |                                                    |        |       |               | 1/0.50 2/1.00 3/1.50 5/2.00                                                                                            | 755-5401-02-Y                               |
|                                            |                 | Euro 4                          |                                                    |        |       |               | 1/0.50 3/1.00                                                                                                          | 755-5401-03-Y                               |
|                                            |                 | Euro 5                          |                                                    |        |       |               | 1/0.50 2/1.00 3/1.50 6/2.00                                                                                            | 755-5401-04-Y                               |
|                                            |                 | Euro 6                          |                                                    |        |       |               | 1/0.50 3/1.00 4/1.50 7/2.00                                                                                            | 755-5401-05-Y                               |
|                                            |                 | Euro 7                          |                                                    |        |       |               | 2/0.50                                                                                                                 | 755-5401-06-Y                               |
|                                            |                 | Euro 8                          | 0.50                                               | 1.00   | 2.00  | 0.20 optional | 1/1.00 2/2.00 3/3.00 5/4.00                                                                                            | 755-5401-07-Y                               |
|                                            |                 | Euro 9                          |                                                    |        |       | 0.20 optional | 1/1.00 3/2.00                                                                                                          | 755-5401-08-Y                               |
|                                            |                 | Euro 10                         |                                                    |        |       |               | 1/1.00 2/1.50 3/2.00                                                                                                   | 755-5401-09-Y                               |
|                                            |                 | Euro 11                         |                                                    |        |       |               | 1/1.00 3/2.00 7/3.00                                                                                                   | 755-5401-10-Y                               |
|                                            |                 | Euro 12                         |                                                    |        |       |               | 1/1.00 4/2.00                                                                                                          | 755-5401-11-Y                               |
|                                            |                 |                                 |                                                    |        |       |               | 2/1.00 4/2.00 6/3.00 9/4.00                                                                                            | 755-5401-12-Y                               |

For a different **Euro Pricing Scheme** (other than Factory Default listed below), scroll through **Standard Adjustment 18**. Euro 1-12 or CUSTOM\* for new setting (reference above Euro 1-12 Summary). Keep the Country Dip Switch Setting the same as listed below.

| Pos. | 1 2 3 4 5 6 7 8 | Default Highlighted | LEFT | CENTER | RIGHT | 4TH | EUR // EUROPEAN UNION EUROS // [ € ] |               |
|------|-----------------|---------------------|------|--------|-------|-----|--------------------------------------|---------------|
| ON   | ▲               | AUSTRIA Euro 9      | 0.50 | 1.00   | 2.00  |     | 1/1.00 2/1.50 3/2.00                 | 755-5401-09-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | BELGIUM Euro 1      | 0.50 | 1.00   | 2.00  |     | 1/0.50                               | 755-5401-01-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | FINLAND Euro 8      | 0.50 | 1.00   | 2.00  |     | 1/1.00 3/2.00                        | 755-5401-08-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | FRANCE Euro 10      | 0.50 | 1.00   | 2.00  |     | 1/1.00 3/2.00 7/3.00                 | 755-5401-10-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | GERMANY 1           | 0.50 | 1.00   | 2.00  |     | 1/0.50                               | 755-5401-01-Y |
| OFF  | ▼               | GERMANY 2           |      |        |       |     | 1/0.50 2/1.00 3/1.50 5/2.00          | 755-5401-02-Y |
|      |                 | GERMANY 3           |      |        |       |     | 1/0.50 2/1.00 3/1.50 6/2.00          | 755-5401-04-Y |
| ON   | ▲               | GREECE Euro 8       | 0.50 | 1.00   | 2.00  |     | 1/1.00 3/2.00                        | 755-5401-08-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | ITALY 1             | 0.50 |        | 0.50  |     | 1/0.50                               | 755-5401-01-Y |
| OFF  | ▼               | ITALY 2             |      |        |       |     | 1/1.00 3/2.00                        | 755-5401-08-Y |
| ON   | ▲               | NETHERLANDS Euro 3  | 0.50 | 1.00   | 2.00  |     | 1/0.50 3/1.00                        | 755-5401-03-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | PORTUGAL            | 0.50 |        | 0.50  |     | 1/0.50                               | 755-5401-01-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |
| ON   | ▲               | SPAIN Euro 8        | 0.50 | 1.00   | 2.00  |     | 1/1.00 3/2.00                        | 755-5401-08-Y |
| OFF  | ▼               |                     |      |        |       |     |                                      |               |


**HIGHLIGHTED** = Factory Default

**HIGHLIGHTED** = Not Shown on Coin Card

## 4.2 CABINET NODE 1

**520-6967-72**


| ID  | Type                                                     | Pin | Description             | Wire Color |
|-----|----------------------------------------------------------|-----|-------------------------|------------|
| CN1 | .100" 8-Pin Header<br>Universal Card Link                | 1   | 12V                     | -          |
|     |                                                          | 2   | Coin 1                  | -          |
|     |                                                          | 3   | Meter 1                 | -          |
|     |                                                          | 4   | N/C                     | -          |
|     |                                                          | 5   | Notch                   | -          |
|     |                                                          | 6   | Coin Enable             | -          |
|     |                                                          | 7   | Ticket Enable           | -          |
|     |                                                          | 8   | Ground                  | -          |
| CN2 | .100" 5-Pin Header<br>low ticket                         | 1   | Ground                  | -          |
|     |                                                          | 2   | Ticket Low sw.          | -          |
|     |                                                          | 3   | Key                     | -          |
|     |                                                          | 4   | Ticket Low              | -          |
|     |                                                          | 5   | 5V Out                  | -          |
| CN3 | .100" 3-Pin Header<br>Meter 1                            | 1   | Meter 12V (+)           | RED        |
|     |                                                          | 2   | Meter (-)               | BLK        |
|     |                                                          | 3   | N/C                     | -          |
| CN4 | .100" 3-Pin Header<br>Meter 2                            | 1   | Meter 12V (+)           | RED        |
|     |                                                          | 2   | Meter (-)               | BLK        |
|     |                                                          | 3   | N/C                     | -          |
| CN5 | .100" 9-Pin Header                                       | 1   | 5V Out                  | YEL/WHT    |
|     |                                                          | 2   | Coin LED Out            | YEL        |
|     |                                                          | 3   | Ground                  | BLK        |
|     |                                                          | 4   | Slam Tilt In            | LGN/RED    |
|     |                                                          | 5   | Coin 5                  | PNK/GRN*   |
|     |                                                          | 6   | Coin 4                  | PNK/YEL*   |
|     |                                                          | 7   | Coin 3                  | PNK/ORN*   |
|     |                                                          | 8   | Coin 2                  | PNK/RED*   |
|     |                                                          | 9   | Coin 1                  | PNK/BRN*   |
| CN6 | .100" 14-Pin Header<br>Cabinet Left                      | 1   | 5V LED Power            | RED        |
|     |                                                          | 2   | Start 2 LED             | YEL-RED    |
|     |                                                          | 3   | Start 1 LED             | YEL-BRN    |
|     |                                                          | 4   | Spare LED               | -          |
|     |                                                          | 5   | Ground                  | BLK-WHT    |
|     |                                                          | 6   | Spare Left              | -          |
|     |                                                          | 7   | Tilt Input              | WHT        |
|     |                                                          | 8   | Door Open               | -          |
|     |                                                          | 9   | Start 2 Switch          | GRY-WHT    |
|     |                                                          | 10  | Start 1 Switch          | GRY        |
|     |                                                          | 11  | N/C                     | -          |
|     |                                                          | 12  | N/C                     | -          |
|     |                                                          | 13  | N/C                     | -          |
|     |                                                          | 14  | N/C                     | -          |
| CN7 | .100" 12-Pin Header<br>Cabinet Right                     | 1   | 5V LED Power            | RED        |
|     |                                                          | 2   | Plunge 2 LED            | RED-WHT    |
|     |                                                          | 3   | Plunge 1 LED            | GRN-WHT    |
|     |                                                          | 4   | Spare LED 2             | BLU-WHT    |
|     |                                                          | 5   | Ground                  | BLK-WHT    |
|     |                                                          | 6   | Spare Right In          | -          |
|     |                                                          | 7   | Plunge 2 Switch         | -          |
|     |                                                          | 8   | Plunge 1 Switch         | -          |
|     |                                                          | 9   | N/C                     | -          |
|     |                                                          | 10  | N/C                     | -          |
|     |                                                          | 11  | N/C                     | -          |
|     |                                                          | 12  | N/C                     | -          |
| CN8 | .100" 10-Pin Header<br>dual row.<br>Electronic Coin Mech | 1   | Ground                  | -          |
|     |                                                          | 2   | 12V                     | -          |
|     |                                                          | 3   | Coin 5                  | -          |
|     |                                                          | 4   | Coin 6                  | -          |
|     |                                                          | 5   | N/C                     | -          |
|     |                                                          | 6   | Coin Enable/Inhibit (+) | -          |
|     |                                                          | 7   | Coin 1                  | -          |
|     |                                                          | 8   | Coin 2                  | -          |
|     |                                                          | 9   | Coin 3                  | -          |
|     |                                                          | 10  | Coin 4                  | -          |



|      |                                            |    |                              |         |
|------|--------------------------------------------|----|------------------------------|---------|
| CN9  | .100" 6-Pin Header<br>Dollar Bill Acceptor | 1  | Coin Enable/DBA Inhibit (-)  | -       |
|      |                                            | 2  | Coin Enable/DBA Inhibit (+)  | -       |
|      |                                            | 3  | Key                          | Key     |
|      |                                            | 4  | DBA 12V                      | -       |
|      |                                            | 5  | Coin 6 / DBA Credit          | -       |
|      |                                            | 6  | Ground                       | -       |
| CN10 | .100" 6-Pin Header<br>Service Switch In    | 1  | Service Back (To Coindoor)   | LGN-BLK |
|      |                                            | 2  | Service Down (To Coindoor)   | LGN-BLU |
|      |                                            | 3  | Service Up (To Coindoor)     | LGN-VIO |
|      |                                            | 4  | Service Select (To Coindoor) | LGN-GRY |
|      |                                            | 5  | Key                          | Key     |
|      |                                            | 6  | Service Ground (To Coindoor) | BLK     |
| CN11 | .100" 5-Pin Header<br>Ticket Dispenser     | 1  | 12V                          | RED     |
|      |                                            | 2  | N/C                          | -       |
|      |                                            | 3  | Ticket Dispenser Enable      | WHT     |
|      |                                            | 4  | Ground                       | BLK     |
|      |                                            | 5  | Ticket Dispenser Notch       | BLU     |
| CN12 | .100" 10-Pin Header<br>CPU Direct Switches | 1  | Service Back (To CPU)        | LGN-BLK |
|      |                                            | 2  | Service Down (To CPU)        | LGN-BLU |
|      |                                            | 3  | Service Up (To CPU)          | LGN-VIO |
|      |                                            | 4  | Service Select (To CPU)      | LGN-GRY |
|      |                                            | 5  | Power Present                | LGN-ORG |
|      |                                            | 6  | Service Ground (To CPU)      | BLK-WHT |
|      |                                            | 7  | N/C                          | -       |
|      |                                            | 8  | N/C                          | -       |
|      |                                            | 9  | N/C                          | -       |
|      |                                            | 10 | N/C                          | -       |
| CN14 | .156" 5-Pin Header<br>Power Input          | 1  | Ground                       | BLK     |
|      |                                            | 2  | Key                          | Key     |
|      |                                            | 3  | N/C                          | -       |
|      |                                            | 4  | N/C                          | -       |
|      |                                            | 5  | 48VDC In                     | GRY-YEL |
| CN15 | .100" 6-Pin Header<br>Spare LED's          | 1  | 5V LED Power                 | -       |
|      |                                            | 2  | Key                          | Key     |
|      |                                            | 3  | Spare LED 3                  | -       |
|      |                                            | 4  | Spare LED 4                  | -       |
|      |                                            | 5  | Spare LED 5                  | -       |
|      |                                            | 6  | Spare LED 6                  | -       |
| CN16 | .156" 5-Pin Header<br>Shaker Motor         | 1  | Shaker Motor (-)             | BLU     |
|      |                                            | 2  | Shaker Motor (-)             | -       |
|      |                                            | 3  | Shaker Motor (+)             | -       |
|      |                                            | 4  | Key                          | Key     |
|      |                                            | 5  | Shaker Motor (+)             | RED     |
|      |                                            |    | *Varies by country model     |         |

## 4.3 LOWER PLAYFIELD 48V DRIVER PINOUT NODE 8

520-7017-72




| ID   | Type                          | Pin | Description              | Wire Color |
|------|-------------------------------|-----|--------------------------|------------|
| SW1  | Address DIP                   | -   | Node 8 - OFF-OFF-OFF-OFF | -          |
| CN4  | RJ45                          | -   | SPIKE Node Bus           | Multi      |
| CN5  | RJ45                          | -   | SPIKE Node Bus           | Multi      |
| CN6  | .156" 5-Pin Header Node Power | 1   | Ground                   | BLK        |
|      |                               | 2   | Key                      | Key        |
|      |                               | 3   | N/C                      | -          |
|      |                               | 4   | N/C                      | -          |
|      |                               | 5   | 48VDC In                 | GRY        |
| CN7  | .156" 4-Pin Header (White)    | 1   | 48V Driver Power         | GRY-ORG    |
|      |                               | 2   | 8-DR-8 Driver Return     | -          |
|      |                               | 3   | 8-DR-6 Driver Return     | YEL-BLK    |
|      |                               | 4   | 8-DR-7 Driver Return     | YEL-BRN    |
| CN8  | .156 11-Pin Header (White)    | 1   | 48V Driver Power         | GRY-ORG    |
|      |                               | 2   | 48V Driver Power         | GRY-ORG    |
|      |                               | 3   | 48V Driver Power         | GRY-ORG    |
|      |                               | 4   | 48V Driver Power         | GRY-ORG    |
|      |                               | 5   | 8-DR-0 Driver Return     | ORG-GRN    |
|      |                               | 6   | 8-DR-5 Driver Return     | ORG-YEL    |
|      |                               | 7   | 8-DR-1 Driver Return     | ORG-GRY    |
|      |                               | 8   | 8-DR-8 Driver Return     | -          |
|      |                               | 9   | 8-DR-4 Driver Return     | ORG-WHT    |
|      |                               | 10  | 8-DR-2 Driver Return     | ORG-VIO    |
|      |                               | 11  | 8-DR-3 Driver Return     | ORG-BLU    |
| CN9  | .100" 8-Pin Header            | 1   | V+                       | -          |
|      |                               | 2   | V+                       | -          |
|      |                               | 3   | 8-SW-24 Switch           | GRY-RED    |
|      |                               | 4   | 8-SW-25 Switch           | GRY-BRN    |
|      |                               | 5   | 8-SW-26 Switch           | VIO-WHT    |
|      |                               | 6   | 8-SW-27 Switch           | -          |
|      |                               | 7   | Ground                   | BLK-GRN    |
|      |                               | 8   | Ground                   | BLK-VIO    |
| CN10 | .100" 9-Pin Header            | 1   | V+                       | -          |
|      |                               | 2   | 8-SW-28 Switch           | GRY-WHT    |
|      |                               | 3   | 8-SW-29 Switch           | GRY-VIO    |
|      |                               | 4   | 8-SW-30 Switch           | GRY-BLU    |
|      |                               | 5   | 8-SW-31 Switch           | GRY-GRN    |
|      |                               | 6   | 8-SW-16 Switch           | GRY-YEL    |
|      |                               | 7   | Ground                   | BLK-GRN    |
|      |                               | 8   | Ground                   | BLK-GRN    |
|      |                               | 9   | Ground                   | BLK-GRN    |

|      |                                        |    |                      |         |
|------|----------------------------------------|----|----------------------|---------|
| CN11 | .100" 12-Pin Header                    | 1  | V+                   | -       |
|      |                                        | 2  | 8-SW-26 Switch       | -       |
|      |                                        | 3  | 8-SW-27 Switch       | -       |
|      |                                        | 4  | 8-SW-17 Switch       | LGN-RED |
|      |                                        | 5  | 8-SW-18 Switch       | LGN-ORG |
|      |                                        | 6  | 8-SW-19 Switch       | LGN-YEL |
|      |                                        | 7  | 8-SW-20 Switch       | LGN-BLU |
|      |                                        | 8  | 8-SW-21 Switch       | LGN-VIO |
|      |                                        | 9  | 8-SW-22 Switch       | LGN-GRY |
|      |                                        | 10 | 8-SW-23 Switch       | LGN-WHT |
|      |                                        | 11 | Ground               | BLK-ORG |
|      |                                        | 12 | Ground               | BLK-ORG |
| CN12 | .100" 10-Pin Header (Orange)           | 1  | V+                   | RED     |
|      |                                        | 2  | 8-SW-8 Switch        | WHT-BRN |
|      |                                        | 3  | 8-SW-9 Switch        | WHT-RED |
|      |                                        | 4  | 8-SW-10 Switch       | WHT-ORG |
|      |                                        | 5  | 8-SW-11 Switch       | WHT-YEL |
|      |                                        | 6  | 8-SW-12 Switch       | -       |
|      |                                        | 7  | 8-SW-13 Switch       | -       |
|      |                                        | 8  | 8-SW-14 Switch       | -       |
|      |                                        | 9  | 8-SW-15 Switch       | PNK-BRN |
|      |                                        | 10 | Ground               | BLK-RED |
| CN13 | .100" 10-Pin Header                    | 1  | V+                   | -       |
|      |                                        | 2  | 8-SW-0 Switch        | -       |
|      |                                        | 3  | 8-SW-1 Switch        | -       |
|      |                                        | 4  | 8-SW-2 Switch        | -       |
|      |                                        | 5  | 8-SW-3 Switch        | -       |
|      |                                        | 6  | 8-SW-4 Switch        | -       |
|      |                                        | 7  | 8-SW-5 Switch        | -       |
|      |                                        | 8  | 8-SW-6 Switch        | -       |
|      |                                        | 9  | 8-SW-7 Switch        | -       |
|      |                                        | 10 | Ground               | -       |
| CN14 | .100" 8-Pin Header                     | 1  | Ground               | -       |
|      |                                        | 2  | 8-LP-7 Driver Return | BRN-ORG |
|      |                                        | 3  | 8-LP-6 Driver Return | BRN-RED |
|      |                                        | 4  | 8-LP-5 Driver Return | BRN     |
|      |                                        | 5  | 8-LP-4 Driver Return | BRN-YEL |
|      |                                        | 6  | 8-LP-3 Driver Return | BRN-BLU |
|      |                                        | 7  | LED V+               | YEL     |
|      |                                        | 8  | LED V+               | YEL     |
| CN15 | .100" 7-Pin Header                     | 1  | LED V+               | YEL-RED |
|      |                                        | 2  | LED V+               | YEL-BLK |
|      |                                        | 3  | LED V+               | -       |
|      |                                        | 4  | -                    | -       |
|      |                                        | 5  | 8-LP-0 GI Return     | RED-BLK |
|      |                                        | 6  | 8-LP-1 GI Return     | WHT-BLK |
|      |                                        | 7  | 8-LP-2 GI Return     | -       |
| CN2  | .100" 6-Pin Header, Node Extension Bus | 1  | Ground               | BLK     |
|      |                                        | 2  | DIN                  | VIO-BLK |
|      |                                        | 3  | DOUT                 | VIO-BRN |
|      |                                        | 4  | SCK                  | VIO-RED |
|      |                                        | 5  | RCK                  | VIO-ORG |
|      |                                        | 6  | V+                   | RED     |
| CN3  | .100" 6-Pin Header, Node Extension Bus | 1  | Ground               | BLK     |
|      |                                        | 2  | DIN                  | VIO-BLK |
|      |                                        | 3  | DOUT                 | VIO-BRN |
|      |                                        | 4  | SCK                  | VIO-RED |
|      |                                        | 5  | RCK                  | VIO-ORG |
|      |                                        | 6  | V+                   | RED     |

## 4.4 MID UPPER PLAYFIELD 48V DRIVER PINOUT NODE 9

### 520-7017-72




| ID   | Type                             | Pin | Description             | Wire Color |
|------|----------------------------------|-----|-------------------------|------------|
| SW1  | Address DIP                      | -   | Node 9 - OFF-OFF-ON-OFF | -          |
| CN4  | RJ45                             | -   | SPIKE Node Bus          | Multi      |
| CN5  | RJ45                             | -   | SPIKE Node Bus          | Multi      |
| CN6  | .156" 5-Pin Header<br>Node Power | 1   | Ground                  | BLK        |
|      |                                  | 2   | Key                     | Key        |
|      |                                  | 3   | N/C                     | -          |
|      |                                  | 4   | N/C                     | -          |
|      |                                  | 5   | 48VDC In                | GRY        |
| CN7  | .156" 4-Pin Header<br>(White)    | 1   | 48V Driver Power        | GRY-BRN    |
|      |                                  | 2   | 9-DR-8 Driver Return    | YEL-GRN    |
|      |                                  | 3   | 9-DR-6 Driver Return    | YEL-ORG    |
|      |                                  | 4   | 9-DR-7 Driver Return    | BRN-BLK    |
| CN8  | .156 11-Pin Header<br>(White)    | 1   | 48V Driver Power        | GRY-BRN    |
|      |                                  | 2   | 48V Driver Power        | GRY-BRN    |
|      |                                  | 3   | 48V Driver Power        | GRY-BRN    |
|      |                                  | 4   | 48V Driver Power        | GRY-BRN    |
|      |                                  | 5   | 9-DR-0 Driver Return    | YEL-BLU    |
|      |                                  | 6   | 9-DR-5 Driver Return    | YEL-VIO    |
|      |                                  | 7   | 9-DR-1 Driver Return    | BRN        |
|      |                                  | 8   | 9-DR-8 Driver Return    | -          |
|      |                                  | 9   | 9-DR-4 Driver Return    | ORG-RED    |
|      |                                  | 10  | 9-DR-2 Driver Return    | ORG-BLK    |
|      |                                  | 11  | 9-DR-3 Driver Return    | ORG-BRN    |
| CN9  | .100" 8-Pin Header               | 1   | V+                      | RED        |
|      |                                  | 2   | V+                      | -          |
|      |                                  | 3   | 9-SW-24 Switch          | TAN-BLK    |
|      |                                  | 4   | 9-SW-25 Switch          | TAN-RED    |
|      |                                  | 5   | 9-SW-26 Switch          | -          |
|      |                                  | 6   | 9-SW-27 Switch          | -          |
|      |                                  | 7   | Ground                  | BLK-BLU    |
|      |                                  | 8   | Ground                  | -          |
| CN10 | .100" 9-Pin Header               | 1   | V+                      | -          |
|      |                                  | 2   | 9-SW-28 Switch          | GRY-BLK    |
|      |                                  | 3   | 9-SW-29 Switch          | GRY-BRN    |
|      |                                  | 4   | 9-SW-30 Switch          | GRY-RED    |
|      |                                  | 5   | 9-SW-31 Switch          | GRY-ORG    |
|      |                                  | 6   | 9-SW-16 Switch          | GRY-YEL    |
|      |                                  | 7   | Ground                  | BLK-BLU    |
|      |                                  | 8   | Ground                  | BLK-BLU    |
|      |                                  | 9   | Ground                  | BLK-BLU    |

|      |                                        |    |                      |         |
|------|----------------------------------------|----|----------------------|---------|
| CN11 | .100" 12-Pin Header                    | 1  | V+                   | -       |
|      |                                        | 2  | 9-SW-26 Switch       | LGN-GRY |
|      |                                        | 3  | 9-SW-27 Switch       | LGN     |
|      |                                        | 4  | 9-SW-17 Switch       | TAN-YEL |
|      |                                        | 5  | 9-SW-18 Switch       | TAN-GRN |
|      |                                        | 6  | 9-SW-19 Switch       | TAN-BLU |
|      |                                        | 7  | 9-SW-20 Switch       | TAN-VIO |
|      |                                        | 8  | 9-SW-21 Switch       | TAN-WHT |
|      |                                        | 9  | 9-SW-22 Switch       | TAN     |
|      |                                        | 10 | 9-SW-23 Switch       | TAN-ORG |
|      |                                        | 11 | Ground               | BLK-GRY |
|      |                                        | 12 | Ground               | BLK-GRY |
| CN12 | .100" 10-Pin Header (Orange)           | 1  | V+                   | RED     |
|      |                                        | 2  | 9-SW-8 Switch        | -       |
|      |                                        | 3  | 9-SW-9 Switch        | PNK-ORG |
|      |                                        | 4  | 9-SW-10 Switch       | PNK-YEL |
|      |                                        | 5  | 9-SW-11 Switch       | PNK-GRN |
|      |                                        | 6  | 9-SW-12 Switch       | PNK-BLU |
|      |                                        | 7  | 9-SW-13 Switch       | PNK-VIO |
|      |                                        | 8  | 9-SW-14 Switch       | PNK-GRY |
|      |                                        | 9  | 9-SW-15 Switch       | PNK-WHT |
|      |                                        | 10 | Ground               | BLK-WHT |
| CN13 | .100" 10-Pin Header                    | 1  | V+                   | RED     |
|      |                                        | 2  | 9-SW-0 Switch        | WHT-BRN |
|      |                                        | 3  | 9-SW-1 Switch        | WHT-RED |
|      |                                        | 4  | 9-SW-2 Switch        | WHT-ORG |
|      |                                        | 5  | 9-SW-3 Switch        | WHT-YEL |
|      |                                        | 6  | 9-SW-4 Switch        | WHT-GRN |
|      |                                        | 7  | 9-SW-5 Switch        | WHT-BLU |
|      |                                        | 8  | 9-SW-6 Switch        | WHT-VIO |
|      |                                        | 9  | 9-SW-7 Switch        | WHT-GRY |
|      |                                        | 10 | Ground               | BLK-BRN |
| CN14 | .100" 8-Pin Header                     | 1  | Ground               | BLK     |
|      |                                        | 2  | 9-LP-7 Driver Return | BRN-YEL |
|      |                                        | 3  | 9-LP-6 Driver Return | BRN-ORG |
|      |                                        | 4  | 9-LP-5 Driver Return | BRN-RED |
|      |                                        | 5  | 9-LP-4 Driver Return | BRN-BLU |
|      |                                        | 6  | 9-LP-3 Driver Return | BRN-GRN |
|      |                                        | 7  | LED V+               | YEL     |
|      |                                        | 8  | LED V+               | -       |
| CN15 | .100" 7-Pin Header                     | 1  | LED V+               | YEL-RED |
|      |                                        | 2  | LED V+               | YEL-BLK |
|      |                                        | 3  | LED V+               | -       |
|      |                                        | 4  | -                    | -       |
|      |                                        | 5  | 9-LP-0 GI Return     | RED-BLK |
|      |                                        | 6  | 9-LP-1 GI Return     | WHT-BLK |
|      |                                        | 7  | 9-LP-2 GI Return     | -       |
| CN2  | .100" 6-Pin Header, Node Extension Bus | 1  | Ground               | -       |
|      |                                        | 2  | DIN                  | -       |
|      |                                        | 3  | DOUT                 | -       |
|      |                                        | 4  | SCK                  | -       |
|      |                                        | 5  | RCK                  | -       |
|      |                                        | 6  | V+                   | -       |
| CN3  | .100" 6-Pin Header, Node Extension Bus | 1  | Ground               | BLK     |
|      |                                        | 2  | DIN                  | VIO-BLK |
|      |                                        | 3  | DOUT                 | VIO-BRN |
|      |                                        | 4  | SCK                  | VIO-RED |
|      |                                        | 5  | RCK                  | VIO-ORG |
|      |                                        | 6  | V+                   | RED     |

## 4.5 LOWER MID LED BOARD 8B


520-8405-00



| ID  | Type                | Pin | Description        | Wire Color |
|-----|---------------------|-----|--------------------|------------|
| CN1 | .100" 4-Pin Header  | 1   | +5 VDC             | RED        |
|     |                     | 2   | +5 VDC             | RED        |
|     |                     | 3   | LED 1              | ORG BRN    |
|     |                     | 4   | LED 2              | ORG RED    |
| CN2 | .100" 3-Pin Header  | 1   | +5 VDC             | RED        |
|     |                     | 2   | NC                 | -          |
|     |                     | 3   | LED 3              | ORG        |
| CN3 | .100" 7-Pin Header  | 1   | Ground             | BLK        |
|     |                     | 2   | MISO Output Data   | VIO-BLK    |
|     |                     | 3   | MOSI Input Data    | VIO-BRN    |
|     |                     | 4   | SCK Serial Clock   | VIO-RED    |
|     |                     | 5   | RCK Register Clock | VIO-ORG    |
|     |                     | 6   | n/c                | -          |
|     |                     | 7   | +5 VDC IN          | RED        |
| CN4 | .100" 9-Pin Header  | 1   | +5 VDC             | RED        |
|     |                     | 2   | +5 VDC             | -          |
|     |                     | 3   | +5 VDC             | -          |
|     |                     | 4   | LED 18             | GRN RED    |
|     |                     | 5   | LED 19             | GRN        |
|     |                     | 6   | LED 20             | GRN BLU    |
|     |                     | 7   | LED 21             | GRN VIO    |
|     |                     | 8   | LED 22             | GRN GRY    |
|     |                     | 9   | LED 23             | GRN WHT    |
| CN5 | .100" 11-Pin Header | 1   | +5 VDC             | RED        |
|     |                     | 2   | +5 VDC             | -          |
|     |                     | 3   | +5 VDC             | -          |
|     |                     | 4   | LED 24             | RED BRN    |
|     |                     | 5   | LED 25             | GRN BRN    |
|     |                     | 6   | LED 26             | BLU BRN    |
|     |                     | 7   | LED 27             | YEL BRN    |
|     |                     | 8   | LED 28             | YEL RED    |
|     |                     | 9   | LED 29             | YEL ORG    |
|     |                     | 10  | LED 30             | YEL GRN    |
|     |                     | 11  | LED 31             | YEL BLU    |


|     |                     |    |        |         |
|-----|---------------------|----|--------|---------|
| CN6 | .100" 8-Pin Header  | 1  | +5 VDC | RED     |
|     |                     | 2  | +5 VDC | -       |
|     |                     | 3  | +5 VDC | -       |
|     |                     | 4  | +5 VDC | -       |
|     |                     | 5  | LED 32 | ORG GRN |
|     |                     | 6  | LED 33 | ORG BLU |
|     |                     | 7  | LED 34 | ORG VIO |
|     |                     | 8  | LED 35 | ORG GRY |
| CN7 | .100" 16-Pin Header | 1  | +5 VDC | RED     |
|     |                     | 2  | +5 VDC | RED     |
|     |                     | 3  | LED 36 | BLU BRN |
|     |                     | 4  | LED 37 | BLU RED |
|     |                     | 5  | LED 38 | RED ORG |
|     |                     | 6  | LED 39 | GRN ORG |
|     |                     | 7  | LED 40 | BLU ORG |
|     |                     | 8  | LED 41 | BLU GRN |
|     |                     | 9  | LED 42 | BLU WHT |
|     |                     | 10 | LED 43 | BLU BLK |
|     |                     | 11 | LED 44 | BLU GRY |
|     |                     | 12 | LED 45 | RED YEL |
|     |                     | 13 | LED 46 | GRN YEL |
|     |                     | 14 | LED 47 | BLU YEL |
|     |                     | 15 | LED 48 | BLU     |
|     |                     | 16 | LED 49 | BLU VIO |
| CN8 | .100" 10-Pin Header | 1  | +5 VDC | RED     |
|     |                     | 2  | +5 VDC | RED     |
|     |                     | 3  | +5 VDC | -       |
|     |                     | 4  | LED 50 | RED VIO |
|     |                     | 5  | LED 51 | GRN VIO |
|     |                     | 6  | LED 52 | BLU VIO |
|     |                     | 7  | LED 53 | YEL VIO |
|     |                     | 8  | LED 54 | YEL GRY |
|     |                     | 9  | LED 55 | YEL WHT |
|     |                     | 10 | LED 56 | ORG YEL |

4.6 LOWER LEFT LED BOARD 8B1  
520-8406-00




| ID  | Type                | Pin | Description   | Wire Color |
|-----|---------------------|-----|---------------|------------|
| CN1 | .100" 13-Pin Header | 1   | +5 VDC        | RED        |
|     |                     | 2   | +5 VDC        | RED        |
|     |                     | 3   | LED 1 & LED 2 | GRN RED    |
|     |                     | 4   | LED 3         | GRN        |
|     |                     | 5   | LED 4         | GRN BLU    |
|     |                     | 6   | LED 5         | GRN VIO    |
|     |                     | 7   | LED 6         | GRN GRY    |
|     |                     | 8   | LED 7         | YEL BRN    |
|     |                     | 9   | LED 8-R       | RED BRN    |
|     |                     | 10  | LED 8-G       | GRN BRN    |
|     |                     | 11  | LED 8-B       | BLU BRN    |
|     |                     | 12  | LED 9         | GRN WHT    |
|     |                     | 13  | LED 10        | YEL RED    |
| CN2 | .100" 3-Pin Header  | 1   | +5 VDC        | RED        |
|     |                     | 2   | NC            | -          |
|     |                     | 3   | LED 9-OUT     | ORG        |
| CN3 | .100" 4-Pin Header  | 1   | +5 VDC        | RED        |
|     |                     | 2   | +5 VDC        | -          |
|     |                     | 3   | NC            | -          |
|     |                     | 4   | LED 7-OUT     | ORG        |

4.7 UPPER MID LED BOARD 8B2  
520-8414-00



| ID  | Type               | Pin | Description | Wire Color |
|-----|--------------------|-----|-------------|------------|
| CN1 | .100" 8-Pin Header | 1   | +5 VDC      | RED        |
|     |                    | 2   | LED 1       | ORG GRY    |
|     |                    | 3   | LED 2       | ORG VIO    |
|     |                    | 4   | LED 3       | ORG BLU    |
|     |                    | 5   | LED 4       | ORG GRN    |
|     |                    | 6   | LED 5       | YEL BLU    |
|     |                    | 7   | LED 6       | YEL GRN    |
|     |                    | 8   | LED 7       | YEL ORG    |

4.8 LOWER RIGHT LED BOARD 8B4  
520-8407-00




| ID  | Type               | Pin | Description | Wire Color |
|-----|--------------------|-----|-------------|------------|
| CN1 | .100" 6-Pin Header | 1   | +5 VDC      | RED        |
|     |                    | 2   | LED 1       | YEL GRY    |
|     |                    | 3   | LED 2       | YEL VIO    |
|     |                    | 4   | LED 3-R     | RED VIO    |
|     |                    | 5   | LED 3-G     | GRN VIO    |
|     |                    | 6   | LED 3-B     | BLU VIO    |



## 4.9 UPPER RIGHT LED BOARD 8B3


### 520-8408-00



| ID  | Type                | Pin | Description | Wire Color |
|-----|---------------------|-----|-------------|------------|
| CN1 | .100" 16-Pin Header | 1   | +5 VDC      | RED        |
|     |                     | 2   | +5 VDC      | RED        |
|     |                     | 3   | LED 1       | BLU BRN    |
|     |                     | 4   | LED 2       | BLU RED    |
|     |                     | 5   | LED 3       | -          |
|     |                     | 6   | LED 4-R     | RED ORG    |
|     |                     | 7   | LED 4-G     | GRN ORG    |
|     |                     | 8   | LED 4-B     | BLU ORG    |
|     |                     | 9   | LED 5       | BLU GRN    |
|     |                     | 10  | LED 6       | -          |
|     |                     | 11  | LED 7       | BLU BLK    |
|     |                     | 12  | LED 8       | BLU GRY    |
|     |                     | 13  | LED 9-R     | RED YEL    |
|     |                     | 14  | LED 9-G     | GRN YEL    |
|     |                     | 15  | LED 9-B     | BLU YEL    |
|     |                     | 16  | LED 10      | BLU WHT    |
| CN2 | .100" 3-Pin Header  | 1   | +5 VDC      | -          |
|     |                     | 2   | NC          | -          |
|     |                     | 3   | LED 3-OUT   | -          |
| CN3 | .100" 3-Pin Header  | 1   | +5 VDC      | -          |
|     |                     | 2   | NC          | -          |
|     |                     | 3   | LED 6-OUT   | -          |
| CN4 | .100" 4-Pin Header  | 1   | +5 VDC      | RED        |
|     |                     | 2   | +5 VDC      | -          |
|     |                     | 3   | NC          | -          |
|     |                     | 4   | LED 8-OUT   | BLU GRY    |
| CN5 | .100" 3-Pin Header  | 1   | +5 VDC      | RED        |
|     |                     | 2   | NC          | -          |
|     |                     | 3   | LED 10-OUT  | BLU WHT    |

## 4.10 UPPER LEFT LED BOARD 9A


### 520-8415-00



| ID  | Type                | Pin | Description        | Wire Color |
|-----|---------------------|-----|--------------------|------------|
| CN1 | .100" 7-Pin Header  | 1   | Ground             | BLK        |
|     |                     | 2   | MISO Output Data   | VIO-BLK    |
|     |                     | 3   | MOSI Input Data    | VIO-BRN    |
|     |                     | 4   | SCK Serial Clock   | VIO-RED    |
|     |                     | 5   | RCK Register Clock | VIO-ORG    |
|     |                     | 6   | NC                 | -          |
|     |                     | 7   | +5 VDC IN          | RED        |
| CN2 | .100" 10-Pin Header | 1   | +5 VDC             | RED        |
|     |                     | 2   | +5 VDC             | RED        |
|     |                     | 3   | LED 13             | BRN BLK    |
|     |                     | 4   | LED 14             | BRN        |
|     |                     | 5   | LED 15             | BRN RED    |
|     |                     | 6   | LED 16             | -          |
|     |                     | 7   | LED 17             | YEL ORG    |
|     |                     | 8   | LED 18             | YEL VIO    |
|     |                     | 9   | LED 19             | BLU WHT    |
|     |                     | 10  | LED 20             | BLU GRN    |
| CN3 | .100" 6-Pin Header  | 1   | +5 VDC             | RED        |
|     |                     | 2   | +5 VDC             | RED        |
|     |                     | 3   | LED 22             | BRN GRN    |
|     |                     | 4   | LED 23             | BRN VIO    |
|     |                     | 5   | LED 24             | BRN GRY    |
|     |                     | 6   | LED 25             | BRN WHT    |
| CN4 | .100" 14-Pin Header | 1   | +5 VDC             | RED        |
|     |                     | 2   | +5 VDC             | RED        |
|     |                     | 3   | LED 29             | RED GRY    |
|     |                     | 4   | LED 30             | GRN GRY    |
|     |                     | 5   | LED 31             | BLU GRY    |
|     |                     | 6   | LED 32             | ORG GRN    |
|     |                     | 7   | LED 33             | ORG BLU    |
|     |                     | 8   | LED 34             | ORG VIO    |
|     |                     | 9   | LED 35             | ORG WHT    |
|     |                     | 10  | LED 36             | ORG BLK    |
|     |                     | 11  | LED 37             | ORG RED    |
|     |                     | 12  | LED 38             | ORG BRN    |
|     |                     | 13  | LED 39             | YEL BRN    |
|     |                     | 14  | LED 40             | YEL RED    |
| CN5 | .100" 6-Pin Header  | 1   | Ground             | BLK        |
|     |                     | 2   | MISO Output Data   | VIO-BLK    |
|     |                     | 3   | MOSI Input Data    | VIO-BRN    |
|     |                     | 4   | SCK Serial Clock   | VIO-RED    |
|     |                     | 5   | RCK Register Clock | VIO-ORG    |
|     |                     | 6   | V+                 | RED        |

## 4.11 SERIAL MOTOR DRIVER BOARD 9B


### 520-6996-00



| ID  | Type                 | Pin | Description        | Wire Color |
|-----|----------------------|-----|--------------------|------------|
| CN1 | .100" 7-Pin Header   | 1   | Ground             | BLK        |
|     |                      | 2   | MISO Output Data   | VIO-BLK    |
|     |                      | 3   | MOSI Input Data    | VIO-BRN    |
|     |                      | 4   | SCK Serial Clock   | VIO-RED    |
|     |                      | 5   | RCK Register Clock | VIO-ORG    |
|     |                      | 6   | n/c                | -          |
|     |                      | 7   | +5 VDC IN          | RED        |
| CN2 | .156 4-Pin Connector | 1   | Ground             | -          |
|     |                      | 2   | DRIVE2-A           | GRY        |
|     |                      | 3   | DRIVE1-A           | BRN        |
|     |                      | 4   | V+                 | -          |
| CN3 | .156 3-Pin Connector | 1   | Ground             | -          |
|     |                      | 2   | DRIVE2-B           | -          |
|     |                      | 3   | DRIVE1-B           | -          |
|     |                      | 4   | V+                 | -          |
| CN4 | .100" 6-Pin Header   | 1   | Ground             | -          |
|     |                      | 2   | MISO Output Data   | -          |
|     |                      | 3   | MOSI Input Data    | -          |
|     |                      | 4   | SCK Serial Clock   | -          |
|     |                      | 5   | RCK Register Clock | -          |
|     |                      | 6   | V+                 | -          |
| CN5 | .156 5-Pin Connector | 1   | GND                | BLK        |
|     |                      | 2   | KEY                | Key        |
|     |                      | 3   | N/C                | -          |
|     |                      | 4   | N/C                | -          |
|     |                      | 5   | +48 VDC IN         | GRY        |

## 4.12 STEPPER MOTOR DRIVER BOARD


### 520-8424-00



| ID  | Type               | Pin | Description | Wire Color |
|-----|--------------------|-----|-------------|------------|
| CN1 | .100" 7-Pin Header | 1   | Ground      | BLK        |
|     |                    | 2   | Ground      | -          |
|     |                    | 3   | NC          | -          |
|     |                    | 4   | Enable      | BRN YEL    |
|     |                    | 5   | PHB         | BRN ORG    |
|     |                    | 6   | PHA         | BRN RED    |
|     |                    | 7   | +5 VDC      | YEL        |
| CN2 | .100" 6-Pin Header | 1   | DriveB-1    | RED        |
|     |                    | 2   | NC          | -          |
|     |                    | 3   | DriveB-0    | BLU        |
|     |                    | 4   | DriveA-1    | GRN        |
|     |                    | 5   | NC          | -          |
|     |                    | 6   | DriveA-0    | BLK        |
| CN3 | .156" 5-Pin Header | 1   | GND         | BLK        |
|     |                    | 2   | KEY         | -          |
|     |                    | 3   | GND         | -          |
|     |                    | 4   | +48V        | -          |
|     |                    | 5   | +48V        | GRY        |

### 4.13 TROUGH SERIAL OPTO RECEIVER EXTENSION 8A


520-7001-00



| ID  | Type               | Pin | Description        | Wire Color |
|-----|--------------------|-----|--------------------|------------|
| CN1 | .100" 7-Pin Header | 1   | Ground             | BLK        |
|     |                    | 2   | MISO Output Data   | VIO-BLK    |
|     |                    | 3   | MOSI Input Data    | -          |
|     |                    | 4   | SCK Serial Clock   | VIO-RED    |
|     |                    | 5   | RCK Register Clock | VIO-ORG    |
|     |                    | 6   | N/C                | -          |
|     |                    | 7   | +5 VDC IN          | RED        |

### 4.15 DUAL INTERRUPTER OPTO


520-8102-00



| ID  | Type               | Pin | Description | Wire Color |
|-----|--------------------|-----|-------------|------------|
| CN1 | .100" 4-Pin Header | 1   | +5 VDC      | RED        |
|     |                    | 2   | Opto 1      | TAN-BLK    |
|     |                    | 3   | Opto 2      | TAN-RED    |
|     |                    | 4   | GND         | BLK-BLU    |

### 4.14 TROUGH SERIAL OPTO TRANSMITTER


520-5344-00



| ID  | Type               | Pin | Description | Wire Color |
|-----|--------------------|-----|-------------|------------|
| CN1 | .100" 3-Pin Header | 1   | Ground      | BLK        |
|     |                    | 2   | N/C         | -          |
|     |                    | 3   | +5 VDC IN   | RED        |

### 4.16 MAIN POWER SUPPLY


011-5003-00



| ID  | Type           | Pin | Description        | Wire Color |
|-----|----------------|-----|--------------------|------------|
| CN1 | Screw Terminal | 1   | AC Line Hot In     | BLK        |
|     |                | 2   | AC Line Neutral In | WHT        |
|     |                | 3   | Earth Ground In    | GRN        |
|     |                | 4   | DC Ground          | BLK        |
|     |                | 5   | DC Ground          | BLK        |
|     |                | 6   | DC Ground          | BLK        |
|     |                | 7   | +48 V System Power | GRY        |
|     |                | 8   | +48 V System Power | GRY        |
|     |                | 9   | +48 V System Power | GRY        |

## 4.17 POWER DISTRIBUTION BOARD

520-8096-00



| ID  | Type                                                                               | Pin | Description                  | Wire Color |
|-----|------------------------------------------------------------------------------------|-----|------------------------------|------------|
| CN1 | .156 in 7-Pin Housing<br>Plug: 045-5259-07<br>Pin: 055-5331-00<br>Key: 060-5013-00 | 1   | +48 VDC IN                   | GRY        |
|     |                                                                                    | 2   | +48 VDC IN                   | GRY        |
|     |                                                                                    | 3   | +48 VDC IN                   | GRY        |
|     |                                                                                    | 4   | Key (n/c)                    | -          |
|     |                                                                                    | 5   | Ground                       | BLK        |
|     |                                                                                    | 6   | Ground                       | BLK        |
|     |                                                                                    | 7   | Ground                       | BLK        |
| CN2 | .093 in 3-Pos Plug<br>Plug: 045-5003-03<br>Pin: 055-5013-09                        | 1   | Line In (100-240 VAC)        | BLK        |
|     |                                                                                    | 2   | Neutral                      | WHT        |
|     |                                                                                    | 3   | Earth Ground                 | GRN        |
| CN3 | 0.084 in 4-Pos Plug<br>Plug: 045-5200-04<br>Pin: 055-5033-08                       | 1   | +48 VDC to CPU Node          | GRY        |
|     |                                                                                    | 2   | Door Interlock Switch Status | GRY/RED    |
|     |                                                                                    | 3   | Line Voltage Status          | VIO        |
|     |                                                                                    | 4   | Ground                       | BLK        |
| CN4 | 0.084 in 6-Pos Plug<br>Plug: 045-5200-06<br>Pin: 055-5033-08                       | 1   | Door Interlock Switch +48V   | GRY        |
|     |                                                                                    | 2   | Door Interlock Switch +48V   | -          |
|     |                                                                                    | 3   | Switched 48V Out (to Node 1) | GRY/YEL    |
|     |                                                                                    | 4   | Door Interlock Return Ground | GRY/RED    |
|     |                                                                                    | 5   | Door Interlock Return Ground | -          |
|     |                                                                                    | 6   | Ground (to Node 1)           | BLK        |
| CN5 | 0.084 in 12-Pos Plug<br>Plug: 045-5200-12<br>Pin: 055-5033-08                      | 1   | Switched 48V Node Power      | GRY        |
|     |                                                                                    | 2   | Switched 48V Node Power      | GRY        |
|     |                                                                                    | 3   | Switched 48V Node Power      | GRY        |
|     |                                                                                    | 4   | Switched 48V Node Power      | GRY        |
|     |                                                                                    | 5   | Switched 48V Node Power      | GRY        |
|     |                                                                                    | 6   | Switched 48V Node Power      | GRY        |
|     |                                                                                    | 7   | Node Ground                  | BLK        |
|     |                                                                                    | 8   | Node Ground                  | BLK        |
|     |                                                                                    | 9   | Node Ground                  | BLK        |
|     |                                                                                    | 10  | Node Ground                  | BLK        |
|     |                                                                                    | 11  | Node Ground                  | BLK        |
|     |                                                                                    | 12  | Node Ground                  | BLK        |
| CN6 | .156 in 3-Pos<br>Plug: 045-5259-03<br>Pin: 055-5331-00<br>(18awg)                  | 1   | Ground                       | -          |
|     |                                                                                    | 2   | Ground                       | -          |
|     |                                                                                    | 3   | +12VDC                       | -          |
| CN7 | .084 2-Pos<br>Plug: 045-5200-02<br>Pin: 055-5033-08                                | 1   | +48 VDC to Topper Node       | GRY        |
|     |                                                                                    | 2   | Ground                       | BLK        |


## 4.18 POWER PLUG WIRING

## CAUTION


**TO MAINTAIN SAFETY, GROUND WIRE FROM LINE FILTER IS TO BE MOUNTED FIRST ON GROUNDING STUD AND SECURED WITH NUT. ALL OTHER GROUNDS MAY THEN BE ATTACHED TO GROUNDING STUD.**

**REPLACE ALL FUSES WITH CORRECT CURRENT RATINGS!**

## NORTH AMERICA



## INTERNATIONAL



## LINE CORDS

| Part Number | Description                           |
|-------------|---------------------------------------|
| 034-6012-00 | Line Cord, 3m, 5-15P USA              |
| 034-6012-01 | Line Cord, 3m, CEE77P EUROPE          |
| 034-6012-02 | Line Cord, 3m, BS1363P United Kingdom |
| 034-6012-03 | Line Cord, 3m, AS-NZS4417P Australia  |
| 034-6012-04 | Line Cord, 3m, CEI23-16P Italy        |
| 034-6012-05 | Line Cord, 3m, SEV1011P Switzerland   |
| 034-6012-06 | Line Cord, 3m, JIS8303P Japan         |
| 034-6012-07 | Line Cord, 3m, SI32P Israel           |
| 034-6012-08 | Line Cord, 3m, BS546P S Africa, India |
| 034-6012-09 | Line Cord, 3m, IS6538P S. India       |

## LINE FUSES

| Line Voltage (Region)            | Fuse Current | Type               | Part Number |
|----------------------------------|--------------|--------------------|-------------|
| 120V (North America)             | 8 A          | Slow Blow 30G      | 200-5000-05 |
| 220/240v (Europe, Australia, UK) | 5 A          | Slow Blow 5 x 20mm | 200-5003-00 |

# 5. PARTS REFERENCE

## 5.1 PLAYFIELD RUBBER PARTS




Figure 5.1.1. Rubber o-ring part locations

### RUBBER O-RINGS

| ID | Qty | Size (ID) | Size (OD) | Durometer | Color | Part Number |
|----|-----|-----------|-----------|-----------|-------|-------------|
| 1  | 6   | 3/16"     |           | 50        | Black | 545-5348-01 |
| 2  | 2   | 5/16"     |           | 50        | Black | 545-5348-02 |
| 3  | 3   | 3/4"      |           | 50        | Black | 545-5348-04 |
| 4  | 2   | 1"        |           | 50        | Black | 545-5348-05 |
| 5  | 2   | 2-1/2"    |           | 50        | Black | 545-5348-09 |
| 6  | 8   |           | 7/16"     | 50        | Black | 545-5348-17 |

Figure 5.1.2. Rubber o-ring part numbers and usage. ID: Inner Diameter, OD: Outer Diameter, Durometer: Higher number is firmer, less bounce, and more durable.

| ID | Qty | Description                 | Color | Part Number |
|----|-----|-----------------------------|-------|-------------|
| 11 | 1   | Plunger Tip                 | Black | 545-5276-00 |
| 12 | 3   | Flipper Rubber              | Red   | 545-5277-22 |
| 13 | 1   | Bumper Pad (Sub-assemblies) | Black | 545-5105-00 |
| 14 | 3   | Bumper Pad (Flippers)       | Black | 545-5428-00 |

Figure 5.1.3. Other rubber part numbers and usage

### 5.2 RUBBER SIZE CHART





Figure 5.2.1. Rubber ring inner diameter sizing tool. Hold ring up to chart and read largest size on inside of ring. Dimensions are Inner Diameter (ID) unless otherwise noted as Outer Diameter (OD).


## 5.3 PLAYFIELD ASSEMBLIES, TOP



| ID | Part Number   | Description           | Qty |
|----|---------------|-----------------------|-----|
| 1  | 500-1117-N1   | Bottom Arch Assembly  | 1   |
| 2  | 755-51M1-12-Y | Instruction Card      | 1   |
| 3  | 755-5400-02-Y | Coin Card (USA)       | 1   |
| 4  | 535-8385-00   | Welded Hanger Bracket | 2   |
| 5  | 260-5000-00   | Pinballs              | 6   |
| 6  | 500-6815-00   | Bubble Level Assembly | 1   |
| 7  | 535-2039-04   | Shooter Lane Ramp     | 1   |
| 8  | 260-5016-00   | Newton Ball           | 1   |
| 9  | 550-5511-00   | Truck                 | 1   |
| 10 | 515-2033-00   | Left Wireform Ramp    | 1   |
| 11 | 535-1591-00   | Spinner Bracket       | 1   |
|    | 515-7088-00   | Spinner Target        | 1   |
| 12 | 511-7967-00   | Pop Bumper Gate       | 1   |
| 13 | 511-7962-00   | One Way Gate          | 1   |
| 14 | 550-5514-00   | T-Rex                 | 1   |

Figure 5.3.1. Major playfield assemblies, Top locations.

## 5.4 PLAYFIELD ASSEMBLIES, BOTTOM



| ID | Part Number | Description            | Qty |
|----|-------------|------------------------|-----|
| 1  | 520-7017-72 | Core Node Driver Board | 2   |
| 2  | 520-8405-00 | LED Board - 8b         | 1   |
| 3  | 520-8406-00 | LED Board - 8b1        | 1   |
| 4  | 520-8407-00 | LED Board - 8b4        | 1   |
| 5  | 520-8408-00 | LED Board - 8b3        | 1   |
| 6  | 520-8414-00 | LED Board - 8b2        | 2   |
| 7  | 520-8415-00 | LED Board - 9a         | 2   |
| 8  | 515-2041-00 | Opto Bracket           | 2   |
| 9  | 530-5133-00 | Pivot Pin              | 2   |
| 10 | 535-5988-01 | Edge Slide Bracket     | 2   |
| 11 | 535-0781-01 | Playfield Support Rail | 2   |

Figure 5.4.1. Major playfield assemblies, Bottom locations.

## 5.5 BACKBOX PARTS




Figure 5.5.1. Backbox external assemblies and components




Figure 5.5.2. Backbox internal assemblies and components

### EXTERNAL

| ID | Part Number | Description                   | Qty |
|----|-------------|-------------------------------|-----|
| 1  | 660-5052-00 | Backglass                     | 1   |
| 2  | 830-8426-M2 | Mirror Backglass [LE]         | 1   |
|    | 830-8427-M3 | Translite Art [Premium]       | 1   |
| 3  | 545-5018-17 | Plastic Extrusion 15-.450"    | 2   |
| 4  | 545-5018-15 | Glass Channel 26"             | 1   |
| 5  | 545-6313-01 | Glass Lift Channel 26"        | 1   |
| 6  | 500-9996-00 | LCD Speaker Panel Assembly    | 1   |
| 7  | 820-76M2-01 | Left Backbox Decal [LE]       | 1   |
|    | 820-76M3-01 | Left Backbox Decal [Premium]  | 1   |
| 8  | 820-76M2-02 | Right Backbox Decal [LE]      | 1   |
|    | 820-76M3-02 | Right Backbox Decal [Premium] | 1   |


### INTERNAL

| ID | Part Number | Description              | Qty |
|----|-------------|--------------------------|-----|
| 1  | 509-1003-01 | CPU Node Board           | 1   |
| 2  | 520-5343-01 | Power Distribution Board | 1   |
| 3  | 011-5003-00 | Power Supply 48V/500W    | 1   |
| 4  | 515-9769-00 | Utility Outlet (USA)     | 1   |
| 5  | 205-5001-00 | Fuse Holder-Screw in     | 1   |
|    | 200-5000-05 | 8A Fuse                  | 1   |
| 6  | 535-1130-00 | Cover AC                 | 1   |
| 7  | 535-1129-00 | Power supply bracket     | 1   |
| 8  | 535-1129-01 | Power supply bracket     | 1   |
| 9  | 180-5001-03 | Power Switch             | 1   |


## 5.6 SPEAKER PANEL PARTS

### 500-9996-00 / 500-2442-M2


| ID | Part Number    | Description                               | Qty |
|----|----------------|-------------------------------------------|-----|
| 1  | 031-5004-02    | Speaker [Premium]                         | 2   |
|    | 031-5017-00    | Speaker Upgrade 35w 4ohm 5-1/4" Dia. [LE] | 2   |
| 2  | 116-0023-00    | 1366 x 768 Display LCD Panel              | 1   |
| 3  | 237-6188-01    | Screw, M3x0.5 X 6MM PPH Sems Zinc         | 4   |
| 4  | 237-6307-06    | 6-32 X 3/8" Torx Stainless Steel Screw    | 2   |
| 5  | 240-5005-00    | 6-32 Nylon Stop Nut                       | 12  |
| 6  | 242-5001-00    | #6 Washer                                 | 16  |
| 7  | 355-5168-00-00 | Nut: Lock w/ Cam                          | 1   |
| 8  | 515-9842-00    | Speaker Panel-LCD                         | 1   |
| 9  | 515-9843-00    | Speaker Plate [Premium]                   | 2   |
|    | 515-1941-00    | Speaker Plate 5-1/4" [LE]                 | 2   |
| 10 | 515-9845-00    | Hinge, Speaker Panel, LCD                 | 2   |
| 11 | 545-9877-00    | LCD Window                                | 1   |
| 12 | 545-9877-01    | Spacer, Small - LCD Speaker Panel         | 4   |
| 13 | 626-5109-00    | Speaker Foam - LCD Panel [Premium]        | 2   |
| 14 | 535-2035-81    | Speaker Metal Ring - Goldtastic [LE]      | 2   |
| 15 | 626-5113-00    | Speaker Gasket [LE]                       | 2   |



## 5.7 CABINET PARTS




| ID | Part Number    | Description                                      | Qty |
|----|----------------|--------------------------------------------------|-----|
| 1  | 525-6026-01    | Cabinet (Melamine Single Button)                 | 1   |
| 2  | 535-5989-00    | Slide & Pivot Bracket - Left Side                | 1   |
| 3  | 535-5990-00    | Slide & Pivot Bracket - Right Side               | 1   |
| 4  | 535-2051-00    | Cabinet Playfield Support Bracket                | 1   |
| 5  | 500-2440-42    | Front Molding Assembly - Green Sparkle [LE]      | 1   |
|    | 500-2440-00    | Front Molding Assembly - Wrinkle Black [Premium] | 1   |
| 6  | 535-7999-42L   | Pivot Hinge, Left - Green Sparkle [LE]           | 1   |
|    | 535-7999-00    | Pivot Hinge, Left - Wrinkle Black [Premium]      | 1   |
| 7  | 535-7999-42L   | Pivot Hinge, Right - Green Sparkle [LE]          | 1   |
|    | 535-7999-01    | Pivot Hinge, Right - Wrinkle Black [Premium]     | 1   |
| 8  | 254-5042-00    | Spacer Nut, Hex, 1/2"OD, 1/4-20                  | 2   |
| 9  | 242-5084-00    | Washer, 1/2" I.D., 3/16" THK                     | 2   |
| 10 | 231-5072-00    | 1/4-20 X 1/2" Carriage Bolt                      | 2   |
| 11 | 545-5017-00    | Plastic Channel                                  | 2   |
| 12 | 545-9802-00    | Glass Rear Extrusion                             | 1   |
| 13 | 535-9596-42L   | Side Armor Left - Green Sparkle [LE]             | 1   |
|    | 535-9596-42R   | Side Armor Right - Green Sparkle [LE]            | 1   |
|    | 535-7297-02    | Side Armor - Wrinkle Black [Premium]             | 2   |
| 14 | 500-6146-00-07 | Ball Shooter Assembly                            | 1   |
| 15 | 535-5027-01    | Plunger Support Plate, Notched                   | 1   |
| 16 | 500-5026-32    | Flipper Button Assembly (Red)                    | 2   |
| 17 | 501-5018-173   | Coin Door 2-Chute No Emboss                      | 1   |
| 18 | 180-5160-01    | Flipper Switch, Single                           | 1   |
|    | 180-5164-01    | Flipper Switch, Double                           | 1   |
| 19 | 545-5072-03    | Grill - Speaker / Vent                           | 1   |
| 20 | 545-5072-02    | Grill - Speaker / Vent                           | 1   |
| 21 | 031-5007-01    | Speaker, Cabinet 8" Round, 4 ohm                 | 1   |
| 22 | 545-5090-00    | Cash Box - Plastic                               | 1   |



|    |             |                                             |   |
|----|-------------|---------------------------------------------|---|
| 23 | 535-5013-03 | Cash Box Cover                              | 1 |
| 24 | 535-7562-00 | Cash Box Lock Bracket Wire                  | 1 |
| 25 | 535-7772-00 | Hair Pin Clip                               | 1 |
| 26 | 500-5921-42 | Leg Assembly - Green Sparkle [LE]           | 4 |
|    | 500-5921-50 | Leg Assembly - Wrinkle Black [Premium]      | 4 |
| 27 | 516-0007-00 | Tilt Assembly                               | 1 |
| 28 | 820-76M2-03 | Decal, Cabinet Left, Jurassic Park LE       | 1 |
|    | 820-76M3-03 | Decal, Cabinet Left, Jurassic Park Premium  | 1 |
| 29 | 820-76M2-04 | Decal, Cabinet Right, Jurassic Park LE      | 1 |
|    | 820-76M3-04 | Decal, Cabinet Right, Jurassic Park Premium | 1 |
| 30 | 820-76M2-05 | Decal, Cabinet Front, Jurassic Park LE      | 1 |
|    | 820-76M3-05 | Decal, Cabinet Front, Jurassic Park Premium | 1 |
| 31 | 660-5001-00 | Playfield Glass [Premium]                   | 1 |
|    | 660-5053-00 | High Resolution Glass [LE]                  | 1 |
| 32 | 520-6967-72 | Cabinet Node Board                          | 1 |
| 33 | 031-5016-00 | Woofer 8" RD 4 OHM                          | 1 |
|    | 820-76M2-XX | Cabinet Decal Replacement Set               |   |
|    | 820-76M3-XX |                                             |   |

5.8 BALL SHOOTER ASSEMBLY


500-6146-00-07



| ID | Part Number | Description                       | Qty |
|----|-------------|-----------------------------------|-----|
| 1  | 535-5067-02 | Housing Assembly                  | 1   |
| 2  | 266-5001-07 | Compressed Spring (Long) - Orange | 1   |
| 3  | 242-5014-00 | Washer 3/8 ID x 5/8 OD x 1/16     | 3   |
| 4  | 515-6557-00 | Rod Assembly                      | 1   |
| 5  | 266-5010-00 | Compressed Spring (Short)         | 1   |
| 6  | 270-5012-00 | Retaining Ring, 3/8"              | 1   |
| 7  | 545-5276-00 | Rubber Tip                        | 1   |

5.9 AUTO LAUNCH ASSEMBLY


500-9818-01



| ID | Part Number | Description                      | Qty |
|----|-------------|----------------------------------|-----|
| 1  | 515-9689-00 | MAIN BRKT: AUTO-PLUNGER          | 1   |
| 2  | 535-0728-00 | KICKER ARM, AUTO-PLUNGER         | 1   |
| 3  | 270-5001-00 | RETAINING E-RING, 3/16" SHAFT OD | 1   |
| 4  | 545-5352-00 | NYLINER, 3/16" SHAFT             | 1   |
| 5  | 090-5044-ND | COIL - 23-800, NO DIODE          | 1   |
| 6  | 545-5411-00 | COIL SLEEVE                      | 1   |
| 7  | 266-5020-00 | COMPRESSION SPRING-CONICAL       | 1   |
| 8  | 530-7834-00 | PIN: KICKER ARM, AUTO-PLUNGER    | 1   |
| 9  | 232-5300-00 | SCREW, 8-32 X 1/4" PPH SEMS      | 4   |
| 10 | 530-7835-00 | PIVOT, AUTO-PLUNGER              | 1   |
| 11 | 545-5423-00 | NYLINER, 1/4" SHAFT, 4L1-FF      | 1   |
| 12 | 237-5937-02 | SCREW, 2-56 X 1/2" HWH MS        | 2   |
| 13 | 535-6539-00 | SWITCH BODY PROTECT PLATE        | 1   |
| 14 | 180-5157-01 | SHOOTER SWITCH - SHORT ARM       | 1   |
| 15 | 545-6268-00 | FISCHE PAPER                     | 1   |
| 16 | 535-0762-00 | COIL BRACKET-AUTOPLUNGER         | 1   |
| 17 | 515-6304-03 | PLUNGER / LINK ASSEMBLY          | 1   |
| 18 | 545-0762-00 | FISCHE PAPER: AUTO-LAUNCHER      | 1   |

## 5.10 BALL TROUGH ASSEMBLY


500-9820-00




| ID  | Part Number    | Description                        | Qty     |
|-----|----------------|------------------------------------|---------|
| 1   | 515-7811-00    | MAIN BRKT. BALL TROUGH             | 1       |
| 2   | 515-7812-00    | COIL BRACKET, BALL TROUGH          | 1       |
| 3   | 237-5975-04    | SCREW, 8-32 X 1/4" HWH SWAGE SERR  | 2       |
| 4   | 266-5020-00    | COMPRESSION SPRING-CONICAL         | 1       |
| 5   | 535-5203-03    | COIL RETAINING BRACKET             | 1       |
| 6   | 545-5076-01    | COIL SLEEVE                        | 1       |
| 7   | 240-5102-00    | 8-32 NYLON LOCK NUT                | 4       |
| 8   | 545-5105-00    | RUBBER BUMPER                      | 1       |
| 9   | 515-7309-01    | PLUNGER ASSEMBLY                   | 1       |
| 10  | 237-5909-00    | SCREW, 4-40 X 1/4" PPH SEMS        | 4       |
| 11  | 520-5344-00    | TROUGH BOARD #1 - ILED TRANSMITTER | 1       |
| 12  | 520-7001-00    | TROUGH BOARD #2 - RECEIVER         | 1       |
| 13  | 090-5004-ND    | COIL 27-1500 - NO DIODE            | 1       |
| 98* | 605-5006-00    | SHRINK TUBING 1/8"                 | .42 FT. |
| 99* | 036-5611-11-F5 | CABLE TROUGH OPTOS                 | 1       |

## 5.11 SLINGSHOT ASSEMBLY


500-9920-01



| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 515-5339-01 | SLINGSHOT BRACKET ASSEMBLY     | 1   |
| 2  | 090-5044-ND | COIL 26-1200 - NO DIODE        | 1   |
| 3  | 545-5031-00 | COIL SLEEVE                    | 1   |
| 4  | 535-5203-03 | COIL RETAINER BRACKET          | 1   |
| 5  | 232-5301-00 | 8-32 X 3/8 PPH MS EXT SEMS ZC  | 2   |
| 6  | 180-5231-00 | SWITCH SLING SHOT 2 LUG CENTER | 2   |
| 7  | 535-5045-00 | SWITCH PLATE                   | 2   |
| 8  | 237-5976-04 | 6-32 X 5/8 SLOT SER HWH SW     | 4   |
| 9  | 515-5340-01 | ARM & TIP ASSEMBLY             | 1   |
| 10 | 270-5002-00 | RETAINING RING - 1/4 DIA       | 2   |
| 11 | 515-5338-00 | PLUNGER & LINK ASSEMBLY        | 1   |
| 12 | 266-5020-00 | COMP SPRING CONICAL            | 1   |
| 13 | 036-5604-00 | 4" GENERIC JUMPER              | 2   |

**5.12 FLIPPER ASSEMBLY, LEFT****500-6543-12-ND**


| ID | Part Number    | Description                                                            | Qty |
|----|----------------|------------------------------------------------------------------------|-----|
| 1  | 515-6617-01    | FLIPPER BASE PLATE LEFT KIT W/ BRACKET MOUNT HARDWARE                  | 1   |
| 2  | 515-6308-01    | COIL STOP BRACKET                                                      | 1   |
| 3  | 180-5149-00    | SWITCH - END OF STROKE N/C                                             | 1   |
| 4  | 090-5032-ND    | COIL                                                                   | 1   |
| 5  | 269-5002-00    | SPRING WASHER                                                          | 1   |
| 6  | 535-7354-00    | SWITCH RETURN SPRING BRACKET                                           | 1   |
| 7  | 265-5035-00    | SPRING FLIPPER RETURN                                                  | 1   |
| 8  | 535-7356-00    | COIL SUPPORT BRACKET                                                   | 1   |
| 9  | 545-5388-00    | COIL SLEEVE, FLIPPER                                                   | 1   |
| 10 | 545-5070-00    | FLIPPER BAT BUSHING                                                    | 1   |
| 11 | 545-5428-00    | FLIPPER BUMPER PAD                                                     | 1   |
| 12 | 237-6144-00    | SET SCREW #10-32 x 3/4" SOCKET                                         | 2   |
| 13 | 515-7203-01    | PLUNGER/CRANK ASSEMBLY, LEFT                                           | 1   |
| 14 | 515-5133-06-06 | FLIPPER BAT AND SHAFT*                                                 | 1   |
|    | 500-6307-10    | FLIPPER REBUILD KIT, LEFT                                              |     |
|    |                | * Refer to game rubber chart for flipper rubber color and part number. |     |

**5.13 FLIPPER ASSEMBLY, RIGHT****LOWER: 500-6543-02-ND****UPPER: 500-6543-03-ND**


| ID | Part Number    | Description                                                            | Qty |
|----|----------------|------------------------------------------------------------------------|-----|
| 1  | 515-6617-00    | FLIPPER BASE PLATE RIGHT KIT W/ BRACKET MOUNTING HARDWARE              | 1   |
| 2  | 515-6308-01    | COIL STOP BRACKET                                                      | 1   |
| 3  | 180-5149-00    | SWITCH - END OF STROKE N/C                                             | 1   |
| 4  | 090-5032-ND    | COIL [LOWER]                                                           | 1   |
|    | 090-5020-30-ND | COIL [UPPER]                                                           | 1   |
| 5  | 269-5002-00    | SPRING WASHER                                                          | 1   |
| 6  | 535-7354-00    | SWITCH RETURN SPRING BRACKET                                           | 1   |
| 7  | 265-5035-00    | SPRING FLIPPER RETURN                                                  | 1   |
| 8  | 535-7356-00    | COIL SUPPORT BRACKET                                                   | 1   |
| 9  | 545-5388-00    | COIL SLEEVE, FLIPPER                                                   | 1   |
| 10 | 545-5070-00    | FLIPPER BAT BUSHING                                                    | 1   |
| 11 | 545-5428-00    | FLIPPER BUMPER PAD                                                     | 1   |
| 12 | 237-6144-00    | SET SCREW #10-32 x 3/4" SOCKET                                         | 2   |
| 13 | 515-7203-00    | PLUNGER/CRANK ASSEMBLY                                                 | 1   |
| 14 | 515-5133-06-06 | FLIPPER BAT AND SHAFT*                                                 | 1   |
|    | 500-6307-00    | FLIPPER REBUILD KIT, RIGHT                                             |     |
|    |                | * Refer to game rubber chart for flipper rubber color and part number. |     |

## 5.14 POP BUMPER ASSEMBLY

516-6784-XX




| ID | Part Number | Description              | Qty |
|----|-------------|--------------------------|-----|
| 1  | 520-5307-03 | POP BUMPER LED MODULE    | 1   |
| 2  | 545-5197-00 | BUMPER BODY              | 1   |
| 3  | 515-5085-00 | RING AND ROD ASSY        | 1   |
| 4  | 545-5607-00 | BUMPER SKIRT             | 1   |
| 5  | 266-5048-00 | BUMPER SKIRT COMP SPRING | 1   |
| 6  | 545-5195-00 | BUMPER BASE              | 1   |




| Part Number    | Description                    | Qty |
|----------------|--------------------------------|-----|
| 515-6459-01L   | BUMPER/RING TOP ASSY, W/ LED 1 | 1   |
| 515-6459-04-ND | BUMPER BOTTOM ASSY, NO DIODE   | 1   |


| ID | Part Number | Description                            | Qty |
|----|-------------|----------------------------------------|-----|
| 7  | 500-9934-01 | POP BUMPER SWITCH ASSY-2 - LUG-LEFT    | 1   |
| 8  | 240-5005-00 | 6-32 NYLON STOP NUT                    | 3   |
| 9  | 090-5044-ND | COIL - 26-1200                         | 1   |
| 10 | 237-5976-01 | #6-32 X 1/4" SHWH SWAGE ZN             | 2   |
| 11 | 240-5005-00 | #6-32 NYLON STOP NUT                   | 2   |
| 12 | 535-7347-00 | METAL YOKE STOP                        | 1   |
| 13 | 234-5101-00 | * 8 X 1/2 SLT                          | 6   |
| 14 | 530-5348-00 | PLUNGER, POP BUMPER                    | 1   |
| 15 | 266-5047-00 | COMPRESSION SPRING, POP BUMPER         | 1   |
| 16 | 545-5031-00 | COIL SLEEVE                            | 1   |
| 17 | 515-5939-00 | COIL BRACKET POP BUMPER ASSY           | 1   |
| 18 | 545-5609-00 | FIBER YOKE                             | 1   |
| 19 | 535-7346-00 | METAL YOKE                             | 1   |
| 20 | 237-5957-00 | #6-32 x 1-3/16" SPIRAL FIN SHANK SCREW | 3   |

**5.15 BALL GUIDE ASSEMBLY****511-2009-09**


| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 535-2039-09 | BALL GUIDE, JURASSIC PARK, -09 | 1   |
| 2  | 511-7962-00 | ONE WAY GATE ASM, BG MNT       | 1   |
| 3  | 237-6087-00 | 4-40 x 3/16 PFH MS - ZINC      | 2   |

**5.16 ONE WAY GATE ASSEMBLY****511-7962-00**

| ID | Part Number | Description                   | Qty |
|----|-------------|-------------------------------|-----|
| 1  | 535-2054-00 | BRACKET, ONE WAY GATE, BG MNT | 1   |
| 2  | 535-2055-00 | WIRE, ONE WAY GATE, BG MNT    | 1   |

**5.17 ORBIT OPTO ASSEMBLY****511-2753-00**


| ID | Part Number | Description                       | Qty |
|----|-------------|-----------------------------------|-----|
| 1  | 515-2041-00 | BRACKET, OPTOS                    | 1   |
| 2  | 515-0215-01 | LONG RANGE OPTO RECEIVER ASSEMBLY | 1   |
| 3  | 515-0215-00 | LONG RANGE OPTO EMITTER ASSEMBLY  | 1   |
| 4  | 237-5979-00 | SCREW, 4-40 X 3/8", PPH (ZINC)    | 4   |

**5.18 POP BUMPER GATE ASSEMBLY****511-7967-00**

| ID | Part Number | Description                      | Qty |
|----|-------------|----------------------------------|-----|
| 1  | 535-2067-00 | BRACKET, POP GATE, JURASSIC PARK | 1   |
| 2  | 535-2068-00 | WIRE, POP GATE, JURASSIC PARK    | 1   |

## 5.19 RIGHT RAMP ROLLUNDER ASSEMBLY


511-7963-00



| ID | Part Number | Description                     | Qty |
|----|-------------|---------------------------------|-----|
| 1  | 535-2056-00 | BRACKET, ROLLUNDER GATE, BG MNT | 1   |
| 2  | 180-5087-00 | SWITCH - GATE                   | 1   |
| 3  | 237-5937-02 | SCREW, 2-56 X 1/2" HWH MS       | 2   |
| 4  | 535-6539-00 | SWITCH BODY PROTECT PLATE       | 1   |
| 5  | 535-2057-00 | WIRE, ROLLUNDER GATE, BG MNT    | 1   |

## 5.20 RIGHT WIRE RAMP ASSEMBLY


511-7968-00



| ID | Part Number | Description                     | Qty |
|----|-------------|---------------------------------|-----|
| 1  | 180-5010-04 | MICRO-SWITCH                    | 1   |
| 2  | 515-2034-00 | WIRE RAMP, JURASSIC PARK, RIGHT | 1   |
| 3  | 535-6539-00 | SWITCH BODY PROTECT PLATE       | 1   |
| 4  | 237-5937-02 | SCREW, 2-56 X 1/2" HWH MS       | 2   |

## 5.21 STAINLESS STEEL UP-POST ASSEMBLY


500-9914-00



| ID | Part Number | Description                          | Qty |
|----|-------------|--------------------------------------|-----|
| 1  | 535-9248-00 | BRACKET                              | 1   |
| 2  | 535-5203-03 | COIL RETAINING BRACKET               | 2   |
| 3  | 090-5044-ND | COIL 26-1200 - NO DIODE              | 1   |
| 4  | 545-5847-00 | COIL SLEEVE                          | 1   |
| 5  | 280-5014-00 | ADJUSTABLE BUMPER/STOP               | 1   |
| 6  | 515-2073-00 | PLUNGER ASSEMBLY, UP-POST, STAINLESS | 1   |
| 7  | 266-5020-00 | COMPRESSION SPRING-CONICAL           | 1   |
| 8  | 232-5300-00 | SCREW, 8-32 X 1/4" PPH SEMS          | 4   |
| 9  | 240-5208-00 | 10-32 KEPS NUT                       | 1   |

## 5.22 MOTO 2-BANK CARRIAGE ASSEMBLY


511-2745-00



| ID | Part Number | Description                  | Qty |
|----|-------------|------------------------------|-----|
| 1  | 510-7767-00 | CARRIAGE ASM, RIVETED        | 1   |
| 2  | 626-5029-00 | FOAM PAD                     | 2   |
| 3  | 510-7768-00 | MOTO TARGET, RIVETED, 2"     | 1   |
| 4  | 240-5303-00 | 4-40 NYLON LOCK NUT          | 4   |
| 5  | 820-1088-50 | DECAL, JURASSIC PARK LE, -50 | 1   |
| 6  | 820-1088-51 | DECAL, JURASSIC PARK LE, -51 | 1   |

## 5.23 MOTO 2-BANK MAIN ASSEMBLY


500-1146-00



| ID | Part Number | Description                         | Qty |
|----|-------------|-------------------------------------|-----|
| 1  | 237-5604-00 | SCREW, 8-32 X 3/4 PPH MS, ZINC      | 2   |
| 2  | 041-5111-00 | MOTOR, 24 VDC, 12 RPM - CLUTCHED    | 1   |
| 3  | 237-5909-00 | SCREW, 4-40 X 1/4" PPH SEMS         | 2   |
| 4  | 180-5119-02 | MICRO-SWITCH - LIGHT ACTUATION      | 2   |
| 5  | 545-6029-00 | INSULATOR - FISH PAPER (SCOOP)      | 2   |
| 6  | 237-5937-02 | SCREW, 2-56 X 1/2" HWH MS           | 4   |
| 7  | 535-6539-00 | SWITCH BODY PROTECT PLATE           | 2   |
| 8  | 515-2014-00 | CRANK, MOTO TARGET                  | 1   |
| 9  | 237-6317-00 | 10-32 X 3/16 SS CUP POINT SET SCREW | 1   |
| 10 | 511-2745-00 | CARRIAGE ASM, MOTO TARGET, 2"       | 1   |
| 11 | 237-5832-00 | SCREW, 4-40 X 5/8" PPH SEMS         | 4   |
| 12 | 535-1990-00 | BRACKET, MOTO TARGET, GUIDE BLOCK   | 2   |
| 13 | 545-1087-00 | BLOCK, MOTO TARGET BEARING          | 2   |
| 14 | 237-5976-01 | SCREW, 6-32 X 1/4 HWH SWAGE         | 4   |
| 15 | 515-2012-00 | BRACKET, MOTO TARGET, MOTOR         | 1   |

## 5.24 PLASTIC 03 ASSEMBLY


511-2010-03



| ID | Part Number | Description                                    | Qty |
|----|-------------|------------------------------------------------|-----|
| 1  | 830-1034-03 | PLASTIC, JURASSIC PARK LE, -03                 | 1   |
| 2  | 254-5000-14 | NYLON SPACER - BLACK - 3/8 OD X .175 ID X 5/8" | 2   |
| 3  | 830-1034-87 | PLASTIC, JURASSIC PARK LE, -87                 | 1   |
| 4  | 242-5001-00 | #6 WASHER                                      | 2   |
| 5  | 232-5206-00 | SCREW, 6-32 X 1" PPH SEMS                      | 2   |
| 6  | 240-5005-00 | 6-32 NYLON STOP NUT                            | 2   |

## 5.25 PLASTIC 04 ASSEMBLY


511-2010-04



| ID | Part Number | Description                                    | Qty |
|----|-------------|------------------------------------------------|-----|
| 1  | 830-1034-04 | PLASTIC, JURASSIC PARK LE, -04                 | 1   |
| 2  | 830-1034-86 | PLASTIC, JURASSIC PARK LE, -86                 | 1   |
| 3  | 242-5001-00 | #6 WASHER                                      | 2   |
| 4  | 254-5000-14 | NYLON SPACER - BLACK - 3/8 OD X .175 ID X 5/8" | 2   |
| 5  | 232-5206-00 | SCREW, 6-32 X 1" PPH SEMS                      | 2   |
| 6  | 240-5005-00 | 6-32 NYLON STOP NUT                            | 2   |

## 5.26 PLASTIC 05 ASSEMBLY


511-2010-05



| ID | Part Number | Description                        | Qty |
|----|-------------|------------------------------------|-----|
| 1  | 240-5005-00 | 6-32 NYLON STOP NUT                | 4   |
| 2  | 242-5001-00 | #6 WASHER                          | 3   |
| 3  | 254-5008-05 | HEX SPACER - 7/8 "                 | 1   |
| 4  | 830-1034-83 | PLASTIC, JURASSIC PARK LE, -83     | 1   |
| 5  | 545-5070-00 | FLIPPER BUSHING                    | 1   |
| 6  | 283-5019-00 | 3-PIECE THRUST BEARING, 1/4" SHAFT | 1   |
| 7  | 237-5502-03 | SCREW, 6-32 X 1/2" PPH MS BLACK    | 3   |
| 8  | 830-1034-05 | PLASTIC, JURASSIC PARK LE, -05     | 1   |
| 9  | 232-5201-00 | SCREW, 6-32 X 3/8" PPH MS SEMS     | 1   |
| 10 | 550-5510-02 | HAT - TRIMMED - RED SB             | 1   |
| 11 | 520-7000-00 | SINGLE FLASH LED BOARD             | 1   |
| 12 | 232-5202-00 | SCREW, 6-32 X 1/2" PPH MS SEMS     | 1   |
| 13 | 270-5002-00 | RETAINING RING - 1/4"              | 1   |
| 14 | 511-2894-00 | HELICOPTER ASM                     | 1   |

## 5.27 PLASTIC 08 ASSEMBLY


511-2010-08



| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 830-1034-08 | PLASTIC, JURASSIC PARK LE, -08 | 1   |
| 2  | 242-5001-00 | #6 WASHER                      | 2   |
| 3  | 254-5008-05 | HEX SPACER - 7/8 "             | 1   |
| 4  | 232-5201-00 | SCREW, 6-32 X 3/8" PPH MS SEMS | 1   |

## 5.28 PLASTIC 09 ASSEMBLY


511-2010-09



| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 830-1034-09 | PLASTIC, JURASSIC PARK LE, -09 | 1   |
| 2  | 237-5809-00 | SCREW, #6 X 1/2" PTH A         | 1   |
| 3  | 550-5052-01 | MINI POST - CLEAR              | 1   |
| 4  | 545-5348-17 | 7/16 O.D. RUBBER RING - BLACK  | 1   |

## 5.29 PLASTIC 11 ASSEMBLY


511-2010-11



| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 830-1034-11 | PLASTIC, JURASSIC PARK LE, -11 | 1   |
| 2  | 237-5809-00 | SCREW, #6 X 1/2" PTH A         | 1   |
| 3  | 545-5348-17 | 7/16 O.D. RUBBER RING - BLACK  | 1   |
| 4  | 550-5052-01 | MINI POST - CLEAR              | 1   |

## 5.31 PLASTIC 15 ASSEMBLY


511-2010-15



| ID | Part Number | Description                         | Qty |
|----|-------------|-------------------------------------|-----|
| 1  | 254-5008-04 | HEX SPACER - 3/4 "                  | 1   |
| 2  | 242-5001-00 | #6 WASHER                           | 1   |
| 3  | 830-1034-15 | PLASTIC, JURASSIC PARK LE, -15      | 1   |
| 4  | 237-5871-00 | SCREW, 6-32 X 3/8" PFH 82° U/C ZINC | 1   |

## 5.30 PLASTIC 12 ASSEMBLY


511-2010-12



| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 830-1034-12 | PLASTIC, JURASSIC PARK LE, -12 | 1   |
| 2  | 237-5809-00 | SCREW, #6 X 1/2" PTH A         | 1   |
| 3  | 550-5052-01 | MINI POST - CLEAR              | 1   |
| 4  | 545-5348-17 | 7/16 O.D. RUBBER RING - BLACK  | 1   |

5.32 PLASTIC 16 ASSEMBLY


511-2010-16



| ID | Part Number | Description                        | Qty |
|----|-------------|------------------------------------|-----|
| 1  | 830-1034-16 | PLASTIC, JURASSIC PARK LE, -16     | 1   |
| 2  | 511-2010-23 | PLASTIC ASM, JURASSIC PARK LE, -23 | 1   |
| 3  | 242-5001-00 | #6 WASHER                          | 8   |
| 4  | 254-5008-02 | HEX SPACER - 5/8 "                 | 2   |
| 5  | 232-5201-00 | SCREW, 6-32 X 3/8" PPH MS SEMS     | 5   |
| 6  | 511-2010-24 | PLASTIC ASM, JURASSIC PARK LE, -24 | 1   |
| 7  | 511-2764-00 | RAPTOR ASM                         | 1   |
| 8  | 511-2887-01 | MINI OPTO ASM, PLASTIC MNT         | 1   |
| 9  | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK    | 2   |
| 10 | 511-2887-00 | MINI OPTO ASM, PLASTIC MNT         | 1   |
| 11 | 237-5502-03 | SCREW, 6-32 X 1/2" PPH MS BLACK    | 2   |
| 12 | 240-5005-00 | 6-32 NYLON STOP NUT                | 2   |
| 13 | 254-5008-11 | HEX SPACER - 1 1/4 "               | 1   |

5.33 PLASTIC 19 ASSEMBLY

511-2010-19




| ID | Part Number | Description                                    | Qty |
|----|-------------|------------------------------------------------|-----|
| 1  | 830-1034-19 | PLASTIC, JURASSIC PARK LE, -19                 | 1   |
| 2  | 232-5201-00 | SCREW, 6-32 X 3/8" PPH MS SEMS                 | 2   |
| 3  | 242-5001-00 | #6 WASHER                                      | 5   |
| 4  | 254-5008-02 | HEX SPACER - 5/8 "                             | 2   |
| 5  | 830-1034-25 | PLASTIC, JURASSIC PARK LE, -25                 | 1   |
| 6  | 550-5510-01 | HAT - TRIMMED - CLEAR SB                       | 1   |
| 7  | 520-7000-00 | SINGLE FLASH LED BOARD                         | 1   |
| 8  | 232-5202-00 | SCREW, 6-32 X 1/2" PPH MS SEMS                 | 1   |
| 9  | 240-5005-00 | 6-32 NYLON STOP NUT                            | 1   |
| 10 | 254-5000-14 | NYLON SPACER - BLACK - 3/8 OD X .175 ID X 5/8" | 2   |
| 11 | 830-1034-56 | PLASTICS, JURASSIC PARK LE, -56                | 1   |
| 12 | 237-6021-00 | SCREW, 6-32 X 7/8" PFH ZINC                    | 2   |



## 5.34 PLASTIC 23 ASSEMBLY


511-2010-23




| ID | Part Number | Description                                      | Qty |
|----|-------------|--------------------------------------------------|-----|
| 1  | 240-5303-00 | 4-40 NYLON LOCK NUT                              | 2   |
| 2  | 520-5307-00 | SINGLE LED PCB                                   | 2   |
| 3  | 237-5997-00 | SCREW, 4-40 X 3/8" PPH MS BLACK                  | 2   |
| 4  | 830-1034-23 | PLASTIC, JURASSIC PARK LE, -23                   | 1   |
| 5  | 254-5090-06 | PLASTIC SPACER #4 SCREW, 3/16" OD - 1/16" LENGTH | 2   |

## 5.35 PLASTIC 24 ASSEMBLY


511-2010-24




| ID | Part Number | Description                                      | Qty |
|----|-------------|--------------------------------------------------|-----|
| 1  | 830-1034-24 | PLASTIC, JURASSIC PARK LE, -24                   | 1   |
| 2  | 240-5303-00 | 4-40 NYLON LOCK NUT                              | 1   |
| 3  | 237-5997-00 | SCREW, 4-40 X 3/8" PPH MS BLACK                  | 1   |
| 4  | 520-5307-00 | SINGLE LED PCB                                   | 1   |
| 5  | 550-5052-01 | MINI POST - CLEAR                                | 1   |
| 6  | 237-5809-00 | SCREW, #6 X 1/2" PTH A                           | 1   |
| 7  | 254-5090-06 | PLASTIC SPACER #4 SCREW, 3/16" OD - 1/16" LENGTH | 1   |
| 8  | 545-5348-17 | 7/16 O.D. RUBBER RING - BLACK                    | 1   |

**5.36 PLASTIC 39 ASSEMBLY****511-2010-39**


| ID | Part Number | Description                        | Qty |
|----|-------------|------------------------------------|-----|
| 1  | 535-2097-00 | BRACKET, WATCH TOWER ROOF          | 1   |
| 2  | 830-1034-42 | PLASTIC, JURASSIC PARK LE, -42     | 1   |
| 3  | 830-1034-39 | PLASTIC, JURASSIC PARK LE, -39     | 1   |
| 4  | 830-1034-40 | PLASTIC, JURASSIC PARK LE, -40     | 1   |
| 5  | 830-1034-41 | PLASTIC, JURASSIC PARK LE, -41     | 1   |
| 6  | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK    | 4   |
| 7  | 077-5100-00 | LAYDOWN STANDARD SOCKET            | 1   |
| 8  | 113-5045-08 | MULTI-LED FLASHER, 5 VDC - WHITE   | 1   |
| 9  | 237-5012-00 | SCREW, 6-32 X 3/8" PPH 18-8 BLK OX | 1   |
| 10 | 240-5005-00 | 6-32 NYLON STOP NUT                | 1   |

**5.37 PLASTIC 44 ASSEMBLY****511-2010-44**


| ID | Part Number | Description                                | Qty |
|----|-------------|--------------------------------------------|-----|
| 1  | 510-7782-44 | RIVETED PLASTIC ASM, JURASSIC PARK LE, -44 | 1   |
| 2  | 830-1034-45 | PLASTICS, JURASSIC PARK LE, -45            | 1   |
| 3  | 830-1034-46 | PLASTIC, JURASSIC PARK LE, -46             | 1   |
| 4  | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK            | 4   |

**5.38 PLASTIC 47 ASSEMBLY****511-2010-47**


| ID | Part Number | Description                                | Qty |
|----|-------------|--------------------------------------------|-----|
| 1  | 510-7782-48 | RIVETED PLASTIC ASM, JURASSIC PARK LE, -48 | 1   |
| 2  | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK            | 2   |
| 3  | 830-1034-47 | PLASTIC, JURASSIC PARK LE, -47             | 1   |
| 4  | 520-5307-00 | SINGLE LED PCB                             | 1   |
| 5  | 240-5303-00 | 4-40 NYLON LOCK NUT                        | 1   |
| 6  | 237-5997-00 | SCREW, 4-40 X 3/8" PPH MS BLACK            | 1   |
| 7  | 113-5045-08 | MULTI-LED FLASHER, 5 VDC - WHITE           | 1   |
| 8  | 077-5100-00 | LAYDOWN STANDARD SOCKET                    | 1   |
| 9  | 237-5012-00 | SCREW, 6-32 X 3/8" PPH 18-8 BLK OX         | 1   |
| 10 | 240-5005-00 | 6-32 NYLON STOP NUT                        | 1   |

**5.39 PLASTIC 63 ASSEMBLY****511-2010-63**


| ID | Part Number | Description                                | Qty |
|----|-------------|--------------------------------------------|-----|
| 1  | 830-1034-61 | PLASTIC, JURASSIC PARK LE, -61             | 1   |
| 2  | 510-7782-63 | RIVETED PLASTIC ASM, JURASSIC PARK LE, -63 | 1   |
| 3  | 510-7782-62 | PLASTIC ASM, JURASSIC PARK LE, -62         | 1   |
| 4  | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK            | 3   |
| 5  | 242-5002-00 | #4 FLAT WASHER - 5/16" O.D.                | 1   |
| 6  | 535-2098-00 | BRACKET, ELECTRIC FENCE PLASTICS           | 1   |

**5.40 PLASTIC 64 ASSEMBLY****511-2010-64**


| ID | Part Number | Description                                | Qty |
|----|-------------|--------------------------------------------|-----|
| 1  | 830-1034-61 | PLASTIC, JURASSIC PARK LE, -61             | 1   |
| 2  | 510-7782-62 | RIVETED PLASTIC ASM, JURASSIC PARK LE, -62 | 1   |
| 3  | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK            | 3   |
| 4  | 242-5002-00 | #4 FLAT WASHER - 5/16" O.D.                | 1   |
| 5  | 535-2098-00 | BRACKET, ELECTRIC FENCE PLASTICS           | 1   |
| 6  | 510-7782-64 | RIVETED PLASTIC ASM, JURASSIC PARK LE, -64 | 1   |

**5.41 PLASTIC 81 ASSEMBLY****511-2010-81**


| ID | Part Number | Description                                      | Qty |
|----|-------------|--------------------------------------------------|-----|
| 1  | 510-7782-81 | RIVETED PLASTIC ASM, JURASSIC PARK LE, -81       | 1   |
| 2  | 240-5303-00 | 4-40 NYLON LOCK NUT                              | 2   |
| 3  | 520-5307-00 | SINGLE LED PCB                                   | 2   |
| 4  | 237-5997-00 | SCREW, 4-40 X 3/8" PPH MS BLACK                  | 2   |
| 5  | 830-1034-49 | PLASTIC, JURASSIC PARK LE, -49                   | 1   |
| 6  | 254-5007-02 | 1/4" SELF RETAINING SPACER                       | 2   |
| 7  | 240-5005-00 | 6-32 NYLON STOP NUT                              | 2   |
| 8  | 237-5503-01 | SCREW, 6-32 X 5/8" PPH MS BLACK                  | 2   |
| 9  | 254-5090-06 | PLASTIC SPACER #4 SCREW, 3/16" OD - 1/16" LENGTH | 2   |

**5.42 PLASTIC 82 ASSEMBLY****511-2010-82**

| ID | Part Number | Description                                      | Qty |
|----|-------------|--------------------------------------------------|-----|
| 1  | 510-7787-82 | RIVETED PLASTIC ASM, JURASSIC PARK PRO, -82      | 1   |
| 2  | 237-5997-00 | SCREW, 4-40 X 3/8" PPH MS BLACK                  | 2   |
| 3  | 240-5303-00 | 4-40 NYLON LOCK NUT                              | 2   |
| 4  | 520-5307-00 | SINGLE LED PCB                                   | 2   |
| 5  | 254-5090-06 | PLASTIC SPACER #4 SCREW, 3/16" OD - 1/16" LENGTH | 2   |

**5.43 LEFT HALFPIPE ASSEMBLY****500-2472-00**


| ID | Part Number | Description                        | Qty |
|----|-------------|------------------------------------|-----|
| 1  | 515-2036-00 | HALFPIPE, JURASSIC PARK, LEFT      | 1   |
| 2  | 515-0215-01 | LONG RANGE OPTO RECEIVER ASSEMBLY  | 1   |
| 3  | 515-0215-00 | LONG RANGE OPTO EMITTER ASSEMBLY   | 1   |
| 4  | 237-5880-00 | SCREW, #6 X 3/8 PPH T-25           | 4   |
| 5  | 511-2010-44 | PLASTIC ASM, JURASSIC PARK LE, -44 | 1   |

**5.44 LEFT RAMP ASSEMBLY****500-1168-00**

| ID | Part Number | Description                                    | Qty |
|----|-------------|------------------------------------------------|-----|
| 1  | 510-7780-00 | LEFT RAMP ASM, JURASSIC PARK, RIVETED          | 1   |
| 2  | 515-0215-00 | LONG RANGE OPTO EMITTER ASSEMBLY               | 2   |
| 3  | 515-0215-01 | LONG RANGE OPTO RECEIVER ASSEMBLY              | 2   |
| 4  | 237-5880-00 | SCREW, #6 X 3/8 PPH T-25                       | 8   |
| 5  | 830-1034-51 | PLASTICS, JURASSIC PARK LE, -51                | 1   |
| 6  | 240-5005-00 | 6-32 NYLON STOP NUT                            | 5   |
| 7  | 232-5204-00 | SCREW, 6-32 X 3/4" PPH SEMS                    | 3   |
| 8  | 242-5001-00 | #6 WASHER                                      | 2   |
| 9  | 254-5000-09 | NYLON SPACER - BLACK - 3/8 OD X .175 ID X 1/4" | 3   |
| 10 | 511-2010-82 | PLASTIC ASM, JURASSIC PARK LE, -82             | 1   |
| 11 | 232-5201-00 | SCREW, 6-32 X 3/8" PPH MS SEMS                 | 2   |
| 12 | 535-2207-00 | RAMP PROTECTOR, JURASSIC PARK                  | 1   |
| 13 | 820-1112-00 | RAMP DECAL, JURASSIC PARK                      | 1   |
| 14 | 040-5000-08 | WIRE CLIP, 3/4" OPEN TAB                       | 1   |

## 5.45 RIGHT RAMP ASSEMBLY


500-1166-80



| ID | Part Number | Description                         | Qty |
|----|-------------|-------------------------------------|-----|
| 1  | 510-7779-00 | JURASSIC PARK RIGHT RAMP, RIVETED   | 1   |
| 2  | 515-2028-00 | WIRE RAMP, JURASSIC PARK, HELIX     | 1   |
| 3  | 254-5008-07 | HEX SPACER - 2"                     | 1   |
| 4  | 254-5008-11 | HEX SPACER - 1 1/4 "                | 3   |
| 5  | 232-5201-00 | SCREW, 6-32 X 3/8" PPH MS SEMS      | 8   |
| 6  | 242-5005-00 | #8 WASHER                           | 4   |
| 7  | 254-5008-17 | HEX SPACER - 1 1/8 "                | 1   |
| 8  | 535-2026-00 | BRACKET, HELICAL RAMP RETAINER      | 1   |
| 9  | 240-5005-00 | 6-32 NYLON STOP NUT                 | 1   |
| 10 | 242-5001-00 | #6 WASHER                           | 1   |
| 11 | 511-7963-00 | RAMP ROLLUNDER GATE, ASM            | 1   |
| 12 | 237-6087-00 | 4-40 x 3/16 PFH MS - ZINC           | 2   |
| 13 | 040-5000-03 | 1/4" CABLE CLAMP                    | 1   |
| 14 | 237-5871-00 | SCREW, 6-32 X 3/8" PFH 82° U/C ZINC | 2   |
| 15 | 830-1034-52 | PLASTIC, JURASSIC PARK LE, -52      | 1   |
| 16 | 511-2010-81 | PLASTIC ASM, JURASSIC PARK LE, -81  | 1   |
| 17 | 830-1034-53 | PLASTICS, JURASSIC PARK LE, -53     | 1   |

## 5.46 RIGHT HALFPIPE ASSEMBLY


500-1182-80



| ID | Part Number | Description                    | Qty |
|----|-------------|--------------------------------|-----|
| 1  | 515-2035-00 | HALFPIPE, RIGHT, JURASSIC PARK | 1   |
| 2  | 820-1088-40 | DECAL, JURASSIC PARK LE, -40   | 1   |
| 3  | 820-1088-41 | DECAL, JURASSIC PARK LE, -41   | 1   |

## 5.47 HELICOPTER SENSOR ASSEMBLY


511-2895-00



| ID | Part Number | Description               | Qty |
|----|-------------|---------------------------|-----|
| 1  | 535-2214-00 | BRACKET, HELI MAG SENSOR  | 1   |
| 2  | 523-0020-00 | FISHCE PAPER, MAG SENSOR  | 1   |
| 3  | 520-8442-00 | MAG SENSOR BOARD          | 1   |
| 4  | 237-6355-00 | SCREW, 4-40 X 1/8" PPH MS | 2   |

## 5.48 T-REX MAIN ASSEMBLY

500-2478-00




| ID | Part Number | Description                                                                       | Qty |
|----|-------------|-----------------------------------------------------------------------------------|-----|
| 1  | 511-7975-00 | TREX HEAD ASM                                                                     | 1   |
| 2  | 511-2901-00 | TREX CRANK ASM                                                                    | 1   |
| 3  | 511-2902-00 | TREX MOTOR FRAME ASM                                                              | 1   |
| 4  | 511-7976-00 | TREX JAW ASSEMBLY                                                                 | 1   |
| 5  | 242-5001-00 | #6 WASHER                                                                         | 1   |
| 6  | 232-5200-00 | SCREW, 6-32 X 1/4" PPH SEMS                                                       | 1   |
| 7  | 283-5018-03 | 3/16 ID X 5/16 OD X 1/4 LG. BUNTING SAE 841 BRONZE FLANGED BEARING-PART #EF030504 | 4   |
| 8  | 535-2094-00 | BRACKET, BODY BOTTOM                                                              | 1   |
| 9  | 237-6317-00 | 10-32 X 3/16 SS CUP POINT SET SCREW                                               | 1   |
| 10 | 530-7834-00 | PIN: KICKER ARM, AUTO-PLUNGER                                                     | 1   |
| 11 | 535-2102-00 | BRACKET, PIVOT FRAME                                                              | 1   |
| 12 | 237-6192-00 | 8-32 X 3/16 X 1/4 SHOULDER SCREW                                                  | 3   |

|    |             |                                  |   |
|----|-------------|----------------------------------|---|
| 13 | 237-5976-01 | SCREW, 6-32 X 1/4 HWH SWAGE      | 6 |
| 14 | 545-1130-00 | LINK, MOTOR, TILT                | 1 |
| 15 | 237-5975-00 | SCREW, 8-32 X 3/8" HWH SWAGE ZN  | 1 |
| 16 | 535-2208-00 | SHIELD, TREX MOTOR               | 1 |
| 17 | 820-1088-90 | MOTOR HEAT WARNING LABEL         | 1 |
| 18 | 254-5007-03 | 3/4" SELF RETAINING SPACER       | 2 |
| 19 | 237-5009-00 | 6-32 x 1" PTH MS ZINC            | 2 |
| 20 | 830-1034-67 | PLASTIC, JURASSIC PARK LE, -67   | 1 |
| 21 | 550-5512-00 | JAW, T-REX                       | 1 |
| 22 | 237-6331-00 | SCREW, 4-40 X 1/4" PPH MS BLACK  | 3 |
| 23 | 530-7812-03 | PIVOT PIN-.188 DIA.              | 1 |
| 24 | 242-5010-00 | #10 WASHER, .50 O.D. X .047 THK  | 2 |
| 25 | 270-5001-00 | RETAINING E-RING, 3/16" SHAFT OD | 2 |




5.52 T-REX HEAD ASSEMBLY, TOP  
511-2903-00



| ID | Part Number | Description                 | Qty |
|----|-------------|-----------------------------|-----|
| 1  | 511-7978-00 | JAW SLIDER ASM              | 1   |
| 2  | 515-2049-00 | BRACKET, HEAD, TOP          | 1   |
| 3  | 535-2082-00 | BRACKET, HEAD SIDE          | 1   |
| 4  | 535-2082-01 | BRACKET, SIDE HEAD, RIGHT   | 1   |
| 5  | 237-5976-01 | SCREW, 6-32 X 1/4 HWH SWAGE | 4   |
| 6  | 545-5352-00 | NYLINER, 3/16" SHAFT        | 2   |
| 7  | 530-8025-00 | PIN, PIVOT                  | 1   |
| 8  | 266-5117-00 | SPRING, JAW                 | 1   |
| 9  | 232-5200-00 | SCREW, 6-32 X 1/4" PPH SEMS | 1   |

5.53 T-REX HEAD ASSEMBLY, BOTTOM  
511-2904-00




| ID | Part Number | Description                 | Qty |
|----|-------------|-----------------------------|-----|
| 1  | 523-0013-00 | FISCHE PAPER, LATCH MAGNET  | 1   |
| 2  | 523-0014-00 | FISCHE PAPER, MOUTH OPTO    | 1   |
| 3  | 520-8412-00 | OPTO RECEIVER, MOUTH        | 1   |
| 4  | 237-5913-00 | SCREW, 4-40 X 5/32" PPH MS  | 1   |
| 5  | 090-5092-00 | MINI COIL, 32-1800, LUGLESS | 1   |
| 6  | 530-1052-00 | MAGNET CORE, REMOVABLE      | 1   |
| 7  | 515-2050-00 | BRACKET, HEAD, BOTTOM       | 1   |



## 5.54 T-REX HEAD ASSEMBLY


511-7975-00



| ID | Part Number | Description                                                                       | Qty |
|----|-------------|-----------------------------------------------------------------------------------|-----|
| 1  | 511-2903-00 | TREX HEAD ASM, TOP                                                                | 1   |
| 2  | 511-2904-00 | TREX HEAD ASM, BOT                                                                | 1   |
| 3  | 090-5072-03 | MINIATURE COIL - 29-1400                                                          | 1   |
| 4  | 515-2057-00 | BRACKET, NECK ASM                                                                 | 1   |
| 5  | 515-2051-00 | COIL STOP, MINI COIL                                                              | 1   |
| 6  | 240-5005-00 | 6-32 NYLON STOP NUT                                                               | 1   |
| 7  | 237-5976-01 | SCREW, 6-32 X 1/4 HWH SWAGE                                                       | 2   |
| 8  | 283-5018-03 | 3/16 ID X 5/16 OD X 1/4 LG. BUNTING SAE 841 BRONZE FLANGED BEARING-PART #EF030504 | 2   |
| 9  | 545-1127-00 | LINK, NECK FOLLOWER                                                               | 1   |
| 10 | 237-6192-00 | 8-32 X 3/16 X 1/4 SHOULDER SCREW                                                  | 1   |
| 11 | 550-5514-00 | HEAD, TREX                                                                        | 1   |
| 12 | 237-5809-00 | SCREW, #6 X 1/2\" PTH A                                                           | 1   |
| 13 | 237-5500-01 | SCREW, 6-32 X 1/4\" PPH MS BLACK                                                  | 2   |
| 14 | 040-5001-08 | CABLE TIE                                                                         | 2   |

## 5.55 T-REX JAW ASSEMBLY


511-7976-00



| ID | Part Number | Description                  | Qty |
|----|-------------|------------------------------|-----|
| 1  | 520-8069-00 | PCB, IR OPTO EMITTER         | 1   |
| 2  | 237-5913-00 | SCREW, 4-40 X 5/32\" PPH MS  | 1   |
| 3  | 535-2081-00 | BRACKET, JAW                 | 1   |
| 4  | 820-1088-70 | DECAL, JURASSIC PARK LE, -70 | 1   |

## 5.56 T-REX JAW SLIDER ASSEMBLY


511-7978-00



| ID | Part Number | Description                           | Qty |
|----|-------------|---------------------------------------|-----|
| 1  | 530-1053-00 | PLUNGER, JAW                          | 1   |
| 2  | 232-5200-00 | SCREW, 6-32 X 1/4\" PPH SEMS          | 1   |
| 3  | 515-2052-00 | FRAME, JAW SLIDER                     | 1   |
| 4  | 545-1121-00 | GLIDE PLATE, JAW                      | 2   |
| 5  | 237-6315-00 | SCREW, 6-32 X 3/16\" 82° PFH U/C ZINC | 2   |

## 5.57 TRUCK SPINNER TOP ASSEMBLY


511-2011-00



| ID | Part Number | Description                   | Qty |
|----|-------------|-------------------------------|-----|
| 1  | 530-8018-00 | SHAFT, TRUCK SPINNER          | 1   |
| 2  | 515-2037-00 | BALL, STUDDED, TRUCK SPINNER  | 1   |
| 3  | 240-5102-00 | 8-32 NYLON LOCK NUT           | 1   |
| 4  | 242-5005-00 | #8 WASHER                     | 1   |
| 5  | 232-5301-00 | SCREW, 8-32 X 3/8" PPH SEMS   | 1   |
| 6  | 535-2043-00 | BRACKET, TRUCK MOUNTING PLATE | 1   |
| 7  | 237-5809-00 | SCREW, #6 X 1/2" PTH A        | 4   |
| 8  | 511-2908-00 | TRUCK ASM, LE                 | 1   |
| 9  | 545-5348-01 | 3/16 ID RUBBER RING           | 4   |

## 5.58 TRUCK DECAL ASSEMBLY


511-2908-00



| ID | Part Number | Description                  | Qty |
|----|-------------|------------------------------|-----|
| 1  | 550-5511-00 | SCULPT, TRUCK, JURASSIC PARK | 1   |
| 2  | 820-1088-80 | DECAL, JURASSIC PARK LE, -80 | 1   |
| 3  | 820-1088-81 | DECAL, JURASSIC PARK LE, -81 | 1   |
| 4  | 820-1088-82 | DECAL, JURASSIC PARK LE, -82 | 1   |
| 5  | 820-1088-83 | DECAL, JURASSIC PARK LE, -83 | 1   |
| 6  | 820-1088-85 | DECAL, JURASSIC PARK LE, -85 | 4   |
| 7  | 820-1088-86 | DECAL, JURASSIC PARK LE, -86 | 1   |
| 8  | 820-1088-87 | DECAL, JURASSIC PARK LE, -87 | 1   |
| 9  | 820-1088-88 | DECAL, JURASSIC PARK LE, -88 | 1   |
| 10 | 820-1088-89 | DECAL, JURASSIC PARK LE, -89 | 1   |

## 5.59 TRUCK SPINNER BOTTOM ASSEMBLY


511-2012-00



| ID | Part Number | Description                  | Qty |
|----|-------------|------------------------------|-----|
| 1  | 535-2041-00 | BRACKET, TRUCK SPINNER       | 1   |
| 2  | 545-5070-00 | FLIPPER BUSHING              | 1   |
| 3  | 237-5976-02 | SCREW, 6-32 X 3/8" HWH SWAGE | 3   |
| 4  | 520-8102-00 | OPTO BOARD, TRUCK SPINNER    | 1   |
| 5  | 232-5209-00 | SCREW, 6-32 X 3/16" PPH SEMS | 2   |

# 5.60 BACK PANEL ASSEMBLY

500-1167-00



| ID | Part Number | Description                             | Qty |
|----|-------------|-----------------------------------------|-----|
| 1  | 525-9730-00 | BACK PANEL, JURASSIC PARK, LE           | 1   |
| 2  | 500-2478-00 | TREX MAIN ASSEMBLY                      | 1   |
| 3  | 234-5000-00 | SCREW, #6 X 3/8" HWH                    | 4   |
| 4  | 077-5100-00 | LAYDOWN STANDARD SOCKET                 | 4   |
| 5  | 113-5045-08 | MULTI-LED FLASHER, 5 VDC - WHITE        | 4   |
| 6  | 040-5000-06 | 1/2" CABLE CLAMP                        | 2   |
| 7  | 040-5000-08 | WIRE CLIP, 3/4" OPEN TAB                | 2   |
| 8  | 234-5001-02 | SCREW, #6 X 1/2" HWH                    | 9   |
| 9  | 535-1926-00 | HANDLE, BACKPANEL, 2.5 INCH             | 1   |
| 10 | 242-5039-00 | WASHER - 13/64 ID X 5/8 OD X .105       | 2   |
| 11 | 232-5406-00 | SCREW, 10-32 X 1" PPH SEMS              | 2   |
| 12 | 240-5101-00 | 8-32 T-NUT                              | 4   |
| 13 | 237-5975-01 | SCREW, 8-32 x 1/2 HWH SLOT SERR SW ZINC | 4   |
| 14 | 237-5921-04 | FIN SHANK SCREW - 7/8" LG.              | 4   |
| 15 | 240-5005-00 | 6-32 NYLON STOP NUT                     | 4   |
| 16 | 234-5003-00 | SCREW, #6 X 3/4" HWH                    | 7   |

|    |              |                                          |   |
|----|--------------|------------------------------------------|---|
| 17 | 830-1034-65  | PLASTIC, JURASSIC PARK LE, -65           | 1 |
| 18 | 254-5007-03  | 3/4" SELF RETAINING SPACER               | 6 |
| 19 | 240-5002-00  | 6-32 T-NUT                               | 6 |
| 20 | 237-5009-00  | 6-32 x 1.5" PTH MS ZINC                  | 6 |
| 21 | 830-1034-66  | PLASTIC, JURASSIC PARK LE, -66           | 1 |
| 22 | 511-7983-00  | TREX TILT ASSMELBY                       | 1 |
| 23 | 242-5008-00  | WASHER, 1/4" ID X 1/2" OD X 1/16" THICK  | 1 |
| 24 | 520-6996-00  | PCB, SERIAL MOTOR CONTROLLER             | 1 |
| 25 | 550-5000-01N | INSERT CIRCLE .625 DIA STARBURST - CLEAR | 3 |
| 26 | 520-5307-00  | SINGLE LED PCB                           | 3 |
| 27 | 830-1034-85  | PLASTIC, JURASSIC PARK LE, -85           | 1 |
| 28 | 237-5809-00  | SCREW, #6 X 1/2" PTH A                   | 4 |
| 29 | 040-5000-03  | 1/4" CABLE CLAMP                         | 2 |
| 30 | 270-5002-00  | RETAINING RING - 1/4"                    | 1 |
| 31 | 520-8424-00  | STEPPER MOTOR DRIVER BOARD               | 1 |
| 32 | 820-1088-60  | DECAL, JURASSIC PARK LE, -60             | 1 |
| 33 | 820-1088-61  | DECAL, JURASSIC PARK LE, -61             | 1 |

# 6. SPECIFICATIONS

500-55M2-01

## SPECIFICATIONS, MECHANICAL, GAME SETUP

| Specification                                 | Imperial           | Metric               |
|-----------------------------------------------|--------------------|----------------------|
| Weight                                        | 210 lbs            | 96 kg                |
| Max dimensions, leg levers extended (h, w, d) | 78 x 27.75 x 57 in | 198 x 70.5 x 145 cm  |
| Minimum game dimensions (h, w, d)             | 76 x 27.75 x 57 in | 193 x 70.5 x 145 cm  |
| Minimum room dimensions per game (h, w, d)    | 80 x 36 x 84 in    | 203 x 91 cm x 214 cm |

- (h, w, d) = height, width, depth.

## SPECIFICATIONS, MECHANICAL, BOXED

| Specification                  | Imperial          | Metric            |
|--------------------------------|-------------------|-------------------|
| Weight, boxed (without pallet) | 230 lbs           | 105 kg            |
| Box dimensions (h, w, d)       | 56.5 x 31 x 31 in | 144 x 79 x 79 cm  |
| Minimum dimensions (h, w, d)   | 76 x 26 x 57 in   | 193 x 66 x 145 cm |

- (h, w, d) = height, width, depth.

## SPECIFICATIONS, ELECTRICAL

| Specification                       | North America - 120VAC | International - 240VAC  |
|-------------------------------------|------------------------|-------------------------|
| Line Voltage, Nominal               | 120 VAC                | 240 VAC                 |
| Line Voltage Range                  | 90 VAC - 250 VAC       | 90 VAC - 250 VAC        |
| Line Frequency *                    | 60 Hz                  | 50 Hz, 60 Hz            |
| Line Power, Current - attract mode  | 70 W, 0.6 A @ 120 VAC  | 70 W, 0.3 A @ 240 VAC   |
| Line Power, Current - nominal       | 360 W, 3 A @ 120 VAC   | 360 W, 1.5 A @ 240 VAC  |
| Line Power, Current - peak, <100 ms | 540 W, 4.5 A @ 120 VAC | 540 W, 2.25 A @ 240 VAC |

\* NOTE: Games designed for 60hz operation (e.g. North America games) will not function correctly on 50hz power and vice versa.


**WARNING:** Overloading electrical supply circuits is dangerous. Do not overload circuits. To calculate the maximum number of games for a circuit, check circuit amperage rating and divide by the game Nominal Line Power Current rating for your line voltage. For example, a 15A 120V household circuit,  $15/3 \text{ A}$  (nominal current) = 5 games maximum.

## SPECIFICATIONS, ENVIRONMENT

|                              | Minimum      | Maximum            |
|------------------------------|--------------|--------------------|
| Temperature, Operating       | 32 °F / 0 °C | 104°F / 40 °C      |
| Temperature, Storage         | 32 °F / 0 °C | 104°F / 40 °C      |
| Relative Humidity, Operating | 5%           | 95% non-condensing |
| Relative Humidity, Storage   | 5%           | 95% non-condensing |

- (a) "The appliance has to be placed in a horizontal position."
- (b) "This appliance is not to be cleaned by a Water Jet."
- (i) "Do not locate this appliance in an area where a Water Jet is used."
- (ii) "Do not clean this appliance with a Water Jet."
- (c) If the supply cord is damaged, it must be replaced with the same cord available from the manufacturer or its service agent.

## 6.1 GAME DIMENSIONS



## 6.2 WARRANTY

500-55M2-01

Stern Pinball machines are assembled in Elk Grove Village, Illinois, USA; each pinball machine has unique characteristics that make it a one-of-a-kind American-made product. Each machine will have variations in appearance resulting from differences in the machine's particular wood parts, individual silk screened art and mechanical assemblies. Stern Pinball has inspected each game element to insure it meets stringent quality and playability standards.

### STERN PINBALL INC LIMITED WARRANTY

Stern Pinball Inc ("SELLER") warrants only to the initial purchaser of its products that the items listed below are free from defects in material and workmanship under normal use and service for the warranty period specified:

- Printed circuit boards (game logic): 2 months
- Dot Matrix / LCD Display: 9 months

No other parts of seller's product are warranted.

Warranty periods are effective from the initial date of shipment from seller to its authorized distributors.

Seller's sole liability shall be, at its option, to repair or replace products which are returned to seller during the warranty periods specified, provided:

1. Seller is notified promptly upon discovery by purchaser that stated products are defective.
2. Such products are properly packaged and then returned freight prepaid, to seller's plant.

This warranty does not apply to any parts damaged during shipment and/or due to improper handling, or due to improper installation or usage, or alteration. In no event shall the seller be liable for any anticipated profits, loss of profits, loss of use, accidental or consequential damages, or any other losses incurred by the customer in connection with the purchase of a Stern Pinball Inc Product.

### WARRANTY DISCLAIMER

Except as specifically provided in a written contract between seller and purchaser, there are no other warranties, express or implied, including any implied warranties of merchantability or fitness for a particular purpose.

This Game Service Manual and all other documents relating to this product, playfield components, features, rules, programming, and operation are subject to change without notice (Service Bulletins, if applicable, available through official Stern Pinball website).

### ATTENTION! IMPORTANT WARRANTY INFORMATION

**The electronics system, node network architecture, mechanical devices and associated software control systems in this pinball machine are designed to work with genuine Stern Pinball accessories and devices.**

**Installation of non-authorized accessories, lamps, LED's, motors or other devices or modification of electro-mechanical devices may damage the system and will void your warranty.**

## 6.3 WARNINGS, COMPLIANCE, AND LEGAL NOTICES

### PHOTOSENSITIVE SEIZURES HEALTH WARNING



A very small percentage of people may experience a seizure when exposed to certain visual images, including flashing lights or patterns. Even people with no history of seizures of epilepsy may have an undiagnosed condition that can cause "photosensitive epileptic seizures" due to certain visual images, flashing lights or patterns. Symptoms can include lightheadedness, altered vision, eye or face twitching, jerking or shaking of arms or legs, disorientation, confusion, momentary loss of awareness, and loss of consciousness or convulsions that can lead to injury from falling down or striking nearby objects.

IMMEDIATELY STOP PLAYING AND CONSULT A DOCTOR IF YOU EXPERIENCE ANY OF THESE SYMPTOMS.

### PARTS SUBSTITUTIONS



For safety and reliability, substitute parts and equipment modifications are not recommended and may void any and all warranties. Use of Non-Stern Pinball Inc Parts or Modifications of game circuitry may adversely affect game play or game safety. Transport pinball machines with hinged backbox in the down position only! Always take great care when servicing any game. Always read the service manual before replacing or servicing components. Substitutions of parts or equipment modifications may void FCC type acceptance.

Always disconnect the line voltage before servicing. Some parts may remain energized when unplugged. Take great caution when servicing any electrical components.

### FCC CLASS A SUBPART J COMPLIANCE



This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

### RF INTERFERENCE NOTICE

The cable harness placements, ground strap routing, and other shielding have been designed to keep RF radiation and conduction within levels accepted by FCC rules. To maintain these levels, factory harness position, shielding, and ground straps must be installed in their factory locations should they become disconnected during maintenance.

### COPYRIGHT AND INTELLECTUAL PROPERTY NOTICE

This document and the data disclosed herein or herewith is not to be reproduced (Except where noted), used, or otherwise disclosed in whole or in part to anyone without written consent of Stern Pinball Inc.

Products in this manual, the company name and devices and the design of the manual itself are protected by federal patents (and patents pending), design registrations, trademarks, and copyrights. Action will be taken in the event of infringement or imitation. The right is reserved to change specifications without prior notice.





**1-800-KICKERS**  
**PARTS.SERVICE@STERNPINBALL.COM**  
**WWW.STERNPINBALL.COM**  
**FACEBOOK.COM/STERNPINBALL**

JURASSIC PARK LE #500-55M2-01  
JURASSIC PARK PREMIUM #500-55M3-01  
MANUAL #780-50M2-00

