

ALPINE CLUB COIL CHART

NOTICE:

THIS GAME OPERATES ON 24 VOLTS. WHEN ORDERING REPLACEMENT TRANSFORMERS, MOTORS, COILS OR METERS --- MAKE SURE TO SPECIFY CORRECT PART NUMBERS.

NUMBERS	DESCRIPTION	LOCATION
14 A 7754	SCORE MOTOR - 60 CYCLE	MECH. PANEL
14 A 7756	SCORE MOTOR - 50 CYCLE	MECH. PANEL
15 A 6771	TRANSFORMER - 60 CYCLE	MECH. PANEL
15 A 6773	TRANSFORMER - 50 CYCLE	MECH. PANEL
20 A 8796	24 VOLT METER	MECH. PANEL
<u>SOLENOID COILS</u>		
A 22-550	BALL RELEASE	PLAYFIELD
A 23-600	BALL COUNT UNIT STEP UP REPLAY UNIT STEP UP	INSERT INSERT
A 23-650	ROLLOVER ADVANCE UNIT STEP UP CLIMBER ADVANCE UNIT STEP UP NUMBER MATCH UNIT STEP UP	PLAYFIELD INSERT INSERT
A 26-1350	EXTRA BALL GATE	PLAYFIELD
A2-23-750	KNOCKER	CABINET
B 26-800	BALL COUNT UNIT RESET REPLAY UNIT RESET SCORE DRUM UNIT (4 REQ'D.)	INSERT INSERT INSERT
C 2-26-800	LARGE BELL	CABINET
D 24-1600	BANK RESET	MECH. PANEL
FL 21-375/ 28-400	FLIPPER (4 REQ'D.)	PLAYFIELD
G 22-550	JET BUMPER (4 REQ'D.)	PLAYFIELD
G 23-750	EJECT POCKET (2 REQ'D.) AUTOMATIC KICKERS (2 REQ'D.)	PLAYFIELD PLAYFIELD
<u>RELAY COILS</u>		
M 23-300	FLAG RELAY	INSERT
M 29-1100	CLIMBER ADVANCE RELAY 1 POINT RELAY 10 POINT RELAY 100 POINT RELAY SCORE RESET RELAY OUTHOLE RELAY TARGET RELAY GATE RELEASE RELAY NO. 1 BUMPER RELAY NO. 2 BUMPER RELAY ROLLOVER ADVANCE RELAY 10th POSITION RELAY	INSERT INSERT INSERT INSERT INSERT PLAYFIELD PLAYFIELD PLAYFIELD PLAYFIELD PLAYFIELD PLAYFIELD PLAYFIELD
M 30-1400	CHANGE RELAY	PLAYFIELD
M 36-5500	25¢ RELAY 10¢ RELAY	MECH. PANEL MECH. PANEL
Z 27-1000	EJECT RELAY RESET RELAY	MECH. PANEL MECH. PANEL

- continued -

ALPINE CLUB COIL CHART

NUMBER	DESCRIPTION	LOCATION
Z 28-1200	LOCK RELAY GATE RELAY SET UP RELAY ON GREEN RELAY ON RED RELAY	MECH. PANEL PLAYFIELD PLAYFIELD PLAYFIELD PLAYFIELD
Z 35-4200	REPLAY RELAY COIN RELAY	MECH. PANEL MECH. PANEL
<u>RELAY BANK COILS</u>		
X 27-500	TILT RELAY	MECH. PANEL
X 27-700	GAME RELAY GAME OVER RELAY 300 RELAY 500 RELAY	MECH. PANEL MECH. PANEL MECH. PANEL MECH. PANEL