

"ROCKET III" #800
REPLAY MODEL ADJUSTMENTS

PLAYFIELD PANEL ADJUSTMENTS:

The playfield panel can be made more conservative towards scoring by moving the posts under the (2) plastic shields with slotted holes at bottom of panel, and/or the post between mushroom bumper and thumper bumper at right side of panel. Spotting holes are provided for the movement of these posts and a card showing them in conservative positions will be found in game.

NOTE--Scoring potential can also be decreased by turning out rear leg levelers to increase pitch of game from front to rear. This will also help to cut down game playing time, if it is desired.

BELL ADJUSTMENT PLUG:

Located on back box insert. This plug provides positions to ring bell for 10 point scores, 100 point scores, or both 10 and 100 point scores.

HI SCORE ADJUSTMENT PLUGS:

Located on back box insert. These (2) plugs combine to provide a wide range of coverage to award replays or added balls,* at various pre-set scores. Recommended plug settings corresponding to score cards shipped with game will be found on score adjustment chart inside back door.

ADVANCE FEATURE ADJUSTMENT PLUG:

Located on mounting board. This plug provides positions to award points, replays or added ball* for advance feature scoring.

ADVANCE FEATURE AWARD ADJUSTMENT PLUG:

Located on mounting board. This plug provides positions for amount of points (100-200-300) or replays (1-2-3) to be awarded for advance feature scoring. NOTE: - When Add-A-Ball conversion kit is installed, only position (1) can be used.

HI SCORE FEATURE ADJUSTMENT PLUG:

Located on mounting board. This plug provides positions to award replays or added balls * for hi-scores.

BALLS PER GAME ADJUSTMENT PLUG:

Located on mounting board. This plug provides positions to operate game on 7, 5, or 3 ball play.

MATCH FEATURE ADJUSTMENT PLUG:

Located on mounting board. This plug provides positions to turn match number feature on or off.

2nd & 3rd COIN CHUTE ADJUSTMENT PLUG:

Located on mounting board. This plug provides positions to give 2 to 6 plays per coin thru 2nd and 3rd coin chutes.

1st COIN CHUTE ADJUSTMENT PLUG:

Located on alternator unit on mounting board. This plug provides positions to give 1 play per coin or 1 play per 2 coins thru 1st coin chute.

*When Add-A-Ball conversion kit is used.