

A L P I N E C L U B

A D J U S T M E N T S H E E T

NO. MATCH ON-OFF JACK,

located in back box. When plug is in 'ON' position, number will pay 10% or 1 game in 10 for one player matching test number in point score to number that appears on back glass when game is over. In 'OFF' position, match lites will not lite on completion of game.

10¢ ADJUSTMENT JACK,

Located on panel, will provide 1 or 2 plays for 1 coin. Insert phone tip in female jack opposite number of desired plays.

25¢ ADJUSTMENT JACK,

located on panel, will provide 2-3-4- or 5 plays for 25¢. Insert phone tip in female jack opposite number of desired plays.

3-5 BALL ADJUSTMENT JACK,

located in back box. For 3 ball play, insert plug in 3 ball position.

THE POWER TRANSFORMER,

located on panel, is equipped with a secondary tap. If your game is on location with extremely low line voltage, remove lead from lug marked 24 V. and solder to alternate lug marked 'HIGH'. This will boost secondary voltage by approximately 4 volts.

LEG LEVELERS,

are provided for two purposes - 1st to level game on location, 2nd to increase pitch for game percentaging, If it is desired to speed up play or decrease score, ~~raise~~ rear leg levelers to increase pitch.