

Jetsons Solenoid List

SOL #	FUNCTION	WIRE COLOR	DRIVER	COIL #	BANK #	FUSE
0	Knocker (optional)		SOL0	23-800	0	F1 3A Slo
1	Shaker Motor (optional)		SOL1		0	F1 3A Slo
2	Right Flipper Low	Orange-Green	SOL2	FL-11629	0	F1 3A Slo
3	Right Flipper High Center	Orange-Violet	SOL3	FL-11629	0	F1 3A Slo
4	Ball Trough Load	Orange-Black	SOL4	26-1200	0	F1 3A Slo
5	Ball Launch	Orange-Gray	SOL5	23-800	0	F1 3A Slo
6	Left Flipper High Center	Orange-White	SOL6	FL-11629	0	F1 3A Slo
7	Left Flipper Low	Orange-Blue	SOL7	FL-11629	0	F1 3A Slo
8	Scoop	Blue-Green	SOL8	23-800	1	F2 3A Slo
9	Left Slingshot	Blue-Red	SOL9	23-800	1	F2 3A Slo
10	Right Slingshot	Blue-Gray	SOL10	23-800	1	F2 3A Slo
11	Not Used	Not Used	SOL11	Not Used	1	F2 3A Slo
12	Not Used	Not Used	SOL12	Not Used	1	F2 3A Slo
13	Not Used	Not Used	SOL13	Not Used	1	F2 3A Slo
14	Not Used	Not Used	SOL14	Not Used	1	F2 3A Slo
15	Not Used	Not Used	SOL15	Not Used	1	F2 3A Slo
16	Up Post	Violet-Black	SOL16	AE-27-1200	2	F3 3A Slo
17	Lower Pop Bumper	Violet-Green	SOL17	23-800	2	F3 3A Slo
18	Left Pop Bumper	Violet-White	SOL18	23-800	2	F3 3A Slo
19	Saucer Kick Out	Violet-Red	SOL19	23-800	2	F3 3A Slo
20	Right Pop Bumper	Violet-Gray	SOL20	23-800	2	F3 3A Slo
21	Not Used	Not Used	SOL21	Not Used	2	F3 3A Slo
22	Not Used	Not Used	SOL22	Not Used	2	F3 3A Slo
23	Not Used	Not Used	SOL23	Not Used	2	F3 3A Slo

Driver Transistors IRL540

Feb. 11, 2019 Ken Layton